Product data sheet

Specifications

multifunction relay, Harmony Timer Relays, 8A, 2CO, 0.05s to 999h asymmetrical on delay and off delay 24 to 240V AC DC

RENF22R2MMW

Product availability: Stock - Normally stocked in distribution facility

Main

Range of Product	Harmony Timer Relays
Product or Component Type	NFC timer relay
Device short name	RENF22
App for product	Ecostruxure Industrial Device downloadable from Google Play store or Apple Store)

Complementary

Discrete output type	Relay
nominal output current	8 A
Contacts type and composition	2 C/O timed contact, cadmium free 1 C/O timed and instantaneous contact, cadmium free
Time delay type	Power on-delay On-delay and off-delay Pulse delay Asymmetrical on-delay and off-delay Interval Off-delay Symmetrical flashing Safe-guard Star-delta Asymmetrical flashing Bistable
Time delay range	0.05 s...999 h
Product Compatibility	NFC enabled mobile device
Control Type	Without test button
[Us] rated supply voltage	24...240 V AC/DC
Release input voltage	<= 2.4 V
Voltage range	0.85...1.1 Un
Maximum RF power transmitted	0.0002 mW
NFC operating frequency	13.56 MHz
Supply frequency	50...60 Hz +/- 5 %
Connections - terminals	Screw terminals, 1 x 0.5...1 x 3.3 mm² AWG 20...AWG 12) solid without cable end Screw terminals, 2 x 0.5...2 x 2.5 mm² AWG 20...AWG 14) solid without cable end Screw terminals, 1 x 0.2...1 x 2.5 mm² AWG 24...AWG 14) flexible with cable end Screw terminals, 2 x 0.2...2 x 1.5 mm² AWG 24...AWG 16) flexible with cable end
Tightening torque	5.3…8.9 lbf.in (0.6…1 N.m) IEC 60947-1 5.3…8.8 lbf.in (0.6…1.0 N.m) IEC 60947-1
Housing material	Self-extinguishing

Price is “List Price” and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Repeat accuracy	+/- 0.2 % 10 s...999 h +/- 0.5 % 100 ms...10 s +/- 0.7 % 50...100 ms
Temperature Drift	+/- 0.05 %/°C
Voltage drift	+/- 0.2 %/V
Setting accuracy of time delay	+/- 1 % 1...999 h 77 °F (25 °C) +/- 2 % 1...3600 s 77 °F (25 °C) +/- 20 ms 100 ms...10 s 77 °F (25 °C) +/- 30 ms 50...100 ms 77 °F (25 °C)
Time delay type	Power on-delay - A- Power on-delay relay On-delay and off-delay - Ac- On-delay and off-delay relay w/ control signal Pulse delay - Ad- Pulse delayed relay w/ control signal Pulse delay - Ah- Pulse delayed relay (single cycle) w/ control signal On-delay and off-delay - Ak- Asymmetrical on-delay and off -delay relay w/ control signal Power on-delay - At- Power on-delay relay w/ pause/summation (Y1) Interval - B- Single interval relay w/ control signal Interval - Bw- Double interval relay w/ control signal Off-delay - C- Off-delay relay w/ control signal Symmetrical flashing - D- Symmetrical flashing relay (starting pulse-off) Symmetrical flashing - Di- Symmetrical flashing relay (starting pulse-on) Symmetrical flashing - Dt- Symmetrical flashing relay (starting pulse-off) w/ pause/summation (Y1) Symmetrical flashing - Dit- Symmetrical flashing relay (starting pulse-on) w/ pause/summation (Y1) Interval - H- Interval relay Interval - Ht- Interval relay w/ pause/summation (Y1) Asymmetrical flashing - Li- Asymmetrical flashing relay (starting pulse-on) Asymmetrical flashing - Lt- Asymmetrical fl ashing relay (starting pulse-off) w/ pause/summation (Y1) Asymmetrical flashing - Lit- Asymmetrical flashing relay (starting pulse-on) w/ pause/summation (Y1) Safe-guard - N- Safe-guard relay Safe-guard - O- Delayed Safe-guard relay Pulse delay - P- Pulse delayed relay w/ fixed pulse length Pulse delay - Pt- Pulse delayed relay w/ fixed pulse length and pause/summation Star-delta - Qt- Star-delta relay (2 CO outputs w/ split common) Star-delta - Qtt- Star-delta relay (2 CO outputs w/ split common) w/ pause/summation (Y1) Bistable - Tl- Bistable relay w/ control signal on Bistable - Tt- Retriggerable bistable relay w/ control signal on Interval - W- Interval relay w/ control signal off Asymmetrical flashing - L- Asymmetrical flashing relay (starting pulse-off)
Control signal pulse width	100 ms with load in parallel 60 ms no-load
Insulation resistance	100 MOhm 500 V DC IEC 60664-1
Recovery time	120 ms on de-energisation
Power consumption in VA	3 VA 240 V AC
Power consumption in W	1.5 W 240 V DC 0.6 W 24 V DC
Switching capacity in VA	2000 VA
Minimum switching current	10 mA 5 V
Maximum switching current	8 A
Maximum switching voltage	250 V
Electrical durability	100000 cycles for resistive load, 8 A at 250 V, AC
Mechanical durability	10000000 cycles
Rated impulse withstand voltage	5 kV 1.2/50 µs IEC 60664-1
power on delay	100 ms
Creepage distance	4 kV/3 IEC 60664-1
Overvoltage category	III conforming to IEC 60664-1

Safety reliability data	MTTFd = 227.5 years 100 % duty cycle continuous operating condition at 30 °C
Mounting position	Any position
Mounting support	35 mm DIN rail conforming to IEC 60715
status LED	Un, green LED steady)power ON R1, amber LED steady)relay energised R2, amber LED steady)relay energised Pairing, green LED steady)communication status Un, green LED fast blinking)diagnosis mode R1, amber LED blinking)timing in progress R2, amber LED blinking)timing in progress
Maximum communication distance	10 mm
Function available	A- Power on-delay relay-2 C/O Ac- On-delay and off-delay relay w/ control signal-2 C/O Ad- Pulse delayed relay w/ control signal-2 C/O Ah- Pulse delayed relay (single cycle) w/ control signal-2 C/O Ak- Asymmetrical on-delay and off -delay relay w/ control signal-2 C/O At- Power on-delay relay w/ pause/summation (Y1)-2 C/O B- Single interval relay w/ control signal-2 C/O Bw- Double interval relay w/ control signal-2 C/O C- Off-delay relay w/ control signal-2 C/O D- Symmetrical flashing relay (starting pulse-off)-2 C/O Di- Symmetrical flashing relay (starting pulse-on)-2 C/O Dt- Symmetrical flashing relay (starting pulse-off) w/ pause/summation (Y1)-2 C/O Dit- Symmetrical flashing relay (starting pulse-on) w/ pause/summation (Y1)-2 C/O H- Interval relay-2 C/O Ht- Interval relay w/ pause/summation (Y1)-2 C/O Li- Asymmetrical flashing relay (starting pulse-on)-2 C/O Lt- Asymmetrical fl ashing relay (starting pulse-off) w/ pause/summation (Y1)-2 C/O Lit- Asymmetrical flashing relay (starting pulse-on) w/ pause/summation (Y1)-2 C/O N- Safe-guard relay-2 C/O O- Delayed Safe-guard relay-2 C/O P- Pulse delayed relay w/ fixed pulse length-2 C/O Pt- Pulse delayed relay w/ fixed pulse length and pause/summation-2 C/O Qt- Star-delta relay (2 CO outputs w/ split common)-2 C/O Qtt- Star-delta relay (2 CO outputs w/ split common) w/ pause/summation (Y1)-2 C/O Tl- Bistable relay w/ control signal on-2 C/O Tt- Retriggerable bistable relay w/ control signal on-2 C/O W- Interval relay w/ control signal off-2 C/O L- Asymmetrical flashing relay (starting pulse-off)-2 C/O
Operating system	Androidversion >= V7.0 IOSversion >= V14.5
Width	0.9 in (22.5 mm)
Net Weight	0.1993 lb(US) (0.0904 kg)
Number of functions	28

Environment

Immunity to microbreaks	10 ms
Dielectric strength	2.5 kV 1 mA/1 minute 50 Hz between relay output and power supply with basic insulation basic insulation
Standards	IEC 61000-6-1 IEC 61000-6-2 IEC 61000-6-4 EN 61812-1 IEC 61000-6-3
Directives	2014/35/EU - low voltage directive 2014/53/EU - radio equipment directive 2014/30/EU - electromagnetic compatibility

Product Certifications	CE CSA KC UL CCC EAC DNV-GL
Ambient air temperature for operation	-4…140 °F (-20…60 °C)
Ambient Air Temperature for Storage	-40…158 °F (-40…70 °C)
IP degree of protection	IP40 housing: conforming to IEC 60529 IP40 front face: conforming to IEC 60529 IP20 terminals: conforming to IEC 60529
Pollution degree	3 IEC 60664-1
Vibration resistance	20 m/s² (f= 10…150 Hz) conforming to IEC 60068-2-6
Shock resistance	15 gn not operating 11 ms IEC 60068-2-27 5 gn in operation 11 ms IEC 60068-2-27
Relative humidity	95 % 77…131 °F (25…55 °C)
Electromagnetic compatibility	Electrostatic discharge immunity test - test level: 6 kV level 3 (contact discharge) conforming to IEC 61000-4-2 Electrostatic discharge immunity test - test level: 8 kV level 3 (air discharge) conforming to IEC 61000-4-2 Fast transients immunity test - test level: 1 kV level 3 (capacitive connecting clip) conforming to IEC 61000-4-4 Fast transients immunity test - test level: 2 kV level 3 (direct contact) conforming to IEC 61000-4-4 Surge immunity test - test level: 1 kV level 3 (differential mode) conforming to IEC 61000-4-5 Surge immunity test - test level: 2 kV level 3 (common mode) conforming to IEC 61000-4-5 Radiated radio-frequency electromagnetic field immunity test - test level: 10 V level 3 (0.15...80 MHz) conforming to IEC 61000-4-6 Electromagnetic field immunity test - test level: 10 V/m level 3 (80 MHz...1 GHz) conforming to IEC 61000-4-3 Immunity to microbreaks and voltage drops - test level: 30 % (500 ms) conforming to IEC 61000-4-11 Immunity to microbreaks and voltage drops - test level: 100 % (20 ms) conforming to IEC 61000-4-11 Radiated emission class B conforming to EN 55022 Conducted emission class A conforming to EN 55022 Electromagnetic field immunity test - test level: 3 V/m level 2 (1.4 GHz...2 GHz) conforming to IEC 61000-4-3 Electromagnetic field immunity test - test level: 1 V/m level 1 (2...2.7 GHz) conforming to IEC 61000-4-3

Ordering and shipping details

Category	US10CP222376
Discount Schedule	0CP2
GTIN	3606480936203
Returnability	Yes
Country of origin	ID

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	0.9 in (2.4 cm)
Package 1 Width	3.17 in (8.05 cm)
Package 1 Length	3.72 in (9.45 cm)
Package weight(Lbs)	3.656 oz (103.635 g)

Unit Type of Package 2	S02
Number of Units in Package 2	40
Package 2 Height	5.9 in (15.0 cm)
Package 2 Width	11.8 in (30.0 cm)
Package 2 Length	15.7 in (40.0 cm)
Package 2 Weight	10.177 lb(US) (4.616 kg)
Unit Type of Package 3	P06
Number of Units in Package 3	640
Package 3 Height	27.6 in (70.0 cm)
Package 3 Width	23.6 in (60.0 cm)
Package 3 Length	31.5 in (80.0 cm)
Package 3 Weight	185.48 lb(US) (84.13 kg)

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

Environmental Data explained

How we assess product sustainability

Environmental footprint

Carbon footprint (kg CO2 eq, Total Life cycle)	**64**

Use Better

Materials and Substances

Packaging made with recycled cardboard	**Yes**
Packaging without single use plastic	**Yes**
EU RoHS Directive	**Pro-active compliance (Product out of EU RoHS legal scope)**
SCIP Number	**7bdc2711-0ad2-427c-8ece-532c5e9f09d7**
REACh Regulation	**REACh Declaration**
California proposition 65	**WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov**

Use Again

Repack and remanufacture

Take-back	**No**

Dimensions Drawings

Dimensions



Connections and Schema

Internal Wiring Diagram



Wiring Diagram



Technical Description

Function A: Power On-Delay Relay

Description

On energisation of power supply, the timing period T starts. After timing, the output(s) R close(s).The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function At: Power On-Delay Relay with Pause / Summation Control Signal

Description

On energisation of power supply, the timing period T starts.Timing can be interrupted / paused each time Y1 energizes. When the cumulative total of time periods elapsed reaches the pre-set value T, the output(s) R close(s).The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



T = t1 + t2 +…

Function Ac: On-Delay and Off-Delay Relay with Control Signal

Description

After energisation of power supply and energization of Y1 causes the timing period T to start.
At the end of this timing period, the output(s) R close(s).
When deenergization of Y1, the timing T starts.
At the end of this timing period T,the output(s) R revert(s) to its/their initial position.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function Ad : Pulse Delayed Relay with Control Signal

Description

After energisation of power supply, pulsing or maintaining of energization of Y1 starts the timing T.
At the end of this timing period T, the output(s) R close(s).
The output(s) R reverts to its initial position the next time Y1 is energized in pulsation or permanent energized manner.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function Ah : Pulse Delayed Relay (Single Cycle) with Control Signal

Description

After energisation of power supply, pulsing or maintaining of energization of Y1 starts the timing T.
A single flashing cycle then starts with 2 timing periods T of equal duration (start with output(s) R in initial position).
Output(s) R closes at the end of the first timing period T and reverts to its initial position at the end of the second timing period T.
Re-energizing of Y1, either in pulsation or permanent energized manner, will re-start the single flashing cycle again.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function Ak: Asymmetrical On-Delay and Off-Delay Relay With Control Signal

Description

After energisation of power supply and energization of Y1, timing starts for a period Ta.
At the end of this timing period Ta, the output(s) R closes.
Deenergization of Y1 causes a second timing period Tr to start.
At the end of this timing period Tr, the output(s) R reverts to its initial state.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function B: Single Interval Relay with Control Signal

Description

After energisation of power supply, pulsing or maintaining of energization of Y1 starts the timing T.
The output(s) R close(s) for the duration of the timing period T then revert(s) to its/their initial state.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function Bw : Double Interval Relay with Control Signal

Description

After energisation of power supply, transition of Y1 (either from energization to deenergization or vice-versa) will cause the output(s) R close(s) for the duration of the timing period T then revert(s) to its/their initial state.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function C: Off-Delay Relay with Control Signal

Description

After energisation of power supply and energization of Y1 causes output(s) R close(s). When Y1 deenergizes, timing T starts.At the end of this timing period T,the output(s) R revert(s) to its/their initial position.The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function D: Symmetrical Flashing Relay (Starting Pulse-Off)

Description

On energisation of power supply, output(s) R starts at its/their initial state for timing duration T then change(s) to output(s) R close(s) for the same timing duration T.This cycle is repeated indefinitely until power supply removal. The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function Di: Symmetrical Flashing Relay (Starting Pulse-On)

Description

On energisation of power supply, output(s) R starts at output(s) R close(s) for timing duration T then revert(s) to its/their initial state for the same timing duration T.This cycle is repeated indefintely until power supply removal.The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function Dt: Symmetrical Flashing Relay (Starting Pulse-Off) With Pause / Summation Control Signal

Description

On energisation of power supply, output(s) R starts at its/their initial state for timing duration T and the timing can be interrupted / paused each time Y1 energizes.When the cumulative total of time periods elapsed reaches the pre-set value T, then changes to output(s) R close(s).The output(s) R close state will remain for the same timing duration T and the timing can be interrupted / paused each time Y1 energizes.When the cumulative total of time periods elapsed reaches the pre-set value T, the output(s) R revert(s) to its/their initial state.This cycle is repeated indefintely until power supply removal.The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



T = t1 + t2 +…
T = t'1 + t'2 +…

Function Dit: Symmetrical Flashing Relay (Starting Pulse-On) With Pause / Summation Control Signal

Description

On energisation of power supply, output(s) R starts at output(s) R close(s) for timing duration T and the timing can be interrupted / paused each time Y1 energizes.When the cumulative total of time periods elapsed reaches the pre-set value T, then revert(s) to its/their initial state.The output(s) R at initial state will remain for the same timing duration T and the timing can be interrupted / paused each time Y1 energizes.When the cumulative total of time periods elapsed reaches the pre-set value T, the output(s) R change(s) to close state.This cycle is repeated indefinitely until power supply removal.The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



T = t1 + t2 +…
T = t'1 + t'2 +…

Function H: Interval Relay

Description

On energisation of power supply, output(s) R close(s) and timing period T starts.At the end of the timing period T, the output(s) R revert(s) to its/their initial state.The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function Ht: Interval Relay With Pause / Summation Control Signal

Description

On energisation of power supply, output(s) R close(s) and timing period T starts.The timing can be interrupted / paused each time Y1 energizes. When the cumulative total of time periods elapsed reaches the pre-set value T, the output(s) R revert(s) to its/their initial state. The second output (R2) can be either timed (when set to "TIMED" or instantaneous (when set to "INST").

Function: 2 Output



T = t1 + t2 +…

Function L: Asymmetrical Flashing Relay (Starting Pulse-Off)

Description

On energisation of power supply, output(s) R starts at its/their initial state for timing duration Tr then change(s) to output(s) R close(s) for the another timing duration Ta.
This cycle is repeated indefinitely until power supply removal.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function Li: Asymmetrical Flashing Relay (Starting Pulse-On)

Description

On energisation of power supply, output(s) R starts at output(s) R close(s) for timing duration Ta then change(s) to its/ their initial state for timing duration Tr.
This cycle is repeated indefinitely until power supply removal.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function Lt: Asymmetrical Flashing Relay (Starting Pulse-Off) With Pause / Summation Control Signal

Description

On energisation of power supply, output(s) R starts at its/their initial state for timing duration Tr and the timing can be interrupted / paused each time Y1 energizes. When the cumulative total of time periods elapsed reaches the pre-set value Tr, then changes to output(s) R close(s).
The output(s) R close state will remain for the same timing duration Ta and the timing can be interrupted / paused each time Y1 energizes. When the cumulative total of time periods elapsed reaches the pre-set value Ta, the output(s) R revert(s) to its/their initial state.
This cycle is repeated indefinitely until power supply removal.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Tr = t1 + t2 +…
Ta = t'1 + t'2 +…

Function Lit: Asymmetrical Flashing Relay (Starting Pulse-On) With Pause / Summation Control Signal

Description

On energisation of power supply, output(s) R starts at output(s) R close(s) for timing duration Ta and the timing can be interrupted / paused each time Y1 energizes. When the cumulative total of time periods elapsed reaches the pre-set value Ta, the output(s) R revert(s) to its/their initial state.
The output(s) R at initial state will remain for timing duration Tr the timing can be interrupted / paused each time Y1 energizes. When the cumulative total of time periods elapsed reaches the pre-set value Tr, then changes to output(s) R close(s)
This cycle is repeated indefinitely until power supply removal.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Ta = t1 + t2 +…
Tr = t'1 + t'2 +…

Function N : Safe-Guard Relay

Description

After energisation of power supply and on energization of Y1 cause the output(s) R close(s) and starts the timing T.
If the duration interval between 2 consecutive energization of Y1 is greater than the pre-set value T, the output(s) R close(s) at the end of the timing period.
If the duration interval between 2 consecutive energization of Y1 is less than the pre-set value T, the output(s) R remain(s) closed and timing restarted base on the last energization of Y1.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function O : Delayed Safe-Guard Relay

Description

On energisation of power supply, the timing T starts.
At the end of this timing period, the output(s) R close(s).
On energization of Y1, the output(s) R revert(s) to its/their initial state and the timing T restarts.
If the duration interval between 2 consecutive energization of Y1 is greater than the pre-set value T, the output(s) R close(s) at the end of the timing period.
If the duration interval between 2 consecutive energization of Y1 is less than the pre-set value T, the output(s) R remain(s) at its/their initial state and timing restarted base on the last energization of Y1.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function P : Pulse Delayed Relay with Fixed Pulse Length

Description

On energisation of power supply, the timing T starts.
At the end of this period, the output(s) R close(s) for a fixed time P then revert(s) to its/their initial state.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



P = 500ms

Function Pt : Pulse Delayed Relay With Fixed Pulse Length and Pause / Summation Control Signal

Description

On energisation of power supply, the timing T starts.
The timing can be interrupted / paused each time Y1 energizes.
When the cumulative total of time periods elapsed reaches the pre-set value T, the output(s) R close(s) for a fixed time P then revert(s) to its/their initial state.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



T = t1 + t2 + …
P = 500ms

Function Qt: Star-Delta Relay (2 CO Outputs with Split Common)

Description

On energisation of power supply, the output R3 & R4 initializes at its initial state such that energizes STAR CONTACTOR + MAIN CONTACTOR and the timing T starts (STAR connection time duration starts).At the end of the timing period T, the output R3 closes such that deenergizes STAR CONTACTOR and causes t transition time starts.At the end of the transition time, the output R4 closes such that energizes DELTA CONTACTOR. Diagnostic feature not available.

Function: 2 Output



T = 50, 60... ms

Function Qtt: Star-Delta Relay (2 CO Outputs With Split Common) with Pause / Summation Control Signal

Description

On energisation of power supply, the output R3 & R4 initializes at its initial state such that energizes STAR CONTACTOR + MAIN CONTACTOR and the timing T starts (STAR connection time duration starts).During STAR connection time, the timing can be interrupted / paused each time Y1 energizes.When the cumulative total of time periods elapsed reaches the pre-set value T, the output R3 closes such that deenergizes STAR CONTACTOR and causes t transition time starts.At the end of the transition time, the output R4 closes such that energizes DELTA CONTACTOR. Diagnostic feature not available.

Function: 2 Output



T = t1 + t2 +...
t = 50, 60 ... ms

Function TL : Bistable Relay with Control Signal On

Description

After energisation of power supply and on energization of Y1 cause the output(s) R close(s). The subsequent on energization of Y1 cause the output(s) R revert(s) to its/their initial state.
This cycle is repeated indefinitely until power supply removal.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function Tt : Retriggerable Bistable Relay with Control Signal On

Description

After energisation of power supply and on energization of Y1 cause the output(s) R close(s) and starts the timing T.
If the duration interval between 2 consecutive energization of Y1 is greater than the pre-set value T, the output(s) R will toggle from its/their present status the end of the timing period.
If the duration interval between 2 consecutive energization of Y1 is less than the pre-set value T, the output(s) R toggle from its/their present status as soon as Y1 energizes without completing T duration.
The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Function W: Interval Relay with Control Signal Off

Description

After energisation of power supply and on energization of Y1 following by denergization of Y1, the output(s) R close(s) and starts the timing T.At the end of the timing period, the output(s) R revert(s) to its/their initial state.The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 2 Output



Legend

Relay de-energised
Relay energised
Output open
Output closed

U -	Supply
R1/R2 -	2 timed outputs
Ta -	Adjustable On-delay
Tr -	Adjustable Off-delay
Y1 -	Retrigger / Restart control
R2 inst. -	The second output is instantaneous if the right position is selected
T -	Timing period
R4 -	Delta contact output
t -	Delay to switch ON Delta contact output
R3 -	Star-Delta contact output

Technical Illustration

Dimensions



Offer Marketing Illustration

Product benefits / Features

Offer Marketing Illustration

Product benefits / Features

Offer Marketing Illustration

Product benefits / Features

Offer Marketing Illustration

Product benefits / Features

Image of product / Alternate images

Alternative




RENF22R2MMW
T : 0.1s-999h
U : 24-240VAC 50-60Hz 3VA
24-240VDC 1.5W
8A/250V~ IEC 61812-1
AC-15: 1A/250V~ DC-13: 1A/24V= IEC 60947-5-1
A1
Y1
15
25/21
R1
R2
A2
16
18
26/22
28/24
Diagnostic Feature Not Applicable For Q Functions
For more timing options, please refer to product reference datasheet
DNV·GL
Use copper conductors only
Telemecanique

A1
15
25/21
RENF22R2MMW
NFC
R2
R1
Un
Schneider
18
16
A2
28/24
26/22
Y1

18
16
A2
28/24
26/22
Y1

Image of product in real life situation