

LED STRIPS UNDERCABINET SYSTEMS

Hide-A-Lite 4 LED Tape lighting for under cabinets and coves:
Add aesthetic, energy efficient and functional lighting in the most used areas of your home: kitchens, utility rooms, laundry rooms, wet bars, display cases. Mount securely under cabinets with Hide-a-Lite's durable adhesive backing.



FOLLOW FOUR SIMPLE STEPS:

1. Choose a Tape Length

Select LED tape strip length. Hide-a-Lite offers 2"L, 12"L and 60"L size options. Mounting clips are included. (Install in rows of two or more to aid in task lighting or enhance lighting effects.)

3. Use Connectors to Customize Project

Connector cords and L-connectors can increase length and help navigate corners. Choose between a variety of connector cords to allow end-to-end connection.

2. Select Transformer

Progress Lighting's 24V transformer emits no audible noise, is moisture and shock resistant and employs automatically resetting short circuit protection. Also it is dimmable with an electronic low-voltage dimmer.

4. Complete the Look

Select end caps to finish and complete the look.

1. CHOOSE A TAPE LENGTH

P7040-30 White
24V LED 12" 3000K tape light.
3/8" W., 12" L., 1/8" ht.

P7041-30 White
24V LED 5' 3000K tape light.
3/8" W., 60" L., 1/8" ht.

P7042-30 White
24V LED 2" 3000K tape light.
3/8" W., 2" L., 1/8" ht.

- 85CRI, 3000K color temp. 40,000 hr. life
- 120 lumens per foot and consumes 3 watts per foot
- Field cuttable at every 2" to end of run.
- CETL listed damp location



2. SELECT TRANSFORMER

P8683-31 Black
24V 100w LED tape transformer
5" L., 2" W., 1" ht.

- Hard wire 100w 24V zero load transformer
- High power factor >95%
- Maximum operating temperature -20° C to +90° C
- Electronic circuit design with short circuit and overload protection with auto shut down/reset
- Sound rated A, emits no audible noise
- Integrated 5-pin female connector for direct connection to the 1st LED strip in the run



3. ADDITIONAL SYSTEM COMPONENTS

P8705-30 Black
6' Connector cord to connect tape sections (P7040, P7041 and P7042)
96" L., 1/2" W., 3/16" ht.

P8732-30 Black
72" Connector cord to connect tape sections (P7040, P7041 and P7042)
6" L., 1/2" W., 3/16" ht.

P8747-31 Black
2" Connector cord to connect tape sections (P7040, P7041 and P7042)
2" L., 1/2" W., 3/16" ht.

P8749-31 Black
12" Connector cord to connect tape sections (P7040, P7041 and P7042)
12" L., 1/2" W., 3/16" ht.

P8750-31 Black
18" Connector cord to connect tape sections (P7040, P7041 and P7042)
18" L., 1/2" W., 3/16" ht.

P8754-31 Black
36" Connector cord to connect tape sections (P7040, P7041 and P7042)
36" L., 1/2" W., 3/16" ht.



L CONNECTOR
P8711-30 Black
90° connector for connecting sections of tape (P7040, P7041 and P7042) on corners.
1-5/16" L., 1-3/8" W.

Y CONNECTOR
P8744-31 Black
Three-way Y connector for Hide-a-Lite 4 LED tape (P7040, P7041 and P7042) with 1 male and 2 female connection points.
3-5/16" dia., 3/16" ht.

SPLICE BOX
P7024-31 Black
Splice box for Hide-a-Lite 4 LED tape system. Splicer with connection between Romex wire and low voltage cable or between two sections of low voltage cable. Mounting screws included.
2" W., 3/4" ht., 1/2" L.



4. MOUNTING CLIPS/END CLIPS

Additional mounting clips and end caps for Hide-a-Lite 4 LED tape system

P8752-01
Pack of 10 clips/screws for straight runs for added support
(2 clips per foot recommended)
5/8" L., 5/8" W., 1/2" ht.



P8731-30 Black
End caps to terminate run of LED tape. Includes one cut end cap and one male end cap. For use when tape has been cut at end of run.
1/4" L., 1/2" W., 1/8" ht.

