

Harmony[®] K, Ø 16-22 cam switches

Catalog

March 2015



How can you fit a 6000-page catalog in your pocket ?

Schneider Electric provides you with the complete set of industrial automation catalogs all on a handy USB key for PC or in an application for tablets



Digi-Cat, a handy USB key for PC



- > Convenient to carry
- > Always up-to-date
- > Environmentally friendly
- > Easy-to-share format



Contact your local representative to get your own Digi-Cat



e-Library, the app for tablets


If you have an iPad®:

- > Go to the App Store and search for e-Library
- > or scan the QR code



If you have an Android tablet:

- > Go to the Google Play Store™ and search for eLibrary
- > or scan the QR code



General contents

Selection guide, functions panorama	1
Complete switches, 10 A.....	2
Complete switches, 12 and 20 A	3
Adaptable sub-assemblies, 12 and 20 A	4
Complete switches, 12 A with key operated lock	5
Switches, 10 and 16 A, mounted in plastic enclosure	6
Complete switches, 32 to 150 A.....	7
Index.....	8

Selection guide, functions panorama

Selection guide 1/2

■ Functions panorama 1/4

Cam switches
Type K

Applications
Functions
Off-On/On-Off switches
Stepping switches
Changeover switches
Measurement switches
Reversing switches
Reversing star-delta switches
Pole change switches

Used in building control panels and consoles, type K cam switches allow control of processes and utilities in industry and buildings and direct control for simple machines.	
1 to 4-pole	1 to 6-pole
2 to 4-position, 1 and 2-pole	2 to 12-position, 1 to 4-pole
1 to 4-pole	1 to 5-pole
Voltmeter and ammeter	Voltmeter and ammeter
–	2 and 3-pole
–	–
–	2 and 3-speed



Conventional rated thermal current (Ith) Rated insulation voltage (Ui)	10 A 440 V	12 A 690 V
Electrical operating characteristics	AC-15 - A300 240 V - 3 A	AC-3 - 3-phase 230 V - 1.1 kW - 4.6 A AC-15 230 V - 3 A
Front plate degree of protection	IP 65	IP 40 IP 65 (with seal)
Product composition	Complete switches	Complete switches Adaptable sub-assemblies Special products (Consult our Customer Care Centre)
Compatibility	Ø 16 and Ø 22 control and signaling units	Ø 22 control and signaling units
Fixing	Single Ø 16 or Ø 22 hole	Multi-fixing Single Ø 22 hole
Front mounting	–	Screw fixing, 4 holes on 36 mm/1.42 in. centres
Rear mounting	–	Screw fixing, 4 holes on 36 mm/1.42 in. centres
Front plate dimensions (mm)	30 x 30 mm/1.18 x 1.18 in.	45 x 45 mm/1.77 x 1.77 in. 60 x 60 mm/2.36 x 2.36 in. (adaptable sub-assemblies)
Operating heads	Black standard handle Metallic legend, black marking	Black and red standard and long handles Key operator Metallic head Metallic legend with black marking or black legend with white marking
Approvals	cULus EN/IEC 60947-3 EN/IEC 60947-5-1	UL-CSA EN/IEC 60947-3 EN/IEC 60947-5-1
Type	Type K10	Type K1/K2
Cam switch model	K10●	K1●

1 to 6-pole	1 to 6-pole
2 to 12-position, 1 to 4-pole	–
1 to 5-pole	1 to 4-pole
–	–
2 and 3-pole	2 and 3-pole
Star-delta	Star-delta
2 and 3-speed	2-speed



20 A 690 V	32 A 690 V	50 A 690 V	63 A 690 V	115 A 690 V	150 A 690 V
AC-3 - 3-phase 230 V - 2.2 kW - 8.3 A AC-15 230 V - 4 A	AC-3 - 3-phase 230 V - 5.5 kW AC-15 230 V - 14 A	AC-3 - 3-phase 230 V - 7.5 kW AC-15 230 V - 16 A	AC-3 - 3-phase 230 V - 11 kW –	AC-3 - 3-phase 230 V - 15 kW –	AC-3 - 3-phase 230 V - 22 kW –
IP 40 IP 65 (with seal)	IP 40	IP 40	IP 40	IP 40	IP 40
Complete switches Adaptable sub-assemblies Special products (Consult our Customer Care Centre)	Complete switches Adaptable sub-assemblies Special products (Consult our Customer Care Centre)	Complete switches Adaptable sub-assemblies Special products (Consult our Customer Care Centre)	Complete switches Adaptable sub-assemblies Special products (Consult our Customer Care Centre)	Complete switches Adaptable sub-assemblies Special products (Consult our Customer Care Centre)	Complete switches Adaptable sub-assemblies Special products (Consult our Customer Care Centre)
Ø 22 control and signaling units	Ø 22 control and signaling units	Ø 22 control and signaling units	Ø 22 control and signaling units	Ø 22 control and signaling units	Ø 22 control and signaling units
Multi-fixing Single Ø 22 hole	Multi-fixing Single Ø 22 hole	Multi-fixing Single Ø 22 hole	Multi-fixing Single Ø 22 hole	Multi-fixing Single Ø 22 hole	Multi-fixing Single Ø 22 hole
Screw fixing, 4 holes on 36 mm/1.42 in. centres	Screw fixing, 4 holes on 36 mm/1.42 in. centres	Screw fixing, 4 holes on 36 mm/1.42 in. centres	Screw fixing, 4 holes on 36 mm/1.42 in. centres	Screw fixing, 4 holes on 36 mm/1.42 in. centres	Screw fixing, 4 holes on 36 mm/1.42 in. centres
45 x 45 mm/1.77 x 1.77 in. 60 x 60 mm/2.36 x 2.36 in. (adaptable sub-assemblies)	45 x 45 mm/1.77 x 1.77 in. 60 x 60 mm/2.36 x 2.36 in. (adaptable sub-assemblies)	45 x 45 mm/1.77 x 1.77 in. 60 x 60 mm/2.36 x 2.36 in. (adaptable sub-assemblies)	45 x 45 mm/1.77 x 1.77 in. 60 x 60 mm/2.36 x 2.36 in. (adaptable sub-assemblies)	45 x 45 mm/1.77 x 1.77 in. 60 x 60 mm/2.36 x 2.36 in. (adaptable sub-assemblies)	45 x 45 mm/1.77 x 1.77 in. 60 x 60 mm/2.36 x 2.36 in. (adaptable sub-assemblies)
Black and red standard and long handles Key operator Metallic head Metallic legend with black marking or black legend with white marking	Black and red standard and long handles Key operator Metallic head Metallic legend with black marking or black legend with white marking	Black and red standard and long handles Key operator Metallic head Metallic legend with black marking or black legend with white marking	Black and red standard and long handles Key operator Metallic head Metallic legend with black marking or black legend with white marking	Black and red standard and long handles Key operator Metallic head Metallic legend with black marking or black legend with white marking	Black and red standard and long handles Key operator Metallic head Metallic legend with black marking or black legend with white marking
UL-CSA EN/IEC 60947-3 EN/IEC 60947-5-1	UL-CSA EN/IEC 60947-3 EN/IEC 60947-5-1	UL-CSA EN/IEC 60947-3 EN/IEC 60947-5-1	UL-CSA EN/IEC 60947-3 EN/IEC 60947-5-1	UL-CSA EN/IEC 60947-3 EN/IEC 60947-5-1	UL-CSA EN/IEC 60947-3 EN/IEC 60947-5-1
Type K2	Type K30...K150	Type K30...K150	Type K30...K150	Type K30...K150	Type K30...K150
K2●	K30●	K50●	K63●	K115●	K150●

Cam switches
Series K
Functions panorama

Functions		Complete switches 10 A
Switches	with 60° switching angle	See pages 2/3
	with 45° switching angle	-
	with 90° switching angle	-
	ON-OFF with spring return from 30° to "0" position	-
	OFF-ON with spring return from 30° to "0" position	-
	OFF-ON with spring return from 120° to 90°	-
	OFF-ON with spring return from 30° and from 330° to "0" position	-
	OFF-ON with 45° switching angle	-
	OFF-ON with momentary-contact function	-
	paralleling with "0" position	-
	OFF-ON changeover with spring return from 240° to 270° and from 120° to 90°	-
Stepping switches	single-pole with or without "0" position	2/3, 2/4
	2-pole with or without "0" position	2/4, 2/5
	2 to 5 step, single-pole, with or without "0" position	-
	2 to 5 step, 2-pole, with or without "0" position	-
	2 and 3 step, 3-pole, with or without "0" position	-
	2 to 11 step, single-pole, with "0" position	-
	2 to 12 step, single-pole, without "0" position	-
	2 to 6 step, 2-pole, with or without "0" position	-
	2 to 6 step, 3-pole, with or without "0" position	-
	2 to 5 step, 4-pole, with or without "0" position	-
	2 and 3 step, with "0" position + left-hand position	-
	3 step, without "0" position	-
	4 step, 4-pole, without "0" position	-
	2 step, with "0" position	-
	3 step, 2-pole, with "0" position	-
	5 step, 2-pole, with "0" position	-
Changeover switches	spring return to "0" position	2/5
	with or without "0" position	2/6
	1 to 4-pole with "0" position	-
	1 to 4-pole without "0" position	-
	1-pole, 2-pole, 3-pole with "0" position	-
	star-delta and reversing star-delta pole change	-
Voltmeter switches	with "0" position	2/7
	without "0" position	-
Ammeter switches	with "0" position	2/7
	without "0" position	-
Selector switches	BCD encoded output, with "0" position	-
	BCD encoded output, without "0" position	-
	multi-circuit	-
	star-delta and reversing star-delta	-
Reversing switches	with "0" position	-
	with spring return from 330° and from 30° to "0" position	-
	with spring return from 315° and from 45° to "0" position	-
	with spring return from 240° to 270° and from 120° to 90°	-
	with momentary-contact function	-
Pole change switches	for 2-speed motors	-
	for 3-speed motors	-
Start selector switches	3-position with "0" position	-
	4-position with "0" position	-
Starting switches	star-delta and reversing star-delta	-
	pole change	-

Complete switches 12 and 20 A	Complete switches 12 A, with key operated lock	Adaptable sub-assemblies 12 and 20 A	Complete switches 32 to 150 A
See pages	See pages	See pages	See pages
-	-	-	7/3
3/6	-	4/2	-
3/6	-	4/3	7/4
3/7	-	4/4	-
3/7	-	4/4	-
3/8	-	4/4	-
3/8	-	4/5	-
-	-	4/4	-
-	-	4/5	-
-	-	4/12, 4/13	-
-	-	4/5	-
-	-	-	-
-	-	-	-
3/9, 3/10	-	-	-
3/11, 3/12	-	-	-
3/13, 3/14	-	-	-
-	-	4/14, 4/15	-
-	-	4/16, 4/17	-
-	-	4/18, 4/19	-
-	-	4/20, 4/21	-
-	-	4/22, 4/23	-
-	-	4/27	-
-	5/2	-	-
-	5/3	-	-
-	5/4	-	-
-	5/5	-	-
-	5/5	-	-
-	-	-	-
-	-	-	-
-	-	4/6, 4/7	7/5
3/15	-	-	-
3/15	-	-	-
-	5/7	-	-
-	-	4/30, 4/31	-
-	-	4/32	7/6
3/18, 3/19	-	4/25, 4/26	-
3/18, 3/19	-	4/25, 4/26	-
3/16, 3/17	-	4/24	-
3/16, 3/17	-	4/24	-
-	-	4/9, 4/10	-
-	-	4/10, 4/11	-
-	-	4/28	-
-	-	4/30	-
-	-	4/8, 4/29	7/7
-	-	4/29	-
3/15	-	4/8	-
-	-	4/8	-
-	-	4/8	-
-	-	4/31, 4/32	7/7
-	-	4/33	-
-	5/6	-	-
-	5/7	-	-
-	-	-	7/6
-	-	-	7/7

Complete switches, 10 A

- General 2/2
- Front mounting by Ø 16 or 22 mm hole, with 30 x 30 mm front plate 2/3
- Switches and stepping switches 2/3
- Changeover switches 2/5
- Voltmeter and ammeter switches 2/7

Cam switches

Complete switches, 10 A


The range of K10 cam switches (10 A rating) comprises only complete switches. These products are more specifically designed for process control applications:

- compact size,
- easy to integrate with other $\varnothing 16 \text{ mm}/0.63 \text{ in.}$ and $\varnothing 22 \text{ mm}/0.87 \text{ in.}$ units,
- selection functions.

Complete switches

- switches
- stepping switches
- changeover switches
- voltmeter switches
- ammeter switches


Front mounting



By $\varnothing 16.3 \text{ mm}/0.64 \text{ in.}$ or $\varnothing 22.3 \text{ mm}/0.88 \text{ in.}$ hole


Mounting

$\varnothing 16$ or $\varnothing 22$ hole fixing




Locking/unlocking of the body-head assembly by spigot

$\varnothing 16$ hole fixing



$\varnothing 22$ hole fixing



Cam switches

Complete switches, 10 A

Front mounting by Ø 16 or Ø 22 mm hole

With 30 x 30 mm front plate



K10B002ACH

Switches with 60° switching angle

Wiring diagram and switching programme	Marking and switch position	Number of poles	Reference	Weight kg/lb
		1	K10A001ACH	0.030/0.066
		2	K10B002ACH	0.035/0.077
		3	K10C003ACH	0.045/0.099
		4	K10D004ACH	0.045/0.099

Stepping switches, single-pole, with "0" position

Wiring diagram and switching programme	Marking and switch position	Number of steps	Reference	Weight kg/lb
		2 + "0" position	K10B002QCH	0.035/0.077
		3 + "0" position	K10C003QCH	0.045/0.099
		4 + "0" position	K10D004QCH	0.045/0.099



K10D004QCH

Cam switches

Complete switches, 10 A
Front mounting by Ø 16 or Ø 22 mm hole
With 30 x 30 mm front plate

2





Stepping switches, 2-pole, with “0” position				
Wiring diagram and switching programme	Marking and switch position	Number of steps	Reference	Weight kg/lb
		2 + “0” position	K10D012QCH	0.045/0.099
		3 + “0” position	K10F013QCH	0.055/0.121
Stepping switches, single-pole, without “0” position				
		3	K10C003NCH	0.045/0.099
		4	K10D004NCH	0.045/0.099


Cam switches

Complete switches, 10 A
Front mounting by Ø 16 or Ø 22 mm hole
With 30 x 30 mm front plate

Stepping switch, 2-pole, without “0” position

Wiring diagram and switching programme	Marking and switch position	Number of steps	Reference	Weight kg/lb
		3	K10F013NCH	0.055/0.121

Changeover switch with spring return to “0” position

Wiring diagram and switching programme	Marking and switch position	Number of poles	Reference	Weight kg/lb
		1	K10B006TCH	0.035/0.077



Cam switches
Complete switches, 10 A
Front mounting by Ø 16 or Ø 22 mm hole
With 30 x 30 mm front plate

2



K10F003UCH

Changeover switches with "0" position				
Wiring diagram and switching programme	Marking and switch position	Number of poles	Reference	Weight kg/lb
1-pole 2-pole 3-pole 4-pole		1	K10B001UCH	0.035/0.077
		2	K10D002UCH	0.045/0.099
		3	K10F003UCH	0.055/0.121
		4	K10H004UCH	0.065/0.143
Changeover switches without "0" position				
1-pole 2-pole 3-pole 4-pole		1	K10B011UCH	0.035/0.077
		2	K10D012UCH	0.045/0.099
		3	K10F013UCH	0.055/0.121
		4	K10H014UCH	0.065/0.143

Cam switches

Complete switches, 10 A

Front mounting by Ø 16 or Ø 22 mm hole

With 30 x 30 mm front plate

550202



K10F027MCH

Voltmeter switches



For measurements between 3 phases and between 1 phase and neutral

Wiring diagram
and
switching programmeMarking
and switch
position

Reference



Weight
kg/lb

K10F027MCH 0.055/0.121



For measurements between 3 phases, with "0" position

K10D024MCH 0.045/0.099



Ammeter switches



For 3 circuits, with "0" position

K10F003MCH 0.055/0.121

550203



K10F003MCH



Complete switches, 12 and 20 A

- General
 - Complete switches and adaptable sub-assemblies, 12 and 20 A..... 3/2
- Front mounting “multi-fixing” or by Ø 22 mm hole, with 45 x 45 mm front plate
 - Switches 3/6
 - Stepping switches 3/9
 - Reversing and changeover switches 3/15
 - Ammeter switches 3/16
 - Voltmeter switches..... 3/18

Cam switches


Complete switches and adaptable sub-assemblies, 12 and 20 A

The cam switch range comprises the equally dimensioned and similar looking products of the K1 (12 A rating) series and K2 (20 A rating) series. Both series feature complete switches and adaptable sub-assemblies for user assembly.

Complete switches


Front mounting

- switches
- stepping switches (2 to 5 step)
- reversing and 1 to 4-pole changeover switches
- ammeter and voltmeter switches




"Multi-fixing"

K1.....H, K2.....H
See pages 3/6 to 3/13



By Ø 22 mm/0.87 in. hole

K1.....H, K2.....H
See pages 3/6 to 3/13




Front mounting by 6 screws
Ø 5.2 mm/0.20 in. and
55 x 100 mm/2.16 x 3.94 in.
front plate

K1.....Z●
See pages 5/2 to 5/7

Switches for user assembly

Front mounting

Body sub-assembly



"Multi-fixing"

K1.....L, K2.....LL
See pages 4/2 to 4/33

Head sub-assembly

- With 45 x 45 mm/1.77 x 1.77 in. front plate and 35 mm/1.38 in. handle




With blank legend

K●G3H
See page 4/34



With marked legend

KCG3H
See page 4/34




Without legend

KDG3H
See page 4/34


Head sub-assembly

- With 45 x 45 mm/1.77 x 1.77 in. front plate, 35 mm/1.38 in. handle and padlocking device



With marked legend

KCG3Y
See page 4/34



Without legend

KDG3Y
See page 4/34


Cam switches

Complete switches and adaptable sub-assemblies, 12 and 20 A

Switches for user assembly (continued)

Front mounting (continued)

Body sub-assembly




With Ø 22 mm/0.87 in. hole

K1●●●●●●, K2●●●●●●L

See pages 4/2 to 4/33

Head sub-assembly


■ With 45 x 45 mm/ 1.77 x 1.77 in. front plate and 35 mm/1.38 in. handle



With blank legend

K●C1H


See page 4/34



With marked legend (1)

K●C1●●

See page 4/34




Without legend

KDC1●●

See page 4/34

Head sub-assembly


■ With 45 x 45 mm/1.77 x 1.77 in. front plate and key operator



With blank legend

K●C1●

See page 4/34




Without legend

KDC1●●

See page 4/34

Head sub-assembly


■ With 60 x 60 mm/2.36 x 2.36 in. front plate and 42 mm/1.65 in handle



With blank legend

K●D1H


See page 4/34



With marked legend

KCD1MH

See page 4/34




Without legend

KDD1H

See page 4/34

Head sub-assembly


■ With 60 x 60 mm/2.36 x 2.36 in. front plate and key operator



With blank legend

K●D1●

See page 4/35



Without legend

KDD1●●

See page 4/35

Head sub-assembly


■ Circular with plastic bezel



Key operator

K●A1●

See page 4/35



35 mm/1.38 in. handle

K●A1H

See page 4/35

(1) With or without padlocking device.


Cam switches

Complete switches and adaptable sub-assemblies, 12 and 20 A

Switches for user assembly (continued)

Front mounting (continued)

Body sub-assembly



With Ø 22 mm/0.87 in. hole and metal mounting plate

K1●●●●●K, K2●●●●●X

See pages 4/2 to 4/33

Head sub-assembly

■ Circular with metal bezel



Standard handle

KAXZ1M1●


See page 4/35



Long handle

KAXZ1C1●

See page 4/35




Key operator

KAXZ1S1●●

See page 4/35

Rear mounting

Body sub-assembly




With 4 holes

K1●●●●●, K2●●●●●

See pages 4/2 to 4/33

Head sub-assembly


■ With 45 x 45 mm/1.77 x 1.77 in. front plate and 35 mm/1.38 in. handle



With blank legend

K●E1H


See page 4/35



With marked legend (1)

KCE1●

See page 4/35




Without legend

KDE1●

See page 4/35

Head sub-assembly


■ With 60 x 60 mm/2.36 x 2.36 in. front plate and 42 mm/1.65 in handle



With blank legend

K●F1H


See page 4/35



With marked legend

KCF1MH

See page 4/35



Without legend

KDF1H

See page 4/35

(1) With or without padlocking device.

Accessories

Various accessories complement the K1 - K2 cam switch range: legends, legend holders, terminal covers, seals, etc. See pages 4/36 to 4/41.

Switches with specific schemes



If you cannot find a standard switching programme listed in this catalogue to suit your application, please consult our Customer Care Centre.

The cam switches are available to suit various mounting and fixing methods.

Fixing

Front mounting


By means of "multi-fixing" front plate, using 2 or 4 screws




The "multi-fixing" concept enables the switch to be panel mounted using the most commonly used fixing centre dimensions. See drawing to left.

Fixing by 6 screws Ø 5.2 mm and 55 x 100 mm front plate.

By means of single Ø 22 mm/0.87 in. hole




Ø 22.5 mm cut-out.
Head attaches to plate using 1/4 turn bayonet locking and secured on panel by 2 needle screws.



Ø 22.5 mm cut-out with anti-rotation notch.
Head clips into body and secured on panel by fixing nut.

Rear mounting

By means of 4 holes



Switch can be directly mounted on backplate using 4 screws.
For DIN rail mounting, an adaptor is available as an accessory. See page 4/41.





Cam switches

Complete switches, 12 and 20 A




Front mounting, "multi-fixing" or by Ø 22 mm hole

With 45 x 45 mm front plate, 35 mm handle and metallic legend with black marking

Switches with 45° switching angle

Wiring diagram and switching programme	Marking and switch position	Front mounting method	Number of poles	Thermal current (Ith)	Reference	Weight
				A		kg/lb
		"Multi-fixing"	1	12	K1A001ALH	0.103/0.227
				20	K2A001ALH	0.103/0.227
			2	12	K1B002ALH	0.113/0.249
				20	K2B002ALH	0.113/0.249
			3	12	K1C003ALH	0.133/0.293
				20	K2C003ALH	0.133/0.293
			4	12	K1D004ALH	0.138/0.304
				20	K2D004ALH	0.138/0.304
			5	12	K1E005ALH	0.158/0.348
				20	K2E005ALH	0.158/0.348
			6	12	K1F006ALH	0.168/0.370
				20	K2F006ALH	0.168/0.370
		By Ø 22 mm/ 0.87 in. hole	1	12	K1A001ACH	0.123/0.271
				20	K2A001ACH	0.123/0.271
			2	12	K1B002ACH	0.133/0.293
				20	K2B002ACH	0.133/0.293
			3	12	K1C003ACH	0.153/0.337
				20	K2C003ACH	0.153/0.337
			4	12	K1D004ACH	0.158/0.348
				20	K2D004ACH	0.158/0.348
			5	12	K1E005ACH	0.178/0.392
				20	K2E005ACH	0.178/0.392
			6	12	K1F006ACH	0.188/0.414
				20	K2F006ACH	0.188/0.414


Switches with 90° switching angle


 O1 O2 O3 O4 O5 O6 O7 O8	 2-pole 3-pole 4-pole		"Multi-fixing"	2	12	K1B1002HLH	0.130/0.287
					20	K2B1002HLH	0.130/0.287
				3	12	K1C003HLH	0.135/0.298
					20	K2C003HLH	0.135/0.298
				4	12	K1D004HLH	0.140/0.309
					20	K2D004HLH	0.140/0.309
				2	12	K1B1002HCH	0.150/0.331
					20	K2B1002HCH	0.150/0.331
				3	12	K1C003HCH	0.155/0.342
					20	K2C003HCH	0.155/0.342
				4	12	K1D004HCH	0.160/0.353
					20	K2D004HCH	0.160/0.353



Cam switches

Complete switches, 12 and 20 A
Front mounting, “multi-fixing” or by Ø 22 mm hole
With 45 x 45 mm front plate, 35 mm handle and metallic
legend with black marking



ON-OFF switches with spring return from 30° to “0” position						
Wiring diagram and switching programme	Marking and switch position	Front mounting method	Number of poles	Thermal current (Ith)	Reference	Weight
		“Multi-fixing”	1	12	K1A002TLH	0.105/0.231
				20	K2A002TLH	0.105/0.231
			1	12	K1A002TCH	0.125/0.275
				20	K2A002TCH	0.125/0.275
					A	kg/lb



OFF-ON switches with spring return from 30° to “0” position						
Wiring diagram and switching programme	Marking and switch position	Front mounting method	Number of poles	Thermal current (Ith)	Reference	Weight
		“Multi-fixing”	1	12	K1A001TLH	0.105/0.231
				20	K2A001TLH	0.105/0.231
			1	12	K1A001TCH	0.125/0.275
				20	K2A001TCH	0.125/0.275
					A	kg/lb


Cam switches

Complete switches, 12 and 20 A
Front mounting, “multi-fixing” or by Ø 22 mm hole
With 45 x 45 mm front plate, 35 mm handle and metallic
legend with black marking



K.....LH

OFF-ON switches with spring return from 120° to 90°						
Wiring diagram and switching programme	Marking and switch position	Front mounting method	Number of poles	Thermal current (Ith)	Reference	Weight
		“Multi-fixing”	1	12	K1B003TLH	0.115/0.253
				20	K2B003TLH	0.115/0.253
			By Ø 22 mm/ 0.87 in. hole	12	K1B003TCH	0.135/0.298
				20	K2B003TCH	0.135/0.298



K.....CH

OFF-ON switches with spring return from 30° and from 330° to “0” position						
Wiring diagram and switching programme	Marking and switch position	Front mounting method	Number of poles	Thermal current (Ith)	Reference	Weight
		“Multi-fixing”	1	12	K1B004TLH	0.115/0.253
				20	K2B004TLH	0.115/0.253
			By Ø 22 mm/ 0.87 in. hole	12	K1B004TCH	0.135/0.298
				20	K2B004TCH	0.135/0.298






Cam switches

Complete switches, 12 and 20 A

Front mounting, “multi-fixing” or by Ø 22 mm hole

With 45 x 45 mm front plate, 35 mm handle and metallic legend with black marking

Stepping switches (2 to 5 step), single-pole, with “0” position


Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
			A		kg/lb
 K.....LH			2 step + “0”		
			12	K1B002QLH	0.115/0.253
			20	K2B002QLH	0.115/0.253
			12	K1B002QCH	0.135/0.298
			20	K2B002QCH	0.135/0.298
 K.....CH			3 step + “0”		
			12	K1C003QLH	0.135/0.298
			20	K2C003QLH	0.135/0.298
			12	K1C003QCH	0.155/0.342
			20	K2C003QCH	0.155/0.342
			4 step + “0”		
			12	K1D004QLH	0.140/0.309
			20	K2D004QLH	0.140/0.309
			12	K1D004QCH	0.160/0.353
			20	K2D004QCH	0.160/0.353
			5 step + “0”		
			12	K1E005QLH	0.160/0.353
			20	K2E005QLH	0.160/0.353
			12	K1E005QCH	0.180/0.397
			20	K2E005QCH	0.180/0.397

Cam switches

Complete switches, 12 and 20 A
Front mounting, “multi-fixing” or by Ø 22 mm hole
With 45 x 45 mm front plate, 35 mm handle and metallic
legend with black marking

Stepping switches (2 to 5 step), single-pole, without “0” position



Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
			A		kg/lb



“Multi-fixing”

By Ø 22 mm/
0.87 in. hole

2 step		
12	K1B002NLH	0.115/0.253
20	K2B002NLH	0.115/0.253
12	K1B002NCH	0.135/0.298
20	K2B002NCH	0.135/0.298



“Multi-fixing”

By Ø 22 mm/
0.87 in. hole

3 step		
12	K1C003NLH	0.135/0.298
20	K2C003NLH	0.135/0.298
12	K1C003NCH	0.155/0.342
20	K2C003NCH	0.155/0.342



“Multi-fixing”

By Ø 22 mm/
0.87 in. hole

4 step		
12	K1D004NLH	0.140/0.309
20	K2D004NLH	0.140/0.309
12	K1D004NCH	0.160/0.353
20	K2D004NCH	0.160/0.353



“Multi-fixing”

By Ø 22 mm/
0.87 in. hole

5 step		
12	K1E005NLH	0.160/0.353
20	K2E005NLH	0.160/0.353
12	K1E005NCH	0.180/0.397
20	K2E005NCH	0.180/0.397

Cam switches

Complete switches, 12 and 20 A


Front mounting, “multi-fixing” or by Ø 22 mm hole

With 45 x 45 mm front plate, 35 mm handle and metallic legend with black marking

Stepping switches (2 to 5 step), 2-pole, with “0” position



K.....LH



“Multi-fixing”


By Ø 22 mm/
0.87 in. hole

2 step + “0”

Thermal current (Ith)	Reference	Weight
12	K1D012QLH	0.140/0.309
20	K2D012QLH	0.140/0.309
12	K1D012QCH	0.160/0.353
20	K2D012QCH	0.160/0.353



K.....CH



“Multi-fixing”

By Ø 22 mm/
0.87 in. hole

3 step + “0”

Thermal current (Ith)	Reference	Weight
12	K1F013QLH	0.170/0.374
20	K2F013QLH	0.170/0.374
12	K1F013QCH	0.190/0.419
20	K2F013QCH	0.190/0.419



“Multi-fixing”

By Ø 22 mm/
0.87 in. hole

4 step + “0”

Thermal current (Ith)	Reference	Weight
12	K1H014QLH	0.195/0.430
20	K2H014QLH	0.195/0.430
12	K1H014QCH	0.215/0.474
20	K2H014QCH	0.215/0.474



“Multi-fixing”

By Ø 22 mm/
0.87 in. hole

5 step + “0”

Thermal current (Ith)	Reference	Weight
12	K1K015QLH	0.225/0.496
20	K2K015QLH	0.225/0.496
12	K1K015QCH	0.245/0.540
20	K2K015QCH	0.245/0.540

Cam switches


Complete switches, 12 and 20 A
Front mounting, “multi-fixing” or by Ø 22 mm hole
With 45 x 45 mm front plate, 35 mm handle and metallic
legend with black marking

Stepping switches (2 to 5 step), 2-pole, without “0” position

Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
			A		kg/lb



K.....LH




“Multi-fixing”	12	K1D012NLH	0.140/0.309
	20	K2D012NLH	0.140/0.309
By Ø 22 mm/ 0.87 in. hole	12	K1D012NCH	0.160/0.353
	20	K2D012NCH	0.160/0.353

20	K2D012NCH	0.160/0.353
----	-----------	-------------



K.....CH



“Multi-fixing” By Ø 22 mm/ 0.87 in. hole	3 step		
	12	K1F013NLH	0.170/0.374
	20	K2F013NLH	0.170/0.374
	12	K1F013NCH	0.190/0.419
	20	K2F013NCH	0.190/0.419

20	K2F013NCH	0.190/0.419
----	-----------	-------------



“Multi-fixing”	4 step		
	12	K1H014NLH	0.195/0.430
	20	K2H014NLH	0.195/0.430
	12	K1H014NCH	0.215/0.474
By Ø 22 mm/ 0.87 in. hole	20	K2H014NCH	0.215/0.474

20	K2H014NCH	0.215/0.474
----	-----------	-------------







“Multi-fixing”	5 step		
	12	K1K015NLH	0.225/0.496
By Ø 22 mm/ 0.87 in. hole	20	K2K015NLH	0.225/0.496
	12	K1K015NCH	0.245/0.540
	20	K2K015NCH	0.245/0.540

20	K2K015NCH	0.245/0.540
----	-----------	-------------

Cam switches

Complete switches, 12 and 20 A
Front mounting, “multi-fixing” or by Ø 22 mm hole
With 45 x 45 mm front plate, 35 mm handle and metallic
legend with black marking

Stepping switches (2 and 3 step), 3-pole, with “0” position

Wiring diagram and switching programme	Marking and switch position	Front mounting method	Reference		
			Thermal current (Ith) A	Weight kg/lb	
 K.....LH			2 step + “0”		
			12	K1F022QLH	0.170/0.374
			20	K2F022QLH	0.170/0.374
			12	K1F022QCH	0.190/0.419
			20	K2F022QCH	0.190/0.419
 K.....CH			3 step + “0”		
			12	K1I023QLH	0.215/0.474
			20	K2I023QLH	0.215/0.474
			12	K1I023QCH	0.235/0.518
			20	K2I023QCH	0.235/0.518

Cam switches



Complete switches, 12 and 20 A
Front mounting, “multi-fixing” or by Ø 22 mm hole
With 45 x 45 mm front plate, 35 mm handle and metallic
legend with black marking

Stepping switches (2 and 3 step), 3-pole, without “0” position

Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
			A		kg/lb




K.....LH




“Multi-fixing”

By Ø 22 mm/
0.87 in. hole

2 step		
12	K1F022NLH	0.170/0.374
20	K2F022NLH	0.170/0.374
12	K1F022NCH	0.190/0.419
20	K2F022NCH	0.190/0.419



K.....CH



“Multi-fixing”

By Ø 22 mm/
0.87 in. hole


3 step		
12	K1I023NLH	0.215/0.474
20	K2I023NLH	0.215/0.474
12	K1I023NCH	0.235/0.518
20	K2I023NCH	0.235/0.518

Cam switches


Complete switches, 12 and 20 A

Front mounting, “multi-fixing” or by Ø 22 mm hole

With 45 x 45 mm front plate, 35 mm handle and metallic legend with black marking







Reversing switches with spring return from 315° and from 45° to “0” position						
Wiring diagram and switching programme	Marking and switch position	Front mounting method	Number of poles	Thermal current (Ith)	Reference	Weight
				A		kg/lb
		“Multi-fixing”	1	12	K1B006TLH	0.115/0.253
				20	K2B006TLH	0.115/0.253
		By Ø 22 mm/ 0.87 in. hole	1	12	K1B006TCH	0.135/0.298
				20	K2B006TCH	0.135/0.298



Changeover switches, 1 to 4-pole						
Wiring diagram and switching programme	Marking and switch position	Front mounting method	Number of poles	Thermal current (Ith)	Reference	Weight
				A		kg/lb
		“Multi-fixing”	1	With “0” position		
				12	K1B001ULH	0.115/0.253
				20	K2B001ULH	0.115/0.253
				12	K1D002ULH	0.140/0.309
				20	K2D002ULH	0.140/0.309
				12	K1F003ULH	0.170/0.374
				20	K2F003ULH	0.170/0.374
				12	K1H004ULH	0.195/0.430
				20	K2H004ULH	0.195/0.430
		By Ø 22 mm/ 0.87 in. hole	1	12	K1B001UCH	0.135/0.298
				20	K2B001UCH	0.135/0.298
			2	12	K1D002UCH	0.160/0.353
				20	K2D002UCH	0.160/0.353
			3	12	K1F003UCH	0.190/0.419
				20	K2F003UCH	0.190/0.419
			4	12	K1H004UCH	0.215/0.474
				20	K2H004UCH	0.215/0.474
		“Multi-fixing”	1	Without “0” position		
				12	K1B011ULH	0.115/0.253
				20	K2B011ULH	0.115/0.253
				12	K1D012ULH	0.140/0.309
				20	K2D012ULH	0.140/0.309
				12	K1F013ULH	0.170/0.374
				20	K2F013ULH	0.170/0.374
				12	K1H014ULH	0.195/0.430
				20	K2H014ULH	0.195/0.430
		By Ø 22 mm/ 0.87 in. hole	1	12	K1B011UCH	0.135/0.298
				20	K2B011UCH	0.135/0.298
			2	12	K1D012UCH	0.160/0.353
				20	K2D012UCH	0.160/0.353
			3	12	K1F013UCH	0.190/0.419
				20	K2F013UCH	0.190/0.419
			4	12	K1H014UCH	0.215/0.474
				20	K2H014UCH	0.215/0.474

Cam switches

Complete switches, 12 A
Front mounting, “multi-fixing” or by Ø 22 mm hole
With 45 x 45 mm front plate, 35 mm handle and metallic
legend with black marking

Ammeter switches					
Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
			A		kg/lb
For 3 circuits					
 K.....LH	 		With “0” position		
			“Multi-fixing”	12	K1F003MLH 0.170/0.374
			By Ø 22 mm/ 0.87 in. hole	12	K1F003MCH 0.190/0.419
 K.....CH	 		Without “0” position		
			“Multi-fixing”	12	K1F013MLH 0.170/0.374
			By Ø 22 mm/ 0.87 in. hole	12	K1F013MCH 0.190/0.419

Cam switches

Complete switches, 12 A

Front mounting, "multi-fixing" or by Ø 22 mm hole

With 45 x 45 mm front plate, 35 mm handle and metallic legend with black marking


Ammeter switches (continued)

Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
			A		kg/lb

For 4 circuits



K.....LH




"Multi-fixing"

With "0" position



12 K1H004MLH 0.195/0.430

By Ø 22 mm/
0.87 in. hole

12 K1H004MCH 0.215/0.474



K.....CH





"Multi-fixing"

Without "0" position

12 K1H014MLH 0.195/0.430

By Ø 22 mm/
0.87 in. hole

12 K1H014MCH 0.215/0.474



















Cam switches

Complete switches, 12 A

Front mounting, “multi-fixing” or by Ø 22 mm hole

With 45 x 45 mm front plate, 35 mm handle and metallic legend with black marking

Voltmeter switches						
Wiring diagram	Switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
				A		kg/lb
For measurements between 3 phases and neutral						
			With "0" position			
			"Multi-fixing"	12	K1D023MLH	0.140/0.309
			By Ø 22 mm/ 0.87 in. hole			
			12	K1D023MCH	0.160/0.353	
For measurements between 3 phases of 2 supplies						
			With "0" position			
			"Multi-fixing"	12	K1H026MLH	0.205/0.452
			By Ø 22 mm/ 0.87 in. hole			
			12	K1H026MCH	0.215/0.474	
			Without "0" position			
			"Multi-fixing"	12	K1H036MLH	0.205/0.452
			By Ø 22 mm/ 0.87 in. hole			
			12	K1H036MCH	0.215/0.474	

Cam switches

Complete switches, 12 A



Front mounting, “multi-fixing” or by Ø 22 mm hole

With 45 x 45 mm front plate, 35 mm handle and metallic legend with black marking

Voltmeter switches (continued)



Wiring diagram	Switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
				A		kg/lb

For measurements between 3 phases and between each of the 3 phases and neutral



	With “0” position			
“Multi-fixing”	12	K1F027MLH	0.170/0.374	



By Ø 22 mm/ 0.87 in. hole	12	K1F027MCH	0.190/0.419	
------------------------------	----	-----------	-------------	--



	Without “0” position			
“Multi-fixing”	12	K1F037MLH	0.170/0.374	


By Ø 22 mm/ 0.87 in. hole	12	K1F037MCH	0.190/0.419	
------------------------------	----	-----------	-------------	--

For measurements between 3 phases



	With “0” position			
“Multi-fixing”	12	K1D024MLH	0.140/0.309	



By Ø 22 mm/ 0.87 in. hole	12	K1D024MCH	0.160/0.353	
------------------------------	----	-----------	-------------	--



	Without “0” position			
“Multi-fixing”	12	K1D034MLH	0.140/0.309	


By Ø 22 mm/ 0.87 in. hole	12	K1D034MCH	0.160/0.353	
------------------------------	----	-----------	-------------	--

For measurements between 3 phases and between 1 phase and neutral



	With “0” position			
“Multi-fixing”	12	K1E025MLH	0.160/0.353	

By Ø 22 mm/ 0.87 in. hole	12	K1E025MCH	0.180/0.397	
------------------------------	----	-----------	-------------	--



	Without “0” position			
“Multi-fixing”	12	K1E035MLH	0.160/0.353	

By Ø 22 mm/ 0.87 in. hole	12	K1E035MCH	0.180/0.397	
------------------------------	----	-----------	-------------	--

Adaptable sub-assemblies, 12 and 20 A
■ Bodies (contact blocks + fixing plate)

□ Switches	4/2
□ Changeover switches	4/6
□ Reversing switches.....	4/8
□ Encoded output switches	4/9
□ Paralleling switches	4/12
□ Stepping switches.....	4/14
□ Ammeter switches	4/24
□ Voltmeter switches.....	4/25
□ Multi-circuit switches.....	4/28
□ Reversing switches.....	4/29
□ Star-delta switches and reversing star-delta switches	4/30
□ Pole change switches and reversing pole change switches.....	4/31

■ Operating heads

□ For “multi-fixing” or Ø 22 mm hole, front mounting bodies	4/34
□ For 4 hole, rear mounting bodies	4/35

■ Legends

□ For “multi-fixing” heads.....	4/36
□ For Ø 22 mm hole mounting heads with plastic bezel	4/37
□ For Ø 22 mm hole mounting heads with chromium plated metal bezel.....	4/38
□ Legend holders for heads	4/39
□ Separate components and accessories.....	4/40

Cam switches
Adaptable sub-assemblies, 12 and 20 A
Bodies (contact blocks + fixing plate)

To combine with operating heads:
see page 4/34

Switches with 45° switching angle										
Wiring diagram and switching programme		Switch position	Mounting method		Reference to be completed (1)	Weight kg/lb				
 Input 1 Input 2 O 1 O 2 O 3 O 4 O 5 O 6 O 7 O 8 O 9 O 10 O 11 O 12 O 13 O 14 O 15 O 16 Output 1 Output 2 U V W N U V W N 1-pole 2-pole 3-pole 4-pole 5-pole 6-pole 7-pole 8-pole		1-pole								
			Front	Multi-fixing	K●A001AL	0.091/0.201				
				By Ø 22 mm/0.87 in. hole	K●A001A	0.075/0.165				
			Rear		K●A001AX (2)	0.153/0.337				
					K●A501A	0.115/0.253				
		 Input 1 Input 2 O 1 O 2 O 3 O 4 O 5 O 6 O 7 O 8 O 9 O 10 O 11 O 12 O 13 O 14 O 15 O 16 Output 1 Output 2 U V W N U V W N 1-pole 2-pole 3-pole 4-pole 5-pole 6-pole 7-pole 8-pole		2-pole						
					Front	Multi-fixing	K●B002AL	0.101/0.223		
						By Ø 22 mm/0.87 in. hole	K●B002A	0.085/0.187		
					Rear		K●B002AX (2)	0.163/0.359		
							K●B502A	0.125/0.275		
				 Input 1 Input 2 O 1 O 2 O 3 O 4 O 5 O 6 O 7 O 8 O 9 O 10 O 11 O 12 O 13 O 14 O 15 O 16 Output 1 Output 2 U V W N U V W N 1-pole 2-pole 3-pole 4-pole 5-pole 6-pole 7-pole 8-pole		3-pole				
							Front	Multi-fixing	K●C003AL	0.121/0.267
	By Ø 22 mm/0.87 in. hole						K●C003A	0.105/0.231		
	Rear						K●C003AX (2)	0.183/0.403		
							K●C503A	0.140/0.309		
 Input 1 Input 2 O 1 O 2 O 3 O 4 O 5 O 6 O 7 O 8 O 9 O 10 O 11 O 12 O 13 O 14 O 15 O 16 Output 1 Output 2 U V W N U V W N 1-pole 2-pole 3-pole 4-pole 5-pole 6-pole 7-pole 8-pole						4-pole				
							Front	Multi-fixing	K●D004AL	0.126/0.278
			By Ø 22 mm/0.87 in. hole				K●D004A	0.110/0.242		
			Rear				K●D004AX (2)	0.188/0.414		
							K●D504A	0.150/0.331		
		 Input 1 Input 2 O 1 O 2 O 3 O 4 O 5 O 6 O 7 O 8 O 9 O 10 O 11 O 12 O 13 O 14 O 15 O 16 Output 1 Output 2 U V W N U V W N 1-pole 2-pole 3-pole 4-pole 5-pole 6-pole 7-pole 8-pole				5-pole				
							Front	Multi-fixing	K●E005AL	0.146/0.322
					By Ø 22 mm/0.87 in. hole		K●E005A	0.130/0.287		
					Rear		K●E005AX (2)	0.208/0.458		
							K●E505A	0.165/0.364		
				 Input 1 Input 2 O 1 O 2 O 3 O 4 O 5 O 6 O 7 O 8 O 9 O 10 O 11 O 12 O 13 O 14 O 15 O 16 Output 1 Output 2 U V W N U V W N 1-pole 2-pole 3-pole 4-pole 5-pole 6-pole 7-pole 8-pole		6-pole				
							Front	Multi-fixing	K●F006AL	0.156/0.344
	By Ø 22 mm/0.87 in. hole						K●F006A	0.140/0.309		
	Rear						K●F006AX (2)	0.218/0.481		
							K●F506A	0.175/0.386		
 Input 1 Input 2 O 1 O 2 O 3 O 4 O 5 O 6 O 7 O 8 O 9 O 10 O 11 O 12 O 13 O 14 O 15 O 16 Output 1 Output 2 U V W N U V W N 1-pole 2-pole 3-pole 4-pole 5-pole 6-pole 7-pole 8-pole						7-pole				
							Front	Multi-fixing	K●G007AL	0.176/0.388
			By Ø 22 mm/0.87 in. hole				K●G007A	0.160/0.353		
			Rear				K●G507A	0.190/0.419		
		 Input 1 Input 2 O 1 O 2 O 3 O 4 O 5 O 6 O 7 O 8 O 9 O 10 O 11 O 12 O 13 O 14 O 15 O 16 Output 1 Output 2 U V W N U V W N 1-pole 2-pole 3-pole 4-pole 5-pole 6-pole 7-pole 8-pole				8-pole				
							Front	Multi-fixing	K●H008AL	0.181/0.399
					By Ø 22 mm/0.87 in. hole		K●H008A	0.165/0.364		
					Rear		K●H508A	0.195/0.430		

(1) To order a cam switch with thermal current I_{th} = 12 A, replace the ● in the reference by 1.
Example K1A001A.
To order a cam switch with thermal current I_{th} = 20 A, replace the ● in the reference by 2.
Example K2A001A.
(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1●●●.

Cam switches

Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)

To combine with operating heads:
see page 4/34

Switches with 90° switching angle

Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
2-pole					
			Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●B1002HL K●B1002H K●B1002HX (2)	0.121/0.267 0.105/0.231 0.183/0.403
3-pole					
			Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●C003HL K●C003H K●C003HX (2)	0.121/0.267 0.105/0.231 0.183/0.403
		Rear		K●C503H	0.140/0.309
3-pole with neutral wire terminal and Earth terminal					
			Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●C023HL K●C023H K●C023HX (2)	0.121/0.267 0.105/0.231 0.183/0.403
		Rear		K●C523H	0.140/0.309
4-pole					
			Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●D004HL K●D004H K●D004HX (2)	0.126/0.278 0.110/0.242 0.188/0.414
		Rear		K●D504H	0.150/0.331
4-pole with neutral wire terminal and Earth terminal					
			Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●D024HL K●D024H K●D024HX (2)	0.126/0.278 0.110/0.242 0.188/0.414
		Rear		K●D524H	0.150/0.331
5-pole					
			Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●E005HL K●E005H K●E005HX (2)	0.146/0.322 0.130/0.287 0.208/0.458
		Rear		K●E505H	0.165/0.364
5-pole with neutral wire terminal and Earth terminal					
			Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●E025HL K●E025H	0.146/0.322 0.130/0.287
		Rear		K●E525H	0.165/0.364
6-pole					
			Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●F006HL K●F006H K●F006HX (2)	0.156/0.344 0.140/0.309 0.218/0.481
		Rear		K●F506H	0.175/0.386
6-pole with neutral wire terminal and Earth terminal					
			Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●F026HL K●F026H	0.156/0.344 0.140/0.309
		Rear		K●F526H	0.175/0.386

(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.

Example **K1C003H**.

To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.


Example **K2C003H**.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.

Cam switches

Adaptable sub-assemblies, 12 and 20 A
Bodies (contact blocks + fixing plate)


To combine with operating heads:
see page 4/34



OFF-ON switches with 45° switching angle					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
			Front	Multi-fixing	K●A001AL 0.091/0.201
				By Ø 22 mm/0.87 in. hole	K●A001A 0.075/0.165
					K●A001AX (2) 0.153/0.337
			Rear		K●A501A 0.115/0.253



OFF-ON switches with spring return from 30° to “0” position					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
			Front	Multi-fixing	K●A001TL 0.091/0.201
				By Ø 22 mm/0.87 in. hole	K●A001T 0.075/0.165
					K●A001TX (2) 0.153/0.337
			Rear		K●A501T 0.115/0.253



ON-OFF switches with spring return from 30° to “0” position					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
			Front	Multi-fixing	K●A002TL 0.091/0.201
				By Ø 22 mm/0.87 in. hole	K●A002T 0.075/0.165
					K●A002TX (2) 0.153/0.337
			Rear		K●A502T 0.115/0.253




OFF-ON switches with spring return from 120° to 90°					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
			Front	Multi-fixing	K●B003TL 0.101/0.223
				By Ø 22 mm/0.87 in. hole	K●B003T 0.085/0.187
			Rear		K●B503T 0.125/0.275

(1) To order a cam switch with thermal current I_{th} = 12 A, replace the ● in the reference by 1.
Example **K1A001A**.
To order a cam switch with thermal current I_{th} = 20 A, replace the ● in the reference by 2.
Example **K2A001A**.
(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.

To combine with operating heads:
see page 4/34




K●●0●●●L

OFF-ON switches with spring return from 30° and from 330° to “0” position						
Wiring diagram and switching programme		Switch position	Mounting method		Reference to be completed (1)	Weight kg/lb
			Front	Multi-fixing	K●B004TL	0.101/0.223
				By Ø 22 mm/0.87 in. hole	K●B004T	0.085/0.187
			Rear		K●B504T	0.115/0.253
						



K●●0●●●


OFF-ON switches with momentary-contact function							
Wiring diagram and switching programme		Switch position		Mounting method		Reference to be completed (1)	Weight kg/lb
				Front	Multi-fixing	K●B001DL	0.101/0.223
				By Ø 22 mm/0.87 in. hole		K●B001D	0.085/0.187
						K●B001DX (2)	0.163/0.359
				Rear		K●B501D	0.125/0.275




K●●5●●●



K●●0●●●X

OFF-ON changeover switches with spring return from 240° to 270° and from 120° to 90°						
Wiring diagram and switching programme		Switch position	Mounting method		Reference to be completed (1)	Weight kg/lb
			Front	Multi-fixing	K●D005TL	0.126/0.278
				By Ø 22 mm/0.87 in. hole	K●D005T	0.110/0.242
			Rear		K●D505T	0.150/0.331

					
---	--	--	--	--	--

(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.

Example K1B004T.



To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.

Example K2B004T.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1●●●.

Cam switches
Adaptable sub-assemblies, 12 and 20 A
Bodies (contact blocks + fixing plate)

To combine with operating heads:
see page 4/34



Changeover switches with “0” position						
Wiring diagram and switching programme		Switch position	Mounting method		Reference to be completed (1)	Weight kg/lb
		1-pole	Front	Multi-fixing	K●B001UL	0.101/0.223
				By Ø 22 mm/0.87 in. hole	K●B001U	0.085/0.187
			Rear		K●B001UX (2)	0.163/0.359
					K●B501U	0.125/0.275
		2-pole	Front	Multi-fixing	K●D002UL	0.126/0.278
				By Ø 22 mm/0.87 in. hole	K●D002U	0.110/0.242
			Rear		K●D002UX (2)	0.188/0.414
					K●D502U	0.150/0.331
		3-pole	Front	Multi-fixing	K●F003UL	0.156/0.344
				By Ø 22 mm/0.87 in. hole	K●F003U	0.140/0.309
			Rear		K●F003UX (2)	0.218/0.481
					K●F503U	0.175/0.386
4-pole	Front	Multi-fixing	K●H004UL	0.181/0.399		
		By Ø 22 mm/0.87 in. hole	K●H004U	0.165/0.364		
	Rear		K●H004UX (2)	0.243/0.536		
			K●H504U	0.195/0.430		
5-pole	Front	Multi-fixing	K●K005UL	0.211/0.465		
		By Ø 22 mm/0.87 in. hole	K●K005U	0.195/0.430		
	Rear		K●K005UX (2)	0.273/0.602		
			K●K505U	0.210/0.463		

(1) To order a cam switch with thermal current I_{th} = 12 A, replace the ● in the reference by 1.
Example K1B001U.
To order a cam switch with thermal current I_{th} = 20 A, replace the ● in the reference by 2.
Example K2B001U.
(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1●●●.

To combine with operating heads:
see page 4/34

Changeover switches without "0" position

Wiring diagram and switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
	1-pole	Front	Multi-fixing	K●B011UL 0.101/0.223
			By Ø 22 mm/0.87 in. hole	K●B011U 0.085/0.187
		Rear		K●B011UX (2) 0.163/0.359
				K●B511U 0.125/0.275
	2-pole	Front	Multi-fixing	K●D012UL 0.126/0.278
			By Ø 22 mm/0.87 in. hole	K●D012U 0.110/0.242
		Rear		K●D012UX (2) 0.188/0.414
				K●D512U 0.150/0.331
	3-pole	Front	Multi-fixing	K●F013UL 0.156/0.344
			By Ø 22 mm/0.87 in. hole	K●F013U 0.140/0.309
		Rear		K●F013UX (2) 0.218/0.481
				K●F513U 0.175/0.386
	4-pole	Front	Multi-fixing	K●H014UL 0.181/0.399
			By Ø 22 mm/0.87 in. hole	K●H014U 0.165/0.364
		Rear		K●H014UX (2) 0.243/0.536
				K●H514U 0.195/0.430
	5-pole	Front	Multi-fixing	K●K015UL 0.211/0.465
			By Ø 22 mm/0.87 in. hole	K●K015U 0.195/0.430
		Rear		K●K015UX (2) 0.273/0.602
				K●K515U 0.220/0.485


(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.

Example **K1B011U**.


To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.

Example **K2B011U**.


(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.



K●●0●●●L



K●●0●●●



K●●5●●●



K●●0●●●X

Cam switches


Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)

To combine with operating heads:
see page 4/34




K●●0●●●L

Reversing switches with "0" position							
Wiring diagram		Switching programme	Switch position	Mounting method		Reference to be completed (1)	Weight kg/lb
				Front	Multi-fixing	K●B001UL	0.101/0.223
					By Ø 22 mm/ 0.87 in. hole	K●B001U	0.085/0.187
						K●B001UX (2)	0.163/0.359
				Rear		K●B501U	0.125/0.275





K●●0●●●

Reversing switches with spring return from 315° and from 45° to “0” position						
Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb	
			Front	Multi-fixing	K●B006TL	0.101/0.223
				By Ø 22 mm/ 0.87 in. hole	K●B006T	0.085/0.187
					K●B006TX (2)	0.163/0.359
			Rear		K●B506T	0.125/0.275





K●●5●●●

Reversing switches with momentary-contact function							
Wiring diagram		Switching programme	Switch position	Mounting method		Reference to be completed (1)	Weight kg/lb
				Front	Multi-fixing	K●C002DL	0.121/0.267
					By Ø 22 mm/ 0.87 in. hole	K●C002D	0.105/0.231
						K●C002DX (2)	0.183/0.403
				Rear		K●C502D	0.140/0.309



K●●0●●●X

Reversing switches with spring return from 240° to 270° and from 120° to 90° position							
Wiring diagram		Switching programme	Switch position	Mounting method		Reference to be completed (1)	Weight kg/lb
				Front	Multi-fixing	K●C007TL	0.121/0.267
					By Ø 22 mm/ 0.87 in. hole	K●C007T	0.105/0.231
				Rear		K●C507T	0.140/0.309

(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.
Example **K1B001U**.

To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.


Example **K2B001U**.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.


To combine with operating heads:
see page 4/34




K...0...L




K...0...



K...5...



K...0...X



BCD encoded output switches with “0” position						
Wiring diagram	Switching programme	Switch position	Mounting method	Reference (1)	Weight kg/lb	
		1 decimal				
			Front	Multi-fixing By Ø 22 mm/ 0.87 in. hole	K1A001BL K1A001B K1A001BX (2)	0.101/0.223 0.085/0.187 0.163/0.359
			Rear		K1A501B	0.125/0.275
			Front	Multi-fixing By Ø 22 mm/ 0.87 in. hole	K1B002BL K1B002B K1B002BX (2)	0.101/0.223 0.085/0.187 0.163/0.359
			Rear		K1B502B	0.125/0.275
			Front	Multi-fixing By Ø 22 mm/ 0.87 in. hole	K1B003BL K1B003B K1B003BX (2)	0.101/0.223 0.085/0.187 0.163/0.359
			Rear		K1B503B	0.125/0.275
			Front	Multi-fixing By Ø 22 mm/ 0.87 in. hole	K1C004BL K1C004B K1C004BX (2)	0.121/0.267 0.105/0.231 0.183/0.403
			Rear		K1C504B	0.140/0.309
			Front	Multi-fixing By Ø 22 mm/ 0.87 in. hole	K1C005BL K1C005B K1C005BX (2)	0.121/0.267 0.105/0.231 0.183/0.403
Rear			K1C505B	0.140/0.309		
	Front	Multi-fixing By Ø 22 mm/ mm/0.87 in. hole	K1C006BL K1C006B K1C006BX (2)	0.121/0.267 0.105/0.231 0.183/0.403		
	Rear		K1C506B	0.140/0.309		
	Front	Multi-fixing By Ø 22 mm/ 0.87 in. hole	K1C007BL K1C007B K1C007BX (2)	0.121/0.267 0.105/0.231 0.183/0.403		
	Rear		K1C507B	0.140/0.309		
		8 decimal				
			Front	Multi-fixing By Ø 22 mm/ 0.87 in. hole	K1D008BL K1D008B K1D008BX (2)	0.126/0.278 0.110/0.242 0.188/0.414
Rear			K1D508B	0.150/0.331		


(1) Ith = 12 A.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1...


To combine with operating heads:
see page 4/34

BCD encoded output switches with "0" position (continued)

Wiring diagram and switching programme	Switch position	Mounting method	Reference (1)	Weight kg/lb
--	-----------------	-----------------	---------------	--------------




K...0...L




87	65	43	21	1	0
8	4	2	1	0	0
1					30
2					60
3					90
4					120
5					150
6					180
7					210
8					240
9					270
10					300
11					330

9 decimal




Front	Multi-fixing	K1D009BL	0.126/0.278
	By Ø 22 mm/0.87 in. hole	K1D009B	0.110/0.242
		K1D009BX (2)	0.188/0.414
Rear		K1D509B	0.150/0.331

10 decimal



Front	Multi-fixing	K1D010BL	0.126/0.278
	By Ø 22 mm/0.87 in. hole	K1D010B	0.110/0.242
		K1D510B	0.150/0.331


11 decimal




Front	Multi-fixing	K1D011BL	0.126/0.278
	By Ø 22 mm/0.87 in. hole	K1D011B	0.110/0.242
		K1D511B	0.150/0.331

BCD encoded output switches without "0" position

Wiring diagram and switching programme	Switch position	Mounting method	Reference (1)	Weight kg/lb
--	-----------------	-----------------	---------------	--------------




K...5...




87	65	43	21	1	0
8	4	2	1	0	0
1					45
2					90
3					135
4					180
5					225

1 and 2 decimal




Front	Multi-fixing	K1B022BL	0.101/0.223
	By Ø 22 mm/0.87 in. hole	K1B022B	0.085/0.187
		K1B022BX (2)	0.163/0.359
Rear		K1B522B	0.125/0.275

3 decimal




Front	Multi-fixing	K1B023BL	0.101/0.223
	By Ø 22 mm/0.87 in. hole	K1B023B	0.085/0.187
		K1B023BX (2)	0.163/0.359
Rear		K1B523B	0.125/0.275

4 decimal




Front	Multi-fixing	K1C024BL	0.121/0.267
	By Ø 22 mm/0.87 in. hole	K1C024B	0.105/0.231
		K1C024BX (2)	0.183/0.403
Rear		K1C524B	0.140/0.309

5 decimal



Front	Multi-fixing	K1C025BL	0.121/0.267
	By Ø 22 mm/0.87 in. hole	K1C025B	0.105/0.231
		K1C025BX (2)	0.183/0.403
Rear		K1C525B	0.140/0.309

6 decimal










Front	Multi-fixing	K1C026BL	0.121/0.267
	By Ø 22 mm/0.87 in. hole	K1C026B	0.105/0.231
		K1C026BX (2)	0.183/0.403
Rear		K1C526B	0.140/0.309

(1) Ith = 12 A.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1....

To combine with operating heads:
see page 4/34

BCD encoded output switches without "0" position (continued)

Wiring diagram and switching programme	Switch position	Mounting method	Reference (1)	Weight kg/lb																																																																																																																					
 <table><tr><td></td><td>87</td><td>65</td><td>43</td><td>21</td></tr><tr><td>1</td><td></td><td></td><td></td><td></td></tr><tr><td>2</td><td></td><td></td><td></td><td></td></tr><tr><td>3</td><td></td><td></td><td></td><td></td></tr><tr><td>4</td><td></td><td></td><td></td><td></td></tr><tr><td>5</td><td></td><td></td><td></td><td></td></tr><tr><td>6</td><td></td><td></td><td></td><td></td></tr><tr><td>7</td><td></td><td></td><td></td><td></td></tr><tr><td>8</td><td></td><td></td><td></td><td></td></tr></table> Contact marking Value <table><tr><td>1</td><td></td><td></td><td></td><td></td><td>0</td></tr><tr><td>2</td><td></td><td></td><td></td><td></td><td>30</td></tr><tr><td>3</td><td></td><td></td><td></td><td></td><td>60</td></tr><tr><td>4</td><td></td><td></td><td></td><td></td><td>90</td></tr><tr><td>5</td><td></td><td></td><td></td><td></td><td>120</td></tr><tr><td>6</td><td></td><td></td><td></td><td></td><td>150</td></tr><tr><td>7</td><td></td><td></td><td></td><td></td><td>180</td></tr><tr><td>8</td><td></td><td></td><td></td><td></td><td>210</td></tr><tr><td>9</td><td></td><td></td><td></td><td></td><td>240</td></tr><tr><td>10</td><td></td><td></td><td></td><td></td><td>270</td></tr><tr><td>11</td><td></td><td></td><td></td><td></td><td>300</td></tr><tr><td>12</td><td></td><td></td><td></td><td></td><td>330</td></tr></table>		87	65	43	21	1					2					3					4					5					6					7					8					1					0	2					30	3					60	4					90	5					120	6					150	7					180	8					210	9					240	10					270	11					300	12					330	7 decimal			
		87	65	43	21																																																																																																																				
	1																																																																																																																								
	2																																																																																																																								
	3																																																																																																																								
	4																																																																																																																								
	5																																																																																																																								
	6																																																																																																																								
	7																																																																																																																								
	8																																																																																																																								
	1					0																																																																																																																			
	2					30																																																																																																																			
3					60																																																																																																																				
4					90																																																																																																																				
5					120																																																																																																																				
6					150																																																																																																																				
7					180																																																																																																																				
8					210																																																																																																																				
9					240																																																																																																																				
10					270																																																																																																																				
11					300																																																																																																																				
12					330																																																																																																																				
	Front	Multi-fixing	K1C027BL	0.121/0.267																																																																																																																					
	Rear	By Ø 22 mm/0.87 in. hole	K1C027B	0.105/0.231																																																																																																																					
			K1C027BX (2)	0.183/0.403																																																																																																																					
			K1C527B	0.140/0.309																																																																																																																					
8 decimal																																																																																																																									
	Front	Multi-fixing	K1D028BL	0.126/0.278																																																																																																																					
	Rear	By Ø 22 mm/0.87 in. hole	K1D028B	0.110/0.242																																																																																																																					
			K1D028BX (2)	0.188/0.414																																																																																																																					
			K1D528B	0.150/0.331																																																																																																																					
9 decimal																																																																																																																									
	Front	Multi-fixing	K1D029BL	0.126/0.278																																																																																																																					
	Rear	By Ø 22 mm/0.87 in. hole	K1D029B	0.110/0.242																																																																																																																					
			K1D029BX (2)	0.188/0.414																																																																																																																					
			K1D529B	0.150/0.331																																																																																																																					
10 decimal																																																																																																																									
	Front	Multi-fixing	K1D030BL	0.126/0.278																																																																																																																					
	Rear	By Ø 22 mm/0.87 in. hole	K1D030B	0.110/0.242																																																																																																																					
			K1D030BX (2)	0.188/0.414																																																																																																																					
			K1D530B	0.150/0.331																																																																																																																					
11 decimal																																																																																																																									
	Front	Multi-fixing	K1D031BL	0.126/0.278																																																																																																																					
	Rear	By Ø 22 mm/0.87 in. hole	K1D031B	0.110/0.242																																																																																																																					
			K1D531B	0.150/0.331																																																																																																																					
12 decimal																																																																																																																									
	Front	Multi-fixing	K1D032BL	0.126/0.278																																																																																																																					
	Rear	By Ø 22 mm/0.87 in. hole	K1D032B	0.110/0.242																																																																																																																					
			K1D532B	0.150/0.331																																																																																																																					

(1) $I_{th} = 12$ A.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.

Cam switches

Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)

To combine with operating heads:
see page 4/34

Paralleling switches with "0" position



K●●0●●●L

Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb	
1-pole for 2 loads						
			Front	Multi-fixing	K●B002GL	0.101/0.223
				By Ø 22 mm/ 0.87 in. hole	K●B002G	0.085/0.187
					K●B002GX (2)	0.163/0.359
			Rear		K●B502G	0.125/0.275

1-pole for 3 loads



K●●0●●●

			Front	Multi-fixing	K●C003GL	0.121/0.267
				By Ø 22 mm/ 0.87 in. hole	K●C003G	0.105/0.231
					K●C003GX (2)	0.183/0.403
			Rear		K●C503G	0.140/0.309

1-pole for 4 loads



K●●0●●●

			Front	Multi-fixing	K●D004GL	0.126/0.278
				By Ø 22 mm/ 0.87 in. hole	K●D004G	0.110/0.242
					K●D004GX (2)	0.188/0.414
			Rear		K●D504G	0.150/0.331

2-pole for 2 loads



K●●0●●●X

			Front	Multi-fixing	K●D012GL	0.126/0.278
				By Ø 22 mm/ 0.87 in. hole	K●D012G	0.110/0.242
					K●D012GX (2)	0.188/0.414
			Rear		K●D512G	0.150/0.331

2-pole for 3 loads

			Front	Multi-fixing	K●F013GL	0.156/0.344
				By Ø 22 mm/ 0.87 in. hole	K●F013G	0.140/0.309
					K●F013GX (2)	0.218/0.481
			Rear		K●F513G	0.175/0.386

(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.

Example K1B002G.











To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.

Example K2B002G.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1●●●.

To combine with operating heads:
see page 4/34

Paralleling switches with "0" position (continued)

Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
2-pole for 4 loads					
			Front	Multi-fixing	K●H014GL 0.181/0.399
				By Ø 22 mm/ 0.87 in. hole	K●H014G 0.165/0.364
					K●H014GX (2) 0.243/0.536
			Rear		K●H514G 0.195/0.430
3-pole for 2 loads					
			Front	Multi-fixing	K●F022GL 0.156/0.344
				By Ø 22 mm/ 0.87 in. hole	K●F022G 0.140/0.309
					K●F022GX (2) 0.218/0.481
			Rear		K●F522G 0.175/0.386
3-pole for 3 loads					
			Front	Multi-fixing	K●I023GL 0.201/0.443
				By Ø 22 mm/ 0.87 in. hole	K●I023G 0.185/0.408
					K●I023GX (2) 0.263/0.580
			Rear		K●I523G 0.215/0.474
3-pole for 4 loads					
			Front	Multi-fixing	K●M024GL 0.241/0.531
				By Ø 22 mm/ 0.87 in. hole	K●M024G 0.225/0.496
					K●M024GX (2) 0.303/0.668
			Rear		K●M524G 0.245/0.540


(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.

Example **K1H014G**.

To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.

Example **K2H014G**.


(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.



K●●0●●●L



K●●0●●●



K●●5●●●








K●●0●●●X

Cam switches
Adaptable sub-assemblies, 12 and 20 A
Bodies (contact blocks + fixing plate)

To combine with operating heads:
see page 4/34










Stepping switches (2 to 11 step), single-pole, with "0" position

Wiring diagram and switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
 K...0...L		2 step + "0"		
		Front	Multi-fixing	K...B002QL 0.101/0.223
			By Ø 22 mm/0.87 in. hole	K...B002Q 0.085/0.187
		Rear		K...B002QX (2) 0.163/0.359
 K...0...L		3 step + "0"		
		Front	Multi-fixing	K...C003QL 0.121/0.267
			By Ø 22 mm/0.87 in. hole	K...C003Q 0.105/0.231
		Rear		K...C003QX (2) 0.183/0.403
 K...0...L		4 step + "0"		
		Front	Multi-fixing	K...D004QL 0.126/0.278
			By Ø 22 mm/0.87 in. hole	K...D004Q 0.110/0.242
		Rear		K...D004QX (2) 0.188/0.414
 K...5...L		5 step + "0"		
		Front	Multi-fixing	K...E005QL 0.146/0.322
			By Ø 22 mm/0.87 in. hole	K...E005Q 0.130/0.287
		Rear		K...E005QX (2) 0.208/0.458
 K...0...X		6 step + "0"		
		Front	Multi-fixing	K...F006QL 0.156/0.344
			By Ø 22 mm/0.87 in. hole	K...F006Q 0.140/0.309
		Rear		K...F006QX (2) 0.218/0.481
 K...0...X		7 step + "0"		
		Front	Multi-fixing	K...G007QL 0.176/0.388
			By Ø 22 mm/0.87 in. hole	K...G007Q 0.160/0.353
		Rear		K...G007QX (2) 0.238/0.525

(1) To order a cam switch with thermal current I_{th} = 12 A, replace the ● in the reference by 1.
Example K1B002Q.
To order a cam switch with thermal current I_{th} = 20 A, replace the ● in the reference by 2.
Example K2B002Q.
(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1...●.

To combine with operating heads:
see page 4/34

Stepping switches (2 to 11 step), single-pole, with "0" position (continued)

Wiring diagram and switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
 K●●0●●●L			Front Multi-fixing	K●H008QL 0.181/0.399
			By Ø 22 mm/ 0.87 in. hole	K●H008Q 0.165/0.364
				K●H008QX (2) 0.243/0.536
			Rear	K●H508Q 0.195/0.430
 K●●0●●●			Front Multi-fixing	K●I009QL 0.201/0.443
			By Ø 22 mm/ 0.87 in. hole	K●I009Q 0.185/0.408
				K●I009QX (2) 0.263/0.580
			Rear	K●I509Q 0.215/0.474
 K●●5●●●			Front Multi-fixing	K●K010QL 0.211/0.465
			By Ø 22 mm/ 0.87 in. hole	K●K010Q 0.195/0.430
				K●K010QX (2) 0.273/0.602
			Rear	K●K510Q 0.220/0.485
 K●●0●●●X			Front Multi-fixing	K●L011QL 0.231/0.509
			By Ø 22 mm/ 0.87 in. hole	K●L011Q 0.215/0.474
				K●L011QX (2) 0.293/0.646
			Rear	K●L511Q 0.240/0.529

(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.

Example K1H008Q.

To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.











Example K2H008Q.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1●●●.

Cam switches
Adaptable sub-assemblies, 12 and 20 A
Bodies (contact blocks + fixing plate)

To combine with operating heads:
see page 4/34









Stepping switches (2 to 12 step), single-pole, without “0” position

Wiring diagram and switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
 K...0...L			2 step	
			Front	Multi-fixing By Ø 22 mm/0.87 in. hole
				K...B002NL 0.101/0.223 K...B002N 0.085/0.187 K...B002NX (2) 0.163/0.359
			Rear	K...B502N 0.125/0.275
 K...0...			3 step	
			Front	Multi-fixing By Ø 22 mm/0.87 in. hole
				K...C003NL 0.121/0.267 K...C003N 0.105/0.231 K...C003NX (2) 0.183/0.403
			Rear	K...C503N 0.140/0.309
 K...0...			4 step	
			Front	Multi-fixing By Ø 22 mm/0.87 in. hole
				K...D004NL 0.126/0.278 K...D004N 0.110/0.242 K...D004NX (2) 0.188/0.414
			Rear	K...D504N 0.150/0.331
 K...5...			5 step	
			Front	Multi-fixing By Ø 22 mm/0.87 in. hole
				K...E005NL 0.146/0.322 K...E005N 0.130/0.287 K...E005NX (2) 0.208/0.458
			Rear	K...E505N 0.165/0.364
 K...5...			6 step	
			Front	Multi-fixing By Ø 22 mm/0.87 in. hole
				K...F006NL 0.156/0.344 K...F006N 0.140/0.309 K...F006NX (2) 0.218/0.481
			Rear	K...F506N 0.175/0.386
 K...0...X			7 step	
			Front	Multi-fixing By Ø 22 mm/0.87 in. hole
				K...G007NL 0.176/0.388 K...G007N 0.160/0.353 K...G007NX (2) 0.238/0.525
			Rear	K...G507N 0.190/0.419
 K...0...X			8 step	
			Front	Multi-fixing By Ø 22 mm/0.87 in. hole
				K...H008NL 0.181/0.399 K...H008N 0.165/0.364 K...H008NX (2) 0.243/0.536
			Rear	K...H508N 0.195/0.430

(1) To order a cam switch with thermal current Ith = 12 A, replace the ● in the reference by 1.
Example K1B002N.
To order a cam switch with thermal current Ith = 20 A, replace the ● in the reference by 2.
Example K2B002N.
(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1...●.

To combine with operating heads:
see page 4/34

Stepping switches (2 to 12 step), single-pole, without "0" position (continued)

Wiring diagram and switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg
	9 step 	Front	Multi-fixing	K●I009NL 0.201/0.443
		By Ø 22 mm/ 0.87 in. hole	K●I009N 0.185/0.408	
		Rear	K●I009NX (2) 0.263/0.580	
	10 step 	Front	Multi-fixing	K●K010NL 0.211/0.465
		By Ø 22 mm/ 0.87 in. hole	K●K010N 0.195/0.430	
		Rear	K●K010NX (2) 0.273/0.602	
	11 step 	Front	Multi-fixing	K●L011NL 0.231/0.509
		By Ø 22 mm/ 0.87 in. hole	K●L011N 0.215/0.474	
		Rear	K●L011NX (2) 0.293/0.646	
	12 step 	Front	Multi-fixing	K●M021NL 0.241/0.531
		By Ø 22 mm/ 0.87 in. hole	K●M021N 0.225/0.496	
		Rear	K●M021NX (2) 0.303/0.668	

(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.
Example **K1I009N**.

To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.






Example **K2I009N**.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.

Cam switches
Adaptable sub-assemblies, 12 and 20 A
Bodies (contact blocks + fixing plate)

To combine with operating heads:
see page 4/34




Stepping switches (2 to 6 step), 2-pole, with “0” position

Wiring diagram and switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
 K...0...L			2 step + “0”	
			Front Multi-fixing	K...D012QL 0.126/0.278
			By Ø 22 mm/0.87 in. hole	K...D012Q 0.110/0.242
			Rear	K...D012QX (2) 0.188/0.414
 K...0...			3 step + “0”	
			Front Multi-fixing	K...F013QL 0.156/0.344
			By Ø 22 mm/0.87 in. hole	K...F013Q 0.140/0.309
			Rear	K...F013QX (2) 0.218/0.481
 K...5...			4 step + “0”	
			Front Multi-fixing	K...H014QL 0.181/0.399
			By Ø 22 mm/0.87 in. hole	K...H014Q 0.165/0.364
			Rear	K...H014QX (2) 0.243/0.536
 K...5...			5 step + “0”	
			Front Multi-fixing	K...K015QL 0.211/0.465
			By Ø 22 mm/0.87 in. hole	K...K015Q 0.195/0.430
			Rear	K...K015QX (2) 0.273/0.602
 K...0...X			6 step + “0”	
			Front Multi-fixing	K...M016QL 0.241/0.531
			By Ø 22 mm/0.87 in. hole	K...M016Q 0.225/0.496
			Rear	K...M016QX (2) 0.303/0.668

(1) To order a cam switch with thermal current I_{th} = 12 A, replace the ● in the reference by 1.
Example K1D012Q.
To order a cam switch with thermal current I_{th} = 20 A, replace the ● in the reference by 2.
Example K2D012Q.
(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1....

To combine with operating heads:
see page 4/34

Stepping switches (2 to 6 step), 2-pole, without "0" position

Wiring diagram and switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
		Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●D012NL	0.126/0.278
			K●D012N	0.110/0.242
			K●D012NX (2)	0.188/0.414
			K●D512N	0.150/0.331
		Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●F013NL	0.156/0.344
			K●F013N	0.140/0.309
			K●F013NX (2)	0.218/0.481
			K●F513N	0.175/0.386
		Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●H014NL	0.181/0.399
			K●H014N	0.165/0.364
			K●H014NX (2)	0.243/0.536
			K●H514N	0.195/0.430
		Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●K015NL	0.211/0.465
			K●K015N	0.195/0.430
			K●K015NX (2)	0.273/0.602
			K●K515N	0.220/0.485
		Front Multi-fixing By Ø 22 mm/0.87 in. hole	K●M016NL	0.241/0.531
			K●M016N	0.225/0.496
			K●M016NX (2)	0.303/0.668
			K●M516N	0.245/0.540

(1) To order a cam switch with thermal current $I_{th} = 12\text{ A}$, replace the ● in the reference by 1.
Example **K1D012N**.

To order a cam switch with thermal current $I_{th} = 20\text{ A}$, replace the ● in the reference by 2.
Example **K2D012N**.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.











Cam switches

Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)

To combine with operating heads:
see page 4/34

Stepping switches (2 to 6 step), 3-pole, with "0" position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
2 step + "0"					
			Front	Multi-fixing K●F022QL	0.156/0.344
			By Ø 22 mm/ 0.87 in. hole	K●F022Q	0.140/0.309
				K●F022QX (2)	0.218/0.481
			Rear	K●F522Q	0.175/0.386
3 step + "0"					
			Front	Multi-fixing K●I023QL	0.201/0.443
			By Ø 22 mm/ 0.87 in. hole	K●I023Q	0.185/0.408
				K●I023QX (2)	0.263/0.580
			Rear	K●I523Q	0.215/0.474
4 step + "0"					
			Front	Multi-fixing K●M024QL	0.241/0.531
			By Ø 22 mm/ 0.87 in. hole	K●M024Q	0.225/0.496
				K●M024QX (2)	0.303/0.668
			Rear	K●M524Q	0.245/0.540
5 step + "0"					
			Front	Multi-fixing K●P025QL	0.286/0.630
			By Ø 22 mm/ 0.87 in. hole	K●P025Q	0.270/0.595
				K●P025QX (2)	0.348/0.767
			Rear	K●P525Q	0.285/0.628
6 step + "0"					
			Front	Multi-fixing K●S026QL	0.321/0.708
			By Ø 22 mm/ 0.87 in. hole	K●S026Q	0.305/0.672
				K●S026QX (2)	0.383/0.844
			Rear	K●S526Q	0.320/0.705

(1) To order a cam switch with thermal current $I_{th} = 12\text{ A}$, replace the ● in the reference by 1.

Example **K1F022Q**.











To order a cam switch with thermal current $I_{th} = 20\text{ A}$, replace the ● in the reference by 2.

Example **K2F022Q**.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.

To combine with operating heads:
see page 4/34

Stepping switches (2 to 6 step), 3-pole, without "0" position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
 K●●0●●●L			2 step 	Front Multi-fixing K●F022NL 0.156/0.344	
				By Ø 22 mm/ 0.87 in. hole K●F022N 0.140/0.309	
				K●F022NX (2) 0.218/0.481	
				Rear K●F522N 0.175/0.386	
 K●●0●●●			3 step 	Front Multi-fixing K●I023NL 0.201/0.443	
				By Ø 22 mm/ 0.87 in. hole K●I023N 0.185/0.408	
				K●I023NX (2) 0.263/0.580	
				Rear K●I523N 0.215/0.474	
 K●●0●●●			4 step 	Front Multi-fixing K●M024NL 0.241/0.531	
				By Ø 22 mm/ 0.87 in. hole K●M024N 0.225/0.496	
				K●M024NX (2) 0.303/0.668	
				Rear K●M524N 0.245/0.540	
 K●●5●●●			5 step 	Front Multi-fixing K●P025NL 0.286/0.630	
				By Ø 22 mm/ 0.87 in. hole K●P025N 0.270/0.595	
				K●P025NX (2) 0.348/0.767	
				Rear K●P525N 0.285/0.628	
 K●●0●●●X			6 step 	Front Multi-fixing K●S026NL 0.321/0.708	
				By Ø 22 mm/ 0.87 in. hole K●S026N 0.305/0.672	
				K●S026NX (2) 0.383/0.844	
				Rear K●S526N 0.320/0.705	

(1) To order a cam switch with thermal current Ith = 12 A, replace the ● in the reference by 1.

Example **K1F022N**.










To order a cam switch with thermal current Ith = 20 A, replace the ● in the reference by 2.

Example **K2F022N**.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.

To combine with operating heads:
see page 4/34

Stepping switches (2 to 5 step), 4-pole, with "0" position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
 K●●0●●●L			2 step + "0"		
			Front	Multi-fixing K●H032QL By Ø 22 mm/ 0.87 in. hole K●H032Q K●H032QX (2)	0.181/0.399 0.165/0.364 0.200/0.441
			Rear	K●H532Q	0.195/0.430
 K●●0●●●			3 step + "0"		
			Front	Multi-fixing K●M033QL By Ø 22 mm/ 0.87 in. hole K●M033Q	0.241/0.531 0.225/0.496
			Rear	K●M533Q	0.245/0.540
 K●●5●●●			4 step + "0"		
			Front	Multi-fixing K●Q034QL By Ø 22 mm/ 0.87 in. hole K●Q034Q	0.296/0.653 0.280/0.617
			Rear	K●Q534Q	0.295/0.650
 K●●0●●●X			5 step + "0"		
			Front	Multi-fixing K●U035QL By Ø 22 mm/ 0.87 in. hole K●U035Q	0.351/0.774 0.335/0.738
			Rear	K●U535Q	0.345/0.761

(1) To order a cam switch with thermal current $I_{th} = 12\text{ A}$, replace the ● in the reference by 1.

Example **K1H032Q**.










To order a cam switch with thermal current $I_{th} = 20\text{ A}$, replace the ● in the reference by 2.

Example **K2H032Q**.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.

To combine with operating heads:
see page 4/34

Stepping switches (2 to 5 step), 4-pole, without "0" position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
 K●●0●●●L			2 step 	Front	Multi-fixing K●H032NL 0.181/0.399
				By Ø 22 mm/ 0.87 in. hole K●H032N 0.165/0.364	
 K●●0●●●			3 step 	Front	Multi-fixing K●M033NL 0.241/0.531
				By Ø 22 mm/ 0.87 in. hole K●M033N 0.225/0.496	
 K●●5●●●			4 step 	Front	Multi-fixing K●Q034NL 0.296/0.653
				By Ø 22 mm/ 0.87 in. hole K●Q034N 0.280/0.617	
 K●●0●●●X			5 step 	Front	Multi-fixing K●U035NL 0.351/0.774
				By Ø 22 mm/ 0.87 in. hole K●U035N 0.335/0.738	
				Rear	K●U535N 0.345/0.761

(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.

Example **K1H032N**.

To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.

Example **K2H032N**.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.




To combine with operating heads:
see page 4/34

Voltmeter switches

Wiring diagram	Switching programme	Switch position	Mounting method	Reference (1)	Weight kg/lb
----------------	---------------------	-----------------	-----------------	---------------	--------------


For measurements between 3 phases and neutral

With "0" position



Front	Multi-fixing	K1D023ML	0.126/0.278
	By Ø 22 mm/ 0.87 in. hole	K1D023M	0.110/0.242
Rear		K1D023MX (2)	0.188/0.414
		K1D523M	0.150/0.331



Without "0" position



Front	Multi-fixing	K1D033ML	0.126/0.278
	By Ø 22 mm/ 0.87 in. hole	K1D033M	0.110/0.242
Rear		K1D533M	0.150/0.331


For measurements between 3 phases

With "0" position



Front	Multi-fixing	K1D024ML	0.126/0.278
	By Ø 22 mm/ 0.87 in. hole	K1D024M	0.110/0.242
		K1D024MX (2)	0.188/0.414
Rear		K1D524M	0.150/0.331




Without "0" position



Front	Multi-fixing	K1D034ML	0.126/0.278
	By Ø 22 mm/ 0.87 in. hole	K1D034M	0.110/0.242
Rear		K1D534M	0.150/0.331


For measurements between 3 phases and between 1 phase and neutral

With "0" position



Front	Multi-fixing	K1E025ML	0.146/0.322
	By Ø 22 mm/ 0.87 in. hole	K1E025M	0.130/0.287
		K1E025MX (2)	0.208/0.458
Rear		K1E525M	0.165/0.364

Without "0" position



Front	Multi-fixing	K1E035ML	0.146/0.322
	By Ø 22 mm/ 0.87 in. hole	K1E035M	0.130/0.287
		K1E535M	0.165/0.364














(1) $I_{th} = 12$ A.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1●●●.

Cam switches

Adaptable sub-assemblies, 12 and 20 A
Bodies (contact blocks + fixing plate)









To combine with operating heads:
see page 4/34

Voltmeter switches (continued)					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference (1)	Weight kg/lb
For measurements between 3 phases of 2 supplies					
	With "0" position			Front Multi-fixing K1H026ML 0.181/0.399	
				By Ø 22 mm/ 0.87 in. hole K1H026M 0.165/0.364	
	Without "0" position			Front Multi-fixing K1H036ML 0.181/0.399	
				By Ø 22 mm/ 0.87 in. hole K1H036M 0.165/0.364	
	With "0" position			Front Multi-fixing K1F027ML 0.156/0.344	
				By Ø 22 mm/ 0.87 in. hole K1F027M 0.140/0.309	
	Without "0" position			K1F027MX (2) 0.218/0.481	
				Rear K1F527M 0.175/0.386	
	With "0" position			Front Multi-fixing K1F037ML 0.156/0.344	
				By Ø 22 mm/ 0.87 in. hole K1F037M 0.140/0.309	
	Without "0" position			K1F537M 0.175/0.386	

(1) Ith = 12 A.
(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.

To combine with operating heads:
see page 4/34

Stepping switches (2 and 3 step), with "0" position + left-hand position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
 K●●0●●●L			Front Multi-fixing	K●C002LL	0.121/0.267
			By Ø 22 mm/ 0.87 in. hole	K●C002L	0.105/0.231
			Rear	K●C502L	0.183/0.403
 K●●0●●●			Front Multi-fixing	K●D003LL	0.126/0.278
			By Ø 22 mm/ 0.87 in. hole	K●D003L	0.110/0.242
			Rear	K●D503L	0.188/0.414
 K●●0●●●			Front Multi-fixing	K●F012LL	0.156/0.344
			By Ø 22 mm/ 0.87 in. hole	K●F012L	0.140/0.309
			Rear	K●F512L	0.218/0.481
 K●●0●●●			Front Multi-fixing	K●H013LL	0.181/0.399
			By Ø 22 mm/ 0.87 in. hole	K●H013L	0.165/0.364
			Rear	K●H513L	0.243/0.536
 K●●5●●●			Front Multi-fixing	K●I022LL	0.201/0.443
			By Ø 22 mm/ 0.87 in. hole	K●I022L	0.185/0.408
			Rear	K●I522L	0.210/0.463
 K●●0●●●X			Front Multi-fixing	K●M023LL	0.241/0.531
			By Ø 22 mm/ 0.87 in. hole	K●M023L	0.225/0.496
			Rear	K●M523L	0.245/0.540

(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.

Example K1C022Q.











To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.

Example K2C022Q.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1●●●.

Cam switches
Adaptable sub-assemblies, 12 and 20 A
Bodies (contact blocks + fixing plate)

To combine with operating heads:
see page 4/34

Multi-circuit switches					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
1-pole					
			Front	Multi-fixing	K●B001SL 0.101/0.223
				By Ø 22 mm/ 0.87 in. hole	K●B001S 0.085/0.187
				K●B001SX (2)	0.163/0.359
			Rear		K●B501S 0.125/0.275
2-pole					
			Front	Multi-fixing	K●D002SL 0.126/0.278
				By Ø 22 mm/ 0.87 in. hole	K●D002S 0.110/0.242
				K●D002SX (2)	0.188/0.414
			Rear		K●D502S 0.150/0.331
3-pole					
			Front	Multi-fixing	K●F003SL 0.156/0.344
				By Ø 22 mm/ 0.87 in. hole	K●F003S 0.140/0.309
				K●F003SX (2)	0.218/0.481
			Rear		K●F503S 0.175/0.386
4-pole					
			Front	Multi-fixing	K●H004SL 0.181/0.399
				By Ø 22 mm/ 0.87 in. hole	K●H004S 0.165/0.364
			Rear		K●H504S 0.195/0.430
5-pole					
			Front	Multi-fixing	K●K005SL 0.211/0.465
				By Ø 22 mm/ 0.87 in. hole	K●K005S 0.195/0.430
			Rear		K●K505S 0.220/0.485

(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.
Example **K1F003S**.

To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.
Example **K2F003S**.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.

To combine with operating heads:
see page 4/34



Reversing switches with "0" position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
----------------	---------------------	-----------------	-----------------	-------------------------------	--------------

2-pole



K●●0●●●L





Front	Multi-fixing	K●D002WL	0.126/0.278
	By Ø 22 mm/ 0.87 in. hole	K●D002W	0.110/0.242
		K●D002WX (2)	0.188/0.414
Rear		K●D502W	0.150/0.331

3-pole



K●●0●●●



Front	Multi-fixing	K●E003WL	0.146/0.322
	By Ø 22 mm/ 0.87 in. hole	K●E003W	0.130/0.287
		K●E003WX (2)	0.208/0.458
Rear		K●E503W	0.165/0.364



Reversing switches with spring return from 330° and from 30° to "0" position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
----------------	---------------------	-----------------	-----------------	-------------------------------	--------------

2-pole



K●●5●●●





Front	Multi-fixing	K●D022WL	0.126/0.278
	By Ø 22 mm/ 0.87 in. hole	K●D022W	0.110/0.242
		K●D022WX (2)	0.188/0.414
Rear		K●D522W	0.150/0.331

3-pole



K●●0●●●X



Front	Multi-fixing	K●E023WL	0.146/0.322
	By Ø 22 mm/ 0.87 in. hole	K●E023W	0.130/0.287
		K●E023WX (2)	0.208/0.458
Rear		K●E523W	0.165/0.364

(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.
Example K1D002W.


To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.

Example K2D002W.

(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1●●●.

Cam switches
Adaptable sub-assemblies, 12 A
Bodies (contact blocks + fixing plate)

To combine with operating heads:
see page 4/34



K20000L


Star-delta switches					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference (1)	Weight kg/lb
			Front Multi-fixing	K2H001YL	0.181/0.399
			By Ø 22 mm/ 0.87 in. hole	K2H001Y	0.165/0.364
				K2H001YX (2)	0.243/0.536
			Rear	K2H501Y	0.195/0.430

With slave contact, without supply disconnection					
			Front Multi-fixing	K2G003YL	0.176/0.388
			By Ø 22 mm/ 0.87 in. hole	K2G003Y	0.160/0.353
				K2G003YX (2)	0.238/0.525
			Rear	K2G503Y	0.190/0.419



K20000

With slave contact, with supply disconnection					
			Front Multi-fixing	K2K004YL	0.211/0.465
			By Ø 22 mm/ 0.87 in. hole	K2K004Y	0.195/0.430
				K2K004YX (2)	0.273/0.602
			Rear	K2K504Y	0.220/0.485



K20005

Reversing star-delta switches					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference (1)	Weight kg/lb
Without slave contact					
			Front Multi-fixing	K2K006YL	0.211/0.465
			By Ø 22 mm/ 0.87 in. hole	K2K006Y	0.195/0.430
				K2K506Y	0.220/0.485






K20006X

(1) Ith = 20 A.
(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAXZ1000.

To combine with operating heads:
see page 4/34

Reversing star-delta switches (continued)

Wiring diagram	Switching programme	Switch position	Mounting method	Reference (2)	Weight kg/lb	
With slave contact						
			Front	Multi-fixing	K2M007YL	0.241/0.531
				By Ø 22 mm/ 0.87 in. hole	K2M007Y	0.225/0.496
			Rear		K2M507Y	0.245/0.540

K●●0●●●L

Pole change switches for 2-speed motors

Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb	
For motors with 2 separate windings						
			Front	Multi-fixing	K●F001PL	0.156/0.344
				By Ø 22 mm/ 0.87 in. hole	K●F001P	0.140/0.309
					K●F001PX (3)	0.218/0.481
			Rear		K●F501P	0.175/0.386




K●●0●●●

For motors with 2 separate windings, with centre "0" position

			Front	Multi-fixing	K●F002PL	0.156/0.344
				By Ø 22 mm/ 0.87 in. hole	K●F002P	0.140/0.309
					K●F002PX (3)	0.218/0.481
			Rear		K●F502P	0.175/0.386

K●●5●●●

For motors with tapped "Dahlander" windings

			Front	Multi-fixing	K●H004PL	0.181/0.399
				By Ø 22 mm/ 0.87 in. hole	K●H004P	0.165/0.364
				K●H004PX (3)	0.243/0.536	
			Rear		K●H504P	0.195/0.430

K●●0●●●X

(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.

Example **K1F001P**.

To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.

Example **K2F001P**.




(2) $I_{th} = 20$ A.


(3) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.

Cam switches
Adaptable sub-assemblies, 12 and 20 A
Bodies (contact blocks + fixing plate)

To combine with operating heads:
see page 4/34


Pole change switches for 2-speed motors (continued)					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb

For motors with tapped “Dahlander” windings, with centre “0” position				
			Front	Multi-fixing K●H005PL 0.181/0.399
				By Ø 22 mm/ 0.87 in. hole K●H005P 0.165/0.364
				K●H005PX (2) 0.243/0.536
			Rear	K●H505P 0.195/0.430




K●●0●●●L

Reversing pole change switches for 2-speed motors					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb



For motors with 2 separate windings, with centre "0" position				
			Front	Multi-fixing K●K008PL 0.211/0.465
				By Ø 22 mm/ 0.87 in. hole K●K008P 0.195/0.430
			Rear	K●K508P 0.220/0.485



K●●0●●●



K●●5●●●

For motors with tapped “Dahlander” windings, with centre “0” position				
			Front	Multi-fixing K●M009PL 0.241/0.531
				By Ø 22 mm/ 0.87 in. hole K●M009P 0.225/0.496
			Rear	K●M509P 0.245/0.540



K●●0●●●X



(1) To order a cam switch with thermal current $I_{th} = 12\text{ A}$, replace the ● in the reference by 1.
Example **K1H005P**.
To order a cam switch with thermal current $I_{th} = 20\text{ A}$, replace the ● in the reference by 2.
Example **K2H005P**.
(2) Bodies using the Ø 22 mm/0.87 in. hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAXZ1●●●**.

To combine with operating heads:
see page 4/34

Pole change switches for 3-speed motors


Wiring diagram	Switching programme	Switch position	Mounting method	Reference to be completed (1)	Weight kg/lb
----------------	---------------------	-----------------	-----------------	-------------------------------	--------------

For motors with open tapped "Dahlander" winding and separate winding for low speed




Front	Multi-fixing	K●L010PL	0.231/0.509
	By Ø 22 mm/ 0.87 in. hole	K●L010P	0.215/0.474
Rear		K●L510P	0.240/0.529

For motors with open tapped "Dahlander" winding and separate winding for intermediate speed




Front	Multi-fixing	K●L011PL	0.231/0.509
	By Ø 22 mm/ 0.87 in. hole	K●L011P	0.215/0.474
Rear		K●L511P	0.240/0.529



For motors with open tapped "Dahlander" winding and separate winding for high speed

K●●5●●●



Front	Multi-fixing	K●L012PL	0.231/0.509
	By Ø 22 mm/ 0.87 in. hole	K●L012P	0.215/0.474
Rear		K●L512P	0.240/0.529



(1) To order a cam switch with thermal current $I_{th} = 12$ A, replace the ● in the reference by 1.
Example K1L010P.
To order a cam switch with thermal current $I_{th} = 20$ A, replace the ● in the reference by 2.
Example K2L010P.


To combine with bodies: see pages 4/2 to 4/33




KBG3H



KCG3Y




KAC1H



KCC1Y



KBC1●



KBD1H

Heads for “multi-fixing” front mounting bodies

Description	Switching angle and marking	Type of operator	Background colour of legend	Padlocking device	Reference	Weight kg/lb
With 45 x 45 mm/1.77 x 1.77 in. front plate and handle						
With blank legend (for engraving by user)	–	Black handle L = 35 mm/1.38 in.	Matt black	Without	KAG3H	0.012/0.026
			Metallic	Without	KBG3H	0.012/0.026
With marked legend	90°	Red handle L = 35 mm/1.38 in.	Yellow	Without	KCG3H	0.012/0.026
				With	KCG3Y	0.024/0.053
Without legend (1)	–	Black handle L = 35 mm/1.38 in.	–	Without	KDG3H	0.010/0.022
		Red handle L = 35 mm/1.38 in.	–	With	KDG3Y	0.022/0.048


Heads for Ø 22 mm/0.87 in. hole, front mounting bodies

Description	Switching angle and marking	Type of operator	Background colour of legend	Padlocking device	Reference	Weight kg/lb
With 45 x 45 mm/1.77 x 1.77 in. front plate and handle						
With blank legend (for engraving by user)	–	Black handle L = 35 mm/1.38 in.	Matt black	Without	KAC1H	0.048/0.106
			Metallic	Without	KBC1H	0.048/0.106
With marked legend	45°	Black handle L = 35 mm/1.38 in.	Matt black	Without	KAC1H41	0.012/0.026
			Metallic	Without	KBC1H41	0.012/0.026
	45°	Black handle L = 35 mm/1.38 in.	Matt black	Without	KAC1H48	0.012/0.026
			Metallic	Without	KBC1H48	0.012/0.026
	60°	Black handle L = 35 mm/1.38 in.	Matt black	Without	KAC1H61	0.048/0.106
			Metallic	Without	KBC1H61	0.048/0.106
	90°	Red handle L = 35 mm/1.38 in.	Yellow	Without	KCC1LH	0.048/0.106
				With	KCC1Y	0.060/0.132
Without legend (1)	–	Black handle L = 35 mm/1.38 in.	–	Without	KDC1H	0.046/0.101
		Red handle L = 35 mm/1.38 in.	–	Without	KDC1LH	0.046/0.101
With 45 x 45 mm/1.77 x 1.77 in. front plate and key operator (2)						
With blank legend (for engraving by user)	45° and 90°	Key (2)	Matt black	Without	KAC1S	0.063/0.139
			Metallic	Without	KBC1S	0.063/0.139
	60°	Key (2)	Matt black	Without	KAC1Z	0.063/0.139
			Metallic	Without	KBC1Z	0.063/0.139
Without legend (1)	45° and 90°	Key (2)	–	Without	KDC1S	0.061/0.134
	60°	Key (2)	–	Without	KDC1Z	0.061/0.134
With 60 x 60 mm/2.36 x 2.36 in. front plate and handle						
With blank legend (for engraving by user)	–	Black handle L = 42 mm/1.65 in.	Matt black	Without	KAD1H	0.053/0.117
			Metallic	Without	KBD1H	0.053/0.117
With marked legend	90°	Red handle L = 42 mm/1.65 in.	Yellow	Without	KCD1MH	0.053/0.117
Without legend (1)	–	Black handle L = 42 mm/1.65 in.	–	Without	KDD1H	0.053/0.117

(1) For separate marked legend ordering information, see pages 4/36 to 4/39.

(2) Head supplied with “Ronis” 8R1 key. To order a head with a “Ronis” 455 key, add the suffix **R** to the references listed above.
Example: reference for Ø 22 mm/0.87 in. hole, front mounting 45 x 45 mm/1.77 x 1.77 in. operating head with 45° switching angle and matt black legend, becomes **KAC1SR**. For a head with “Ronis” 8R15 key, use the suffix **R1**.

To combine with bodies: see pages 4/2 to 4/33



KBD1●



KBA1H



KBA1●



KAXZ1C12



KBE1H

Heads for Ø 22 mm/0.87 in. hole, front mounting bodies (continued)

Description	Switching angle and marking	Type of operator	Background colour of legend	Padlocking device	Reference	Weight kg/lb
With 60 x 60 mm/2.36 x 2.36 in. front plate and key operator (1)						
With blank legend (to be engraved by user)	45° and 90°	Key (1)	Matt black	Without	KAD1S	0.068/0.150
			Metallic	Without	KBD1S	0.068/0.150
	60°	Key (1)	Matt black	Without	KAD1Z	0.068/0.150
			Metallic	Without	KBD1Z	0.068/0.150
Without legend (2)	45° and 90°	Key (1)	—	Without	KDD1S	0.066/0.145
	60°	Key (1)	—	Without	KDD1Z	0.066/0.145

Description	Switching angle and marking	Type of operator	Colour of bezel	Padlocking device	Reference	Weight kg/lb
With Ø 29 mm/1.14 in., metallic finish, plastic bezel and handle or key operator (1)						
Circular heads	—	Black handle L = 35 mm/1.38 in.	Matt black	Without	KAA1H	0.042/0.093
			Metallic	Without	KBA1H	0.042/0.093
	45°	Key (1)	Matt black	Without	KAA1S	0.057/0.126
			Metallic	Without	KBA1S	0.057/0.126
	60°	Key (1)	Matt black	Without	KAA1Z	0.057/0.126
			Metallic	Without	KBA1Z	0.057/0.126

With Ø 38 mm /1.50 in., black, plastic bezel and handle

Circular head	—	Black handle L = 35 mm/1.38 in.	Matt black	Without	KAA2H	0.048/0.106
----------------------	---	------------------------------------	------------	---------	--------------	-------------

With Ø 28.5 mm/1.12 in., chromium plated, metal bezel (3) (2) and standard, handle, long handle or key operator (4)

Circular heads	—	Standard black handle	Metal	Without	KAXZ1M12	0.040/0.088
		Standard red handle	Metal	Without	KAXZ1M14	0.040/0.088
		Long black handle	Metal	Without	KAXZ1C12	0.040/0.088
		Long red handle	Metal	Without	KAXZ1C14	0.040/0.088
	30°	Key	Metal	Without	KAXZ1S13● (4)	0.065/0.143
	45°	Key	Metal	Without	KAXZ1S14● (4)	0.065/0.143
	60°	Key	Metal	Without	KAXZ1S16● (4)	0.065/0.143
	90°	Key	Metal	Without	KAXZ1S19● (4)	0.065/0.143

Operating heads for 4 hole, rear mounting bodies

Description	Switching angle and marking	Type of operator	Background colour of legend	Padlocking device	Reference	Weight kg/lb
With 45 x 45 mm/1.77 x 1.77 in. front plate and handle						
With blank legend (to be engraved by user)	—	Black handle L = 35 mm/1.38 in.	Matt black	Without	KAE1H	0.029/0.064
			Metallic	Without	KBE1H	0.029/0.064
With marked legend	90°	Red handle L = 35 mm/1.38 in.	Yellow	Without	KCE1LH	0.029/0.064
				With	KCE1Y	0.060/0.132



Without legend (2)	—	Black handle L = 35 mm/1.38 in.	—	Without	KDE1H	0.027/0.059
		Red handle L = 35 mm/1.38 in.	—	Without	KDE1LH	0.027/0.059

With 60 x 60 mm/2.36 x 2.36 in. front plate and handle

With blank legend (to be engraved by user)	—	Black handle L = 42 mm/1.65 in	Matt black	Without	KAF1H	0.068/0.150
			Metallic	Without	KBF1H	0.068/0.150
With marked legend	90°	Red handle L = 42 mm/1.65 in	Yellow	Without	KCF1MH	0.068/0.150
Without legend (2)	—	Black handle L = 42 mm/1.65 in	—	Without	KDF1H	0.066/0.145

(1) Head supplied with "Ronis" 8R1 key. To order a head with a "Ronis" 455 key, add the suffix **R** to the references listed above.Example: reference for operating head with 60 x 60 mm/2.36 x 2.36 in. front plate, key operator, blank legend, 45° switching angle and matt black background, becomes **KAD1SR**. For a head with "Ronis" 8R15 key, use the suffix **R1**.

(2) For separate marked legend ordering information, see pages 4/36 to 4/39.

(3) Heads **only** for use with bodies K●●●●●X, incorporating adaptor plate **KZ127**. See pages 4/2 to 4/32.

(4) To order:

- a head with key n° 455, replace the ● in the reference by 1. Example: **KAXZ1S131**,- a head with key n° 421, replace the ● in the reference by 2. Example: **KAXZ1S132**,- a head with key n° 520, replace the ● in the reference by 3. Example: **KAXZ1S133**,- a head with a special key, replace the ● in the reference by 9. Example: **KAXZ1S139** (state the key number on the order).

Key withdrawal from all positions.


Cam switches

Adaptable sub-assemblies, 12 and 20 A
Legends for **MULTI-FIXING** heads


45 x 45 mm/1.77 x 1.77 in. legends - marked (1)

White text on black background


30°



45°



60°



90°




Black text on yellow background

45°

KZ19041L



90°



45 x 45 mm/1.77 x 1.77 in. legends - unmarked

Colour	Sold in lots of	Unit reference	Weight kg/lb
Black	20	KZ17L	0.003/0.007
Metallic	20	KZ18L	0.003/0.007
Yellow	10	KZ19L	0.003/0.007

(1) Weight = 0.003 kg/0.007 lb.

Cam switches

Adaptable sub-assemblies, 12 and 20 A

Legends for Ø 22 mm HOLE mounting heads with plastic bezel

45 x 45 mm/1.77 x 1.77 in. legends - marked (1)

Black text on metallic background

30°

KZ18032



KZ18312



45°

KZ18041



KZ18042



KZ18043



KZ18044



KZ18045



KZ18046



KZ18047



KZ18048



KZ18412



KZ18413



KZ18415



KZ18416



KZ18417



KZ18418



KZ18419



KZ18420



KZ18421



KZ18422F



KZ18423F



KZ18434



KZ18436F



KZ18451



60°

KZ18061



KZ18630



KZ18631



KZ18632



KZ18634



KZ18635



KZ18637



KZ18068



90°

KZ18091



KZ18093



KZ18913



KZ18931F



Black text on yellow background

45°

KZ19041



90°

KZ19093



KZ19098F



KZ19910



45 x 45 mm/1.77 x 1.77 in.. legends - unmarked

Colour	Sold in lots of	Unit reference	Weight kg/lb
Black	20	KZ17	0.003/0.007
Metallic	20	KZ18	0.003/0.007
Yellow	10	KZ19	0.003/0.007

60 x 60 mm/2.36 x 2.36 in. legends - marked (2)

Black text on metallic background

45°

KZ21041



KZ21412



KZ21048



KZ21451



KZ21635



KZ21637



KZ21910



KZ21093



60 x 60 mm/2.36 x 2.36 in. legends - unmarked

Colour	Sold in lots of	Unit reference	Weight kg/lb
Black	20	KZ20	0.003/0.007
Metallic	20	KZ21	0.003/0.007
Yellow	10	KZ22	0.003/0.007

(1) Weight = 0.003 kg/0.007 lb.

(2) Weight = 0.005 kg/0.011 lb.

Cam switches


Adaptable sub-assemblies, 12 and 20 A

Legends for Ø 22 mm HOLE mounting heads with chromium plated metal bezel, type KAXZ1●●●


46 x 46 mm - marked (PVC) (1)

White text on black background


30°




45°



60°



90°




46 x 46 mm legends - unmarked (PVC)

Colour	Sold in lots of	Unit reference	Weight kg/lb
Black/red	10	KZ17X	0.004/0.009
White/yellow	10	KZ19X	0.004/0.009


(1) Weight = 0.004 kg/0.009 lb.

Cam switches

Adaptable sub-assemblies, 12 and 20 A
Legend holders for heads



KZ13




KZ15




KZ01R



KZ2



KZ14



KZ16

Legend holders with and without legend

Description	For use with heads	Legend marking	Sold in lots of	Unit reference	Weight kg/lb
With blank legend	With 45 x 45 mm/1.77 x 1.77 in. front – plate (1)		5	KZ13	0.004/0.009
	With 60 x 60 mm/2.36 x 2.36 in. front plate (1)	–	5	KZ15	0.010/0.022
	Circular, with Ø 29 mm/1.14 in. collar	–	5	KZ01R	0.010/0.022
With marked legend	Circular, with Ø 29 mm/1.14 in. collar	1 2	1	KZ1	0.003/0.007
		2 0 1	5	KZ2	0.003/0.007
Without legend	With 45 x 45 mm/1.77 x 1.77 in. front plate (1)	–	20	KZ14	0.003/0.007
	With 60 x 60 mm/2.36 x 2.36 in. front plate (1)	–	10	KZ16	0.007/0.015

Blank legends (for engraving) for legend holders

Description	For use with heads	Sold in lots of	Unit reference	Weight kg/lb
Legend for legend holder KZ14 Plastic with metallic finish. Self-adhesive. For engraved markings.	With 45 x 45 mm/1.77 x 1.77 in. front plate (1)	20	KZ76	0.002/0.004
Legend for legend holder KZ16 Plastic with metallic finish. Self-adhesive. For engraved markings.	With 60 x 60 mm/2.36 x 2.36 in. front plate (1)	10	KZ77	0.003/0.007


(1) Operating heads for single Ø 22 mm/0.87 in. hole or 4 hole mounting.

Cam switches


Complete switches, 12 and 20 A
Separate components and accessories




KZ27H




KZ27




KZ32




KZ83



KZ127



KZ140




KZ141

Handles


Description	Colour	Dimensions	Sold in lots of	Unit reference	Weight
		mm/in.			kg/lb
New shape	Black	35/1.38	5	KZ27H	0.007/0.015
		42/1.65	5	KZ28H	0.009/0.020
	Red	35/1.38	5	KZ41H	0.007/0.015
		42/1.65	5	KZ42H	0.009/0.020
Old shape	Black	34/1.34	5	KZ27	0.007/0.015
		42/1.65	5	KZ28	0.009/0.020

Accessories


Description	For use with	Dimensions	Sold in lots of	Unit reference	Weight
		mm/in.			kg/lb
Door interlocking plate	Rear mounting switches	45 x 45/ 1.77 x 1.77	5	KZ32	0.010/0.022
Plate with rubber seal	Rear mounting switches. IP 65 between front plate and operating head	60 x 60/ 2.36 x 2.36	5	KZ83	0.018/0.040
Adaptor plate, metal (replacement)	Mounting KAXZ1... chromium plated metal bezel heads on front mounting bodies for Ø 22 mm/0.87 in. hole	—	1	KZ127	0.088/0.194
Plastic plate (replacement)	Ø 22 mm/0.87 in. hole, front mounting, clip-in bodies	—	1	KZ140	0.010/0.022
Multi-fixing plate (replacement)	"Multi-fixing", front mounting, — bodies	—	1	KZ141	0.026/0.057




KZ6●



KZ5●



KZ3●



Z01




KZ30



KZ93




Z18



KZ31



KZ95



KZ91H

Accessories (continued)


Description	For use with		Sold in lots of	Unit reference	Weight kg/lb
Rubber seals for IP 65 degree of protection	Ø 22 mm/0.87 in. or 4 hole, front mounting, operating heads with 45 x 45 mm/1.77 x 1.77 in. front plate		5	KZ65	0.003/0.007
	Ø 22 mm/0.87 in. or 4 hole, front mounting, operating heads with 60 x 60 mm/2.36 x 2.36 in. front plate		5	KZ66	0.004/0.009
	Multi-fixing operating heads with 45 x 45 mm/1.77 x 1.77 in. front plate		5	KZ73	0.004/0.009
Shaft couplers	Ø 6 mm/0.24 in. shaft	Length = 26 mm/1.02 in.	3	KZ52	0.007/0.015
		Length = 60 mm/2.36 in.	3	KZ50	0.013 /0.029
Terminal covers	Contact blocks	4 contacts	1	KZ35	0.010/0.022
		8 contacts	1	KZ36	0.020 /0.044
		12 contacts	1	KZ37	0.004/0.009
		16 contacts	1	KZ38	0.040/0.088
		20 contacts	1	KZ39	0.050 /0.110
Nut wrench	M22 fixing nuts		5	Z01	0.010/0.022
Fixing nut, M22	Fixing operating heads on panel or in an enclosure		5	KZ30	0.007/0.015
Mounting adaptor	Converting Ø 30.5 mm/1.20 in. fixing hole to Ø 22.5 mm/0.88 in.		50	KZ93	0.003/0.007
Keys	8D1 key lock		2	Z18	0.010/0.022
	"Ronis" 8R1 key lock		2	Z18R1	0.010/0.022
	"Ronis" 455 key lock		2	Z18R	0.010/0.022
	"Ronis" 8R15 key lock		2	Z18R15	0.010/0.022
Quick assembly device	Mounting on 35 mm/1.38 in. rails to DIN 46277. 2 fixing screws included for rear mounting		5	KZ31	0.030/0.066
Fixing screws 3.5 x 16 mm/0.14 x 0.63 in.	4 hole fixing operating heads		100	KZ95	0.001/0.066
Cam switch installation kit Comprising: - mounting plate, - 45 x 45 mm/1.77 x 1.77 in. front plate, without legend - black handle, length 35 mm/1.38 in. (KZ27H), - 2 fixing screws	Installation of a cam switch on a distribution panel		1	KZ91H	0.010/0.022

Complete switches, 12 A with key operated lock

- Front mounting by 6 screws Ø 5.2 mm, with 55 x 100mm front plate
- Stepping switches, 2 to 5 step..... 5/2
- Start selector switches changeover switches..... 5/6
- Changeover switches 5/7

Cam switches

Complete switches, 12 A with key operated lock
Front mounting by 6 screws Ø 5.2 mm
with 55 x 100 mm front plate



K1C003NZ2

Stepping switches (3 step), without “0” position																																																																													
Wiring diagram and switching programme	Marking and switch position	Colour of handle	Reference	Weight kg/lb																																																																									
1-pole																																																																													
 <table border="1"><tr><td>0</td><td>60</td><td>120</td><td>1</td></tr><tr><td>X</td><td></td><td></td><td>2</td></tr><tr><td></td><td>X</td><td></td><td>3</td></tr><tr><td></td><td></td><td>X</td><td>4</td></tr><tr><td></td><td></td><td></td><td>5</td></tr><tr><td></td><td></td><td></td><td>6</td></tr></table>	0	60	120	1	X			2		X		3			X	4				5				6	 	Red Black	K1C003NZ2 K1C003NZ4	0.170/0.374 0.170/0.374																																																	
0	60	120	1																																																																										
X			2																																																																										
	X		3																																																																										
		X	4																																																																										
			5																																																																										
			6																																																																										
2-pole																																																																													
 <table border="1"><tr><td>0</td><td>60</td><td>120</td><td>1</td></tr><tr><td>X</td><td></td><td></td><td>2</td></tr><tr><td></td><td>X</td><td></td><td>3</td></tr><tr><td></td><td></td><td>X</td><td>4</td></tr><tr><td></td><td></td><td></td><td>5</td></tr><tr><td></td><td></td><td></td><td>6</td></tr><tr><td></td><td></td><td></td><td>7</td></tr><tr><td></td><td></td><td></td><td>8</td></tr><tr><td></td><td></td><td></td><td>9</td></tr><tr><td></td><td></td><td></td><td>10</td></tr><tr><td></td><td></td><td></td><td>11</td></tr><tr><td></td><td></td><td></td><td>12</td></tr></table>	0	60	120	1	X			2		X		3			X	4				5				6				7				8				9				10				11				12	 	Red Black	K1F013NZ2 K1F013NZ4	0.170/0.374 0.170/0.374																									
0	60	120	1																																																																										
X			2																																																																										
	X		3																																																																										
		X	4																																																																										
			5																																																																										
			6																																																																										
			7																																																																										
			8																																																																										
			9																																																																										
			10																																																																										
			11																																																																										
			12																																																																										
3-pole																																																																													
 <table border="1"><tr><td>0</td><td>60</td><td>120</td><td>1</td></tr><tr><td>X</td><td></td><td></td><td>2</td></tr><tr><td></td><td>X</td><td></td><td>3</td></tr><tr><td></td><td></td><td>X</td><td>4</td></tr><tr><td></td><td></td><td></td><td>5</td></tr><tr><td></td><td></td><td></td><td>6</td></tr><tr><td></td><td></td><td></td><td>7</td></tr><tr><td></td><td></td><td></td><td>8</td></tr><tr><td></td><td></td><td></td><td>9</td></tr><tr><td></td><td></td><td></td><td>10</td></tr><tr><td></td><td></td><td></td><td>11</td></tr><tr><td></td><td></td><td></td><td>12</td></tr><tr><td></td><td></td><td></td><td>13</td></tr><tr><td></td><td></td><td></td><td>14</td></tr><tr><td></td><td></td><td></td><td>15</td></tr><tr><td></td><td></td><td></td><td>16</td></tr><tr><td></td><td></td><td></td><td>17</td></tr><tr><td></td><td></td><td></td><td>18</td></tr></table>	0	60	120	1	X			2		X		3			X	4				5				6				7				8				9				10				11				12				13				14				15				16				17				18	 	Red Black	K1I023NZ2 K1I023NZ4	0.170/0.374 0.170/0.374	
0	60	120	1																																																																										
X			2																																																																										
	X		3																																																																										
		X	4																																																																										
			5																																																																										
			6																																																																										
			7																																																																										
			8																																																																										
			9																																																																										
			10																																																																										
			11																																																																										
			12																																																																										
			13																																																																										
			14																																																																										
			15																																																																										
			16																																																																										
			17																																																																										
			18																																																																										

Cam switches

Complete switches, 12 A with key operated lock

Front mounting by 6 screws Ø 5.2 mm

with 55 x 100 mm front plate

Stepping switches (4 step), 4-pole, without “0” position

Wiring diagram and switching programme	Marking and switch position	Colour of handle	Reference	Weight kg/lb
--	-----------------------------	------------------	-----------	--------------

4 step (1)

Red

K1Q034NZ2

0.170/0.374

Black

K1Q034NZ4

0.170/0.374

4 step with intermediate steps at 30°

4 step with intermediate steps at 30°

Red

K1Q8621Z1

0.170/0.374







(1) Switching programme identical for 4 step and 4 step with intermediate steps at 30°.

Cam switches

Complete switches, 12 A with key operated lock
Front mounting by 6 screws Ø 5.2 mm
with 55 x 100 mm front plate



K1D012QZ2

Stepping switches (2 step), with “0” position					
Wiring diagram and switching programme	Marking and switch position	Colour of handle	Reference	Weight kg/lb	
2-pole					
		Red	K1D012QZ2	0.170/0.374	
		Black	K1D012QZ4	0.170/0.374	
3-pole					
		Red	K1F022QZ2	0.170/0.374	
		Black	K1F022QZ4	0.170/0.374	
4-pole					
		Red	K1H032QZ2	0.170/0.374	
		Black	K1H032QZ4	0.170/0.374	



Cam switches

Complete switches, 12 A with key operated lock
Front mounting by 6 screws Ø 5.2 mm
with 55 x 100 mm front plate

Stepping switches (3 step), 2-pole, with "0" position

Switching programme	Marking and switch position	Colour of handle	Reference	Weight kg/lb
---------------------	-----------------------------	------------------	-----------	--------------

3 step with intermediate steps at 30°






Red **K1M10317Z1** 0.170/0.374

Stepping switches (5 step), 2-pole, with "0" position

Wiring diagram and switching programme	Marking and switch position	Colour of handle	Reference	Weight kg/lb
--	-----------------------------	------------------	-----------	--------------




5 step (1)



Red **K1K015NZ2** 0.170/0.374

Black **K1K015NZ4** 0.170/0.374

5 step with intermediate steps at 30°




Red **K1K1060Z1** 0.170/0.374

(1) Switching programme identical for 5 step and 5 step with intermediate steps at 30°.

Cam switches

Complete switches, 12 A with key operated lock
Front mounting by 6 screws Ø 5.2 mm
with 55 x 100 mm front plate




K1D032RZ2

Start selector switches (3-position) with “0” position				
Switching programme	Marking and switch position	Colour of handle	Reference	Weight kg/lb
1-pole				
		Red	K1D032RZ2	0.170/0.374
		Black	K1D032RZ4	0.170/0.374
2-pole				
		Red	K1G043RZ2	0.170/0.374
		Black	K1G043RZ4	0.170/0.374
2-pole with intermediate positions at 30°				
		Red	K1I9289Z1	0.170/0.374

Cam switches

Complete switches, 12 A with key operated lock
Front mounting by 6 screws Ø 5.2 mm
with 55 x 100 mm front plate




K1B001UZ2

Start selector switches (4-position) with "0" position

Switching programme	Marking and switch position	Colour of handle	Reference	Weight kg/lb
---------------------	-----------------------------	------------------	-----------	--------------

0	30	60	90	120	150	180	210	240	1
		X			X			X	2
			X			X			3
				X			X		4
					X			X	5
						X			6
							X		7
								X	8
									9
									10
									11
									12
									13
									14
									15
									16
									17
									18
									19
									20
									21
									22
									23
									24
									25
									26
									27
									28
									29
									30
									31
									32




Red **K1Q10805Z1** 0.170/0.374

Changeover switches with "0" position

Wiring diagram and switching programme	Marking and switch position	Colour of handle	Reference	Weight kg/lb
--	-----------------------------	------------------	-----------	--------------

1-pole

300	0	60	1
X			2
			3
			4




Red **K1B001UZ2** 0.170/0.374

Black **K1B001UZ4** 0.170/0.374

2-pole



300	0	60	1
X			2
			3
			4
			5
			6
			7
			8



Red **K1D002UZ2** 0.170/0.374

Black **K1D002UZ4** 0.170/0.374

3-pole



Red **K1F003UZ2** 0.170/0.374

Black **K1F003UZ4** 0.170/0.374

300	0	60	1
X			2
			3
			4
			5
			6
			7
			8
			9
			10
			11
			12

Switches, 10 and 16 A, mounted in plastic enclosure

- Emergency stop switches..... 6/2
- OFF-ON switches..... 6/3

Cam switches

Switches mounted in plastic enclosure,
10 and 16 A



KA●●●●●G

"Emergency stop" switches in enclosure

Specifications

- PVC enclosure.
- 60 x 60 mm/2.36 x 2.36 in. operating head, red handle (without padlocking device) (1) on yellow background. Marking: O I.
- Legend holder with metallic finish blank legend.
- Protection degree (conforming to standard EN/IEC 60529): IP 65.

Composition (2)				Dimensions w x h x d (3)	Thermal current (Ithe) (4)	Reference	Weight
Poles	N	N/O	N/C				
				mm/in.	A		kg/lb
1	—	—	—	74 x 135 x 106/ 2.91 x 5.31 x 4.17	10	KA1A050G	0.365/0.805
					16	KA2A050G	0.365/0.805
3	—	—	—	74 x 135 x 106/ 2.91 x 5.31 x 4.17	10	KA1C051G	0.390/0.860
					16	KA2C051G	0.390/0.860
3	1	—	—	74 x 135 x 106/ 2.91 x 5.31 x 4.17	10	KA1D052G	0.400/0.882
					16	KA2D052G	0.400/0.882
3	—	1	—	74 x 135 x 106/ 2.91 x 5.31 x 4.17	10	KA1D053G	0.400/0.882
					16	KA2D053G	0.400/0.882
3	—	1	1	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10	KA1E054G	0.694/1.530
					16	KA2E054G	0.694/1.530
3	—	2	2	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10	KA1G055G	0.719/1.585
					16	KA2G055G	0.719/1.585
3	1	1	1	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10	KA1F056G	0.704/1.552
					16	KA2F056G	0.704/1.552
6	—	—	—	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10	KA1F057G	0.704/1.552
					16	KA2F057G	0.704/1.552
6	1	—	—	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10	KA1G058G	0.719/1.585
					16	KA2G058G	0.719/1.585
6	—	1	—	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10	KA1G059G	0.719/1.585
					16	KA2G059G	0.719/1.585
6	—	1	1	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10	KA1H060G	0.724/1.596
					16	KA2H060G	0.724/1.596
9	—	—	—	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10	KA1I061G	0.744/1.640
					16	KA2I061G	0.744/1.640
9	1	—	—	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10	KA1K062G	0.749/1.651
					16	KA2K062G	0.719/1.585
9	—	1 (5)	—	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10	KA1K063G	0.719/1.585
					16	KA2K063G	0.719/1.585

(1) To order a switch with a red padlockable handle (up to 3 padlocks), replace the letter A (2nd letter) in the references shown above by the letter C.
Example : KA1A050G becomes KC1A050G.

(2) Poles : main contacts

- N/O contact : late make (unballasting contact)
- N/C contact : signaling contact
- Neutral conductor (N) : early make, late break.

(3) Total depth, including operating head.

(4) Permissible power, AC-23 at 400 V :

- K1 switches : 2.2 kW,
- K2 switches : 5.5 kW.

(5) Contact not late make.

Cam switches

Switches mounted in plastic enclosure,
10 and 16 A

KD●●●●●G

OFF-ON switches in enclosure

Specifications

- PVC enclosure.
- 60 x 60 mm/2.36 x 2.36 in. operating head, black handle (without padlocking device) on metallic background. Marking: O I.
- Legend holder with metallic finish blank legend.
- Protection degree (conforming to standard EN/IEC 60529): IP 65.

Composition (1)				Dimensions w x h x d (2)	Thermal current (Ithe) (3)	Reference	Weight
Poles	N	N/O	N/C				
				mm/in.	A		kg/lb
1	—	—	—	74 x 135 x 106/ 2.91 x 5.31 x 4.17	10 16	KD1A050G KD2A050G	0.365/0.805 0.365/0.805
3	—	—	—	74 x 135 x 106/ 2.91 x 5.31 x 4.17	10 16	KD1C051G KD2C051G	0.390/0.860 0.390/0.860
3	1	—	—	74 x 135 x 106/ 2.91 x 5.31 x 4.17	10 16	KD1D052G KD2D052G	0.400/0.882 0.400/0.882
3	—	1	—	74 x 135 x 106/ 2.91 x 5.31 x 4.17	10 16	KD1D053G KD2D053G	0.400/0.882 0.400/0.882
3	—	1	1	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10 16	KD1E054G KD2E054G	0.694/1.530 0.694/1.530
3	—	2	2	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10 16	KD1G055G KD2G055G	0.719/1.585 0.719/1.585
3	1	1	1	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10 16	KD1F056G KD2F056G	0.704/1.552 0.704/1.552
6	—	—	—	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10 16	KD1F057G KD2F057G	0.704/1.552 0.704/1.552
6	1	—	—	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10 16	KD1G058G KD2G058G	0.719/1.585 0.719/1.585
6	—	1	—	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10 16	KD1G059G KD2G059G	0.719/1.585 0.719/1.585
6	—	1	1	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10 16	KD1H060G KD2H060G	0.724/1.596 0.724/1.596
9	—	—	—	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10 16	KD1I061G KD2I061G	0.744/1.640 0.744/1.640
9	1	—	—	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10 16	KD1K062G KD2K062G	0.749/1.651 0.749/1.651
9	—	1 (4)	—	105 x 170 x 146/ 4.13 x 6.69 x 5.74	10 16	KD1K063G KD2K063G	0.749/1.651 0.749/1.651

(1) Poles : main contacts

□ N/O contact : late make (unballasting contact)

□ N/C contact : signaling contact

□ Neutral conductor (N) : early make, late break.

(2) Total depth, including operating head.

(3) Permissible power, AC-23 at 400 V :

□ K1 switches : 2.2 kW.

□ K2 switches : 5.5 kW.

(4) Contact not late make.

Complete switches, 32 to 150 A

- General 7/2
- With 64 x 64 mm front plate (32 to 63 A ratings) and 88 x 88 mm front plate (115 and 150 A ratings)
 - Switches 7/3
 - Changeover switches 7/5
 - Star-delta and reversing star-delta switches 7/6
 - Pole change and reversing switches..... 7/7

Cam switches

Complete switches, 32 to 150 A


The range of K30 to K150 cam switches (32 to 150 A ratings) comprises only complete switches.

These products are more specifically designed for direct control of simple machines.

Complete switches

- switches
- stepping switches
- changeover switches
- voltmeter switches
- ammeter switches
- starting switches

Front mounting




By 4 holes
with 64 x 64 mm/2.52 x 2.52 in. front plate
32 to 63 A ratings
K30, K50 and K63

By 4 holes
with 88 x 88 mm/3.46 x 3.46 in. front plate
115 to 150 A ratings
K115 and K150

"Multi-fixing" mounting

Rear mounting



By 4 holes on 48 mm/1.89 in. centres
32 to 63 A ratings
K30, K50 and K63

By 4 holes on 68 mm/2.68 in. centres
115 to 150 A ratings
K115 and K150

Cam switches

Complete switches, 32 to 150 A

With 64 x 64 mm front plate (32 to 63 A ratings)

and 88 x 88 mm front plate (115 and 150 A ratings)



K30C003AP



K50C003AP

Switches with 60° switching angle

Front mounting

Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current (Ith)	Reference	Weight																		
			A		kg/lb																		
<table><tr><td></td><td>0</td><td>60</td></tr><tr><td>1-pole</td><td></td><td>X</td></tr><tr><td>2-pole</td><td></td><td>X</td></tr><tr><td>3-pole</td><td></td><td>X</td></tr><tr><td>4-pole</td><td></td><td>X</td></tr><tr><td>6-pole</td><td></td><td>X</td></tr></table>		0	60	1-pole		X	2-pole		X	3-pole		X	4-pole		X	6-pole		X		1	32	K30A001AP	0.130/0.287
		0	60																				
	1-pole		X																				
	2-pole		X																				
	3-pole		X																				
	4-pole		X																				
	6-pole		X																				
	50	K50A001AP	0.175/0.386																				
	2	32	K30B002AP	0.170/0.375																			
	50	K50B002AP	0.215/0.474																				
	3	32	K30C003AP	0.224/0.494																			
	50	K50C003AP	0.275/0.606																				
63	K63C003AP	0.345/0.761																					
115	K115C003AP	0.680/1.499																					
150	K150C003AP	0.790/1.742																					
4	32	K30D004AP	0.250/0.551																				
50	K50D004AP	0.305/0.672																					
63	K63D004AP	0.390/0.860																					
115	K115D004AP	0.745/1.642																					
150	K150D004AP	0.880/1.940																					
6	32	K30F006AP	0.425/0.937																				
50	K50F006AP	0.530/1.168																					
63	K63F006AP	0.590/1.301																					

Cam switches



Complete switches, 32 to 150 A
With 64 x 64 mm front plate (32 to 63 A ratings)
and 88 x 88 mm front plate (115 and 150 A ratings)



K63C003HP



K150D004HP

Switches with 90° switching angle					
Front mounting					
Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current (Ith)	Reference	Weight
			A		kg/lb
		3	32	K30C003HP	0.224/0.494
		50	K50C003HP	0.275/0.606	
		63	K63C003HP	0.345/0.761	
		115	K115C003HP	0.680/1.499	
		150	K150C003HP	0.790/1.742	
		4	32	K30D004HP	0.250/0.551
		50	K50D004HP	0.305/0.672	
		63	K63D004HP	0.390/0.860	
		115	K115D004HP	0.745/1.642	
		150	K150D004HP	0.880/1.940	
Rear mounting					
		3	32	K30C503HP	0.250/0.551
		50	K50C503HP	0.300/0.661	
		63	K63C503HP	0.370/0.816	
		115	K115C503HP	0.720/1.587	
		150	K150C503HP	0.830/1.830	
		4	32	K30D504HP	0.280/0.617
		50	K50D504HP	0.350/0.772	
		63	K63D504HP	0.440/0.970	
		115	K115D504HP	0.790/1.742	
		150	K150D504HP	0.930/2.050	


Cam switches

Complete switches, 32 to 150 A

With 64 x 64 mm front plate (32 to 63 A ratings)

and 88 x 88 mm front plate (115 and 150 A ratings)

103522



K50B001UP

Changeover switches with "0" position

Front mounting


Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current (Ith)	Reference	Weight
			A		kg/lb
		1	32	K30B001UP	0.170/0.375
			50	K50B001UP	0.215/0.474
			150	K150B001UP	0.790/1.742
		2	32	K30D002UP	0.250/0.551
			50	K50D002UP	0.305/0.672
			150	K150D002UP	0.790/1.742
		3	32	K30F003UP	0.425/0.937
			50	K50F003UP	0.530/1.168
			63	K63F003UP	0.590/1.301
			115	K115F003UP	0.645/1.422
			150	K150F003UP	0.760/1.675
		4	32	K30H004UP	0.485/1.069
			50	K50H004UP	0.610/1.345
			63	K63H004UP	0.680/1.499
			115	K115H004UP	0.750/1.653
			150	K150H004UP	0.880/1.940

Changeover switches without "0" position

Front mounting

		3	32	K30F013UP	0.425/0.937
			50	K50F013UP	0.530/1.168
			63	K63F013UP	0.590/1.301
			115	K115F013UP	0.645/1.422
			150	K150F013UP	0.760/1.675
		4	32	K30H014UP	0.485/1.069
			50	K50H014UP	0.610/1.345
			63	K63H014UP	0.680/1.499
			115	K115H014UP	0.750/1.653
			150	K150H014UP	0.880/1.940


501179



K63F013UP


Cam switches

Complete switches, 32 to 150 A
With 64 x 64 mm front plate (32 to 63 A ratings)
and 88 x 88 mm front plate (115 and 150 A ratings)



K50H001YP

Star-delta switches						
Front mounting						
Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current (Ith)	Reference	Weight	
			A		kg/lb	
		3	32	K30H001YP	0.485/1.069	
			50	K50H001YP	0.610/1.345	
			63	K63H001YP	0.680/1.499	
			115	K115H001YP	0.750/1.653	
			150	K150H001YP	0.880/1.940	



K115K006YP

Reversing star-delta switches						
Front mounting						
Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current (Ith)	Reference	Weight	
			A		kg/lb	
		3	32	K30K006YP	0.560/1.235	
			50	K50K006YP	0.690/1.521	
			63	K63K006YP	0.770/1.697	
			115	K115K006YP	0.880/1.940	
			150	K150K006YP	0.990/2.183	

Cam switches

Complete switches, 32 to 150 A

With 64 x 64 mm front plate (32 to 63 A ratings)
and 88 x 88 mm front plate (115 and 150 A ratings)

Accessories

501179



K63H004PP

Pole change switches for 2-speed motors (for motors with tapped "Dahlander" windings)

Front mounting

Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current (Ith)	Reference	Weight
			A		kg/lb
		3	32	K30H004PP	0.485/1.069
			50	K50H004PP	0.610/1.345
			63	K63H004PP	0.680/1.499

501178



K150D002WP

Reversing switches with "0" position

Front mounting

Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current (Ith)	Reference	Weight
			A		kg/lb
		2	32	K30D002WP	0.250/0.551
			50	K50D002WP	0.305/0.672
			63	K63D002WP	0.390/0.860
			115	K115D002WP	0.745/1.642
			150	K150D002WP	0.880/1.940
		3	32	K30E003WP	0.385/0.849
			50	K50E003WP	0.485/1.069
			63	K63E003WP	0.540/1.190
			115	K115E003WP	0.590/1.301
			150	K150E003WP	0.710/1.565

Accessories

Description	For use with	Sold in lots of	Unit reference	Weight
Legend holders With blank legend	Square heads 64 x 64 mm/ 2.52 x 2.52 in.	5	KZN15	0.020/0.044
	Square heads 88 x 88 mm/ 3.46 x 3.46 in.	5	KZN103	0.040/0.088
Replacement blank legends for legend holder	KZN15	5	KZ77N	0.025/0.055
	KZN103	5	KZ100N	0.040/0.088
Blank legends for metallic finish front plate	64 x 64	5	KZN21	0.035/0.077
	88 x 88	5	KZN24	0.045/0.099

Index

■ Product reference index..... 8/2

K					
K1A001ACH	3/6	K1C003NZ2	5/2	K1D009BX	4/10
K1A001ALH	3/6	K1C003NZ4	5/2	K1D010B	4/10
K1A001B	4/9	K1C003QCH	3/9	K1D010BL	4/10
K1A001BL	4/9	K1C003QLH	3/9	K1D011B	4/10
K1A001BX	4/9	K1C004B	4/9	K1D011BL	4/10
K1A001TCH	3/7	K1C004BL	4/9	K1D012NCH	3/12
K1A001TLH	3/7	K1C004BX	4/9	K1D012NLH	3/12
K1A002TCH	3/7	K1C005B	4/9	K1D012QCH	3/11
K1A002TLH	3/7	K1C005BL	4/9	K1D012QLH	3/11
K1A501B	4/9	K1C005BX	4/9	K1D012QZ2	5/4
K1B001UCH	3/15	K1C006B	4/9	K1D012QZ4	5/4
K1B001ULH	3/15	K1C006BL	4/9	K1D012UCH	3/15
K1B001UZ2	5/7	K1C006BX	4/9	K1D012ULH	3/15
K1B001UZ4	5/7	K1C007B	4/9	K1D023M	4/25
K1B002ACH	3/6	K1C007BL	4/9	K1D023MCH	3/18
K1B002ALH	3/6	K1C007BX	4/9	K1D023ML	4/25
K1B002B	4/9	K1C024B	4/10	K1D023MLH	3/18
K1B002BL	4/9	K1C024BL	4/10	K1D023MX	4/25
K1B002BX	4/9	K1C024BX	4/10	K1D024M	4/25
K1B002NCH	3/10	K1C025B	4/10	K1D024MCH	3/19
K1B002NLH	3/10	K1C025BL	4/10	K1D024ML	4/25
K1B002QCH	3/9	K1C025BX	4/10	K1D024MLH	3/19
K1B002QLH	3/9	K1C026B	4/10	K1D024MX	4/25
K1B003B	4/9	K1C026BL	4/10	K1D028B	4/11
K1B003BL	4/9	K1C026BX	4/10	K1D028BL	4/11
K1B003BX	4/9	K1C027B	4/11	K1D028BX	4/11
K1B003TCH	3/8	K1C027BL	4/11	K1D029B	4/11
K1B003TLH	3/8	K1C027BX	4/11	K1D029BL	4/11
K1B004TCH	3/8	K1C504B	4/9	K1D029BX	4/11
K1B004TLH	3/8	K1C505B	4/9	K1D030B	4/11
K1B006TCH	3/15	K1C506B	4/9	K1D030BL	4/11
K1B006TLH	3/15	K1C507B	4/9	K1D030BX	4/11
K1B011UCH	3/15	K1C524B	4/10	K1D031B	4/11
K1B011ULH	3/15	K1C525B	4/10	K1D031BL	4/11
K1B022B	4/10	K1C526B	4/10	K1D032B	4/11
K1B022BL	4/10	K1C527B	4/11	K1D032BL	4/11
K1B022BX	4/10	K1D002UCH	3/15	K1D032RZ2	5/6
K1B023B	4/10	K1D002ULH	3/15	K1D032RZ4	5/6
K1B023BL	4/10	K1D002UZ2	5/7	K1D033M	4/25
K1B023BX	4/10	K1D002UZ4	5/7	K1D033MCH	3/18
K1B502B	4/9	K1D004ACH	3/6	K1D033ML	4/25
K1B503B	4/9	K1D004ALH	3/6	K1D033MLH	3/18
K1B522B	4/10	K1D004HCH	3/6	K1D034M	4/25
K1B523B	4/10	K1D004HLH	3/6	K1D034MCH	3/19
K1B1002HCH	3/6	K1D004NLH	3/10	K1D034ML	4/25
K1B1002HLH	3/6	K1D004QCH	3/9	K1D034MLH	3/19
K1C003ACH	3/6	K1D004QLH	3/9	K1D508B	4/9
K1C003ALH	3/6	K1D008B	4/9	K1D509B	4/10
K1C003HCH	3/6	K1D008BL	4/9	K1D510B	4/10
K1C003HLH	3/6	K1D008BX	4/9	K1D511B	4/10
K1C003NCH	3/10	K1D009B	4/10	K1D523M	4/25
K1C003NLH	3/10	K1D009BL	4/10	K1D524M	4/25
				K1D528B	4/11
				K1D529B	4/11
				K1D530B	4/11
				K1D531B	4/11
				K1D532B	4/11
				K1D533M	4/25
				K1D534M	4/25
				K1E005ACH	3/6
				K1E005ALH	3/6
				K1E005NCH	3/10
				K1E005NLH	3/10
				K1E005QCH	3/9
				K1E005QLH	3/9
				K1E025M	4/25
				K1E025MCH	3/19
				K1E025ML	4/25
				K1E025MLH	3/19
				K1E025MX	4/25
				K1E035M	4/25
				K1E035MCH	3/19
				K1E035ML	4/25
				K1E035MLH	3/19
				K1E525M	4/25
				K1E535M	4/25
				K1F003M	4/24
				K1F003MCH	3/16
				K1F003ML	4/24
				K1F003MLH	3/16
				K1F003MX	4/24
				K1F003UCH	3/15
				K1F003ULH	3/15
				K1F003UZ2	5/7
				K1F003UZ4	5/7
				K1F006ACH	3/6
				K1F006ALH	3/6
				K1F013M	4/24
				K1F013MCH	3/16
				K1F013ML	4/24
				K1F013MLH	3/16
				K1F013MX	4/24
				K1F013NCH	3/12
				K1F013NLH	3/12
				K1F013NZ2	5/2
				K1F013NZ4	5/2
				K1F013QCH	3/11
				K1F013QLH	3/11
				K1F013UCH	3/15
				K1F013ULH	3/15
				K1F022NCH	3/14
				K1F022NLH	3/14
				K1F022QCH	3/13
				K1F022QLH	3/13
				K1F022QZ2	5/4
				K1F022QZ4	5/4
				K1F027M	4/26
				K1F027MCH	3/19
				K1F027ML	4/26
				K1F027MLH	3/19
				K1F027MX	4/26
				K1F037M	4/26
				K1F037MCH	3/19
				K1F037ML	4/26
				K1F037MLH	3/19
				K1F503M	4/24
				K1F513M	4/24
				K1F527M	4/26
				K1F537M	4/26
				K1G043RZ2	5/6
				K1G043RZ4	5/6
				K1H004M	4/24
				K1H004MCH	3/17
				K1H004ML	4/24
				K1H004MLH	3/17
				K1H004MX	4/24
				K1H004UCH	3/15
				K1H004ULH	3/15
				K1H014M	4/24
				K1H014MCH	3/17
				K1H014ML	4/24
				K1H014MLH	3/17
				K1H014MX	4/24
				K1H014NCH	3/12
				K1H014NLH	3/12
				K1H014QCH	3/11
				K1H014QLH	3/11
				K1H014UCH	3/15
				K1H014ULH	3/15
				K1H026M	4/26
				K1H026MCH	3/18
				K1H026ML	4/26
				K1H026MLH	3/18
				K1H032QZ2	5/4
				K1H032QZ4	5/4
				K1H036M	4/26
				K1H036MCH	3/18
				K1H036ML	4/26
				K1H036MLH	3/18
				K1H504M	4/24
				K1H514M	4/24
				K1H526M	4/26
				K1H536M	4/26
				K1I023NCH	3/14
				K1I023NLH	3/14
				K1I023QCH	3/13
				K1I023QLH	3/13
				K1I9289Z1	5/6
				K1K015NCH	3/12

K1K015NLH	3/12	K2D004QCH	3/9	K2K015NCH	3/12	K50A001AP	7/3	K150C503HP	7/4
K1K015NZ2	5/5	K2D004QLH	3/9	K2K015NLH	3/12	K50B001UP	7/5	K150D002WP	7/7
K1K015NZ4	5/5	K2D012NCH	3/12	K2K015QCH	3/11	K50B002AP	7/3	K150D004AP	7/3
K1K015QCH	3/11	K2D012NLH	3/12	K2K015QLH	3/11	K50C003AP	7/3	K150D004HP	7/4
K1K015QLH	3/11	K2D012QCH	3/11	K2K504Y	4/30	K50C003HP	7/4	K150D504HP	7/4
K1K1060Z1	5/5	K2D012QLH	3/11	K2K506Y	4/30	K50C503HP	7/4	K150E003WP	7/7
K1I023NZ2	5/2	K2D012UCH	3/15	K2M007Y	4/31	K50D002UP	7/5	K150F003UP	7/5
K1I023NZ4	5/2	K2D012ULH	3/15	K2M007YL	4/31	K50D002WP	7/7	K150F013UP	7/5
K1M10317Z1	5/5	K2E005ACH	3/6	K2M507Y	4/31	K50D004AP	7/3	K150H001YP	7/6
K1Q034NZ2	5/3	K2E005ALH	3/6	K10A001ACH	2/3	K50D004HP	7/4	K150H004UP	7/5
K1Q034NZ4	5/3	K2E005NCH	3/10	K10B001UCH	2/6	K50D504HP	7/4	K150H014UP	7/5
K1Q8621Z1	5/3	K2E005NLH	3/10	K10B002ACH	2/3	K50E003WP	7/7	K150K006YP	7/6
K1Q10805Z1	5/7	K2E005QCH	3/9	K10B002QCH	2/3	K50F003UP	7/5	KA1A050G	6/2
K2A001ACH	3/6	K2E005QLH	3/9	K10B006TCH	2/5	K50F006AP	7/3	KA1C051G	6/2
K2A001ALH	3/6	K2F003UCH	3/15	K10B011UCH	2/6	K50F013UP	7/5	KA1D052G	6/2
K2A001TCH	3/7	K2F003ULH	3/15	K10C003ACH	2/3	K50H001YP	7/6	KA1D053G	6/2
K2A001TLH	3/7	K2F006ACH	3/6	K10C003NCH	2/4	K50H004PP	7/7	KA1E054G	6/2
K2A002TCH	3/7	K2F006ALH	3/6	K10C003QCH	2/3	K50H004UP	7/5	KA1F056G	6/2
K2A002TLH	3/7	K2F013NCH	3/12	K10D002UCH	2/6	K50H014UP	7/5	KA1F057G	6/2
K2B001UCH	3/15	K2F013NLH	3/12	K10D004ACH	2/3	K50K006YP	7/6	KA1G055G	6/2
K2B001ULH	3/15	K2F013QCH	3/11	K10D004NCH	2/4	K63C003AP	7/3	KA1G058G	6/2
K2B002ACH	3/6	K2F013QLH	3/11	K10D004QCH	2/3	K63C003HP	7/4	KA1G059G	6/2
K2B002ALH	3/6	K2F013UCH	3/15	K10D012QCH	2/4	K63C503HP	7/4	KA1H060G	6/2
K2B002NCH	3/10	K2F013ULH	3/15	K10D012UCH	2/6	K63D002WP	7/7	KA1I061G	6/2
K2B002NLH	3/10	K2F022NCH	3/14	K10D024MCH	2/7	K63D004AP	7/3	KA1K062G	6/2
K2B002QCH	3/9	K2F022NLH	3/14	K10F003MCH	2/7	K63D004HP	7/4	KA1K063G	6/2
K2B002QLH	3/9	K2F022QCH	3/13	K10F003UCH	2/6	K63D504HP	7/4	KA2A050G	6/2
K2B003TCH	3/8	K2F022QLH	3/13	K10F013NCH	2/5	K63E003WP	7/7	KA2C051G	6/2
K2B003TLH	3/8	K2G003Y	4/30	K10F013QCH	2/4	K63F003UP	7/5	KA2D052G	6/2
K2B004TCH	3/8	K2G003YL	4/30	K10F013UCH	2/6	K63F006AP	7/3	KA2D053G	6/2
K2B004TLH	3/8	K2G003YX	4/30	K10F027MCH	2/7	K63F013UP	7/5	KA2E054G	6/2
K2B006TCH	3/15	K2G503Y	4/30	K10H004UCH	2/6	K63H001YP	7/6	KA2F056G	6/2
K2B006TLH	3/15	K2H001Y	4/30	K10H014UCH	2/6	K63H004PP	7/7	KA2F057G	6/2
K2B011UCH	3/15	K2H001YL	4/30	K30A001AP	7/3	K63H004UP	7/5	KA2G055G	6/2
K2B011ULH	3/15	K2H001YX	4/30	K30B001UP	7/5	K63H014UP	7/5	KA2G058G	6/2
K2B1002HCH	3/6	K2H004UCH	3/15	K30B002AP	7/3	K63K006YP	7/6	KA2G059G	6/2
K2B1002HLH	3/6	K2H004ULH	3/15	K30C003AP	7/3	K115C003AP	7/3	KA2H060G	6/2
K2C003ACH	3/6	K2H014NCH	3/12	K30C003HP	7/4	K115C003HP	7/4	KA2I061G	6/2
K2C003ALH	3/6	K2H014NLH	3/12	K30C503HP	7/4	K115C503HP	7/4	KA2K062G	6/2
K2C003HCH	3/6	K2H014QCH	3/11	K30D002UP	7/5	K115D002WP	7/7	KA2K063G	6/2
K2C003HLH	3/6	K2H014QLH	3/11	K30D002WP	7/7	K115D004AP	7/3	KAA1H	4/35
K2C003NCH	3/10	K2H014UCH	3/15	K30D004AP	7/3	K115D004HP	7/4	KAA1S	4/35
K2C003NLH	3/10	K2H014ULH	3/15	K30D004HP	7/4	K115D504HP	7/4	KAA1Z	4/35
K2C003QCH	3/9	K2H501Y	4/30	K30D504HP	7/4	K115E003WP	7/7	KAA2H	4/35
K2C003QLH	3/9	K2I023NCH	3/14	K30E003WP	7/7	K115F003UP	7/5	KAC1H	4/34
K2D002UCH	3/15	K2I023NLH	3/14	K30F003UP	7/5	K115F013UP	7/5	KAC1H41	4/34
K2D002ULH	3/15	K2I023QCH	3/13	K30F006AP	7/3	K115H001YP	7/6	KAC1H48	4/34
K2D004ACH	3/6	K2I023QLH	3/13	K30F013UP	7/5	K115H004UP	7/5	KAC1H61	4/34
K2D004ALH	3/6	K2K004Y	4/30	K30H001YP	7/6	K115H014UP	7/5	KAC1S	4/34
K2D004HCH	3/6	K2K004YL	4/30	K30H004PP	7/7	K115K006YP	7/6	KAC1Z	4/34
K2D004HLH	3/6	K2K004YX	4/30	K30H004UP	7/5	K150B001UP	7/5	KAD1H	4/34
K2D004NCH	3/10	K2K006Y	4/30	K30H014UP	7/5	K150C003AP	7/3	KAD1S	4/35
K2D004NLH	3/10	K2K006YL	4/30	K30K006YP	7/6	K150C003HP	7/4	KAD1Z	4/35

KAE1H	4/35	KD2F056G	6/3	K●B002GL	4/12	K●C003QX	4/14	K●D012U	4/7
KAF1H	4/35	KD2F057G	6/3	K●B002GX	4/12	K●C007T	4/8	K●D012UL	4/7
KAG3H	4/34	KD2G055G	6/3	K●B002N	4/16	K●C007TL	4/8	K●D012UX	4/7
KAXZ1C12	4/35	KD2G058G	6/3	K●B002NL	4/16	K●C023H	4/3	K●D022W	4/29
KAXZ1C14	4/35	KD2G059G	6/3	K●B002NX	4/16	K●C023HL	4/3	K●D022WL	4/29
KAXZ1M12	4/35	KD2H060G	6/3	K●B002Q	4/14	K●C023HX	4/3	K●D022WX	4/29
KAXZ1M14	4/35	KD2I061G	6/3	K●B002QL	4/14	K●C502D	4/8	K●D024H	4/3
KAXZ1S13●	4/35	KD2K062G	6/3	K●B002QX	4/14	K●C502L	4/27	K●D024HL	4/3
KAXZ1S14●	4/35	KD2K063G	6/3	K●B003T	4/4	K●C503A	4/2	K●D024HX	4/3
KAXZ1S16●	4/35	KDC1H	4/34	K●B003TL	4/4	K●C503G	4/12	K●D502S	4/28
KAXZ1S19●	4/35	KDC1LH	4/34	K●B004T	4/5	K●C503H	4/3	K●D502U	4/6
KBA1H	4/35	KDC1S	4/34	K●B004TL	4/5	K●C503N	4/16	K●D502W	4/29
KBA1S	4/35	KDC1Z	4/34	K●B006T	4/8	K●C503Q	4/14	K●D503L	4/27
KBA1Z	4/35	KDD1H	4/34	K●B006TL	4/8	K●C507T	4/8	K●D504A	4/2
KBC1H	4/34	KDD1S	4/35	K●B006TX	4/8	K●C523H	4/3	K●D504G	4/12
KBC1H41	4/34	KDD1Z	4/35	K●B011U	4/7	K●D002S	4/28	K●D504H	4/3
KBC1H48	4/34	KDE1H	4/35	K●B011UL	4/7	K●D002SL	4/28	K●D504N	4/16
KBC1H61	4/34	KDE1LH	4/35	K●B011UX	4/7	K●D002SX	4/28	K●D504Q	4/14
KBC1S	4/34	KDF1H	4/35	K●B501D	4/5	K●D002U	4/6	K●D505T	4/5
KBC1Z	4/34	KDG3H	4/34	K●B501S	4/28	K●D002UL	4/6	K●D512G	4/12
KBD1H	4/34	KDG3Y	4/34	K●B501U	4/6	K●D002UX	4/6	K●D512N	4/19
KBD1S	4/35	K●A001A	4/2	K●B501U	4/8	K●D002W	4/29	K●D512Q	4/18
KBD1Z	4/35	K●A001A	4/4	K●B502A	4/2	K●D002WL	4/29	K●D512U	4/7
KBE1H	4/35	K●A001AL	4/2	K●B502G	4/12	K●D002WX	4/29	K●D522W	4/29
KBF1H	4/35	K●A001AL	4/4	K●B502N	4/16	K●D003L	4/27	K●D524H	4/3
KBG3H	4/34	K●A001AX	4/2	K●B502Q	4/14	K●D003LL	4/27	K●E003W	4/29
KCC1LH	4/34	K●A001AX	4/4	K●B503T	4/4	K●D003LX	4/27	K●E003WL	4/29
KCC1Y	4/34	K●A001T	4/4	K●B504T	4/5	K●D004A	4/2	K●E003WX	4/29
KCD1MH	4/34	K●A001TL	4/4	K●B506T	4/8	K●D004AL	4/2	K●E005A	4/2
KCE1LH	4/35	K●A001TX	4/4	K●B511U	4/7	K●D004AX	4/2	K●E005AL	4/2
KCE1Y	4/35	K●A002T	4/4	K●B1002H	4/3	K●D004G	4/12	K●E005AX	4/2
KCF1MH	4/35	K●A002TL	4/4	K●B1002HL	4/3	K●D004GL	4/12	K●E005H	4/3
KCG3H	4/34	K●A002TX	4/4	K●B1002HX	4/3	K●D004GX	4/12	K●E005HL	4/3
KCG3Y	4/34	K●A501A	4/2	K●C002D	4/8	K●D004H	4/3	K●E005HX	4/3
KD1A050G	6/3	K●A501A	4/4	K●C002DL	4/8	K●D004HL	4/3	K●E005N	4/16
KD1C051G	6/3	K●A501T	4/4	K●C002DX	4/8	K●D004HX	4/3	K●E005NL	4/16
KD1D052G	6/3	K●A502T	4/4	K●C002L	4/27	K●D004N	4/16	K●E005NX	4/16
KD1D053G	6/3	K●B001D	4/5	K●C002LL	4/27	K●D004NL	4/16	K●E005Q	4/14
KD1E054G	6/3	K●B001DL	4/5	K●C002LX	4/27	K●D004NX(2)	4/16	K●E005QL	4/14
KD1F056G	6/3	K●B001DX	4/5	K●C003A	4/2	K●D004Q	4/14	K●E005QX	4/14
KD1F057G	6/3	K●B001S	4/28	K●C003AL	4/2	K●D004QL	4/14	K●E023W	4/29
KD1G055G	6/3	K●B001SL	4/28	K●C003AX	4/2	K●D004QX	4/14	K●E023WL	4/29
KD1G058G	6/3	K●B001SX	4/28	K●C003G	4/12	K●D005T	4/5	K●E023WX	4/29
KD1G059G	6/3	K●B001U	4/6	K●C003GL	4/12	K●D005TL	4/5	K●E025H	4/3
KD1H060G	6/3	K●B001U	4/8	K●C003GX	4/12	K●D012G	4/12	K●E025HL	4/3
KD1I061G	6/3	K●B001UL	4/6	K●C003H	4/3	K●D012GL	4/12	K●E503W	4/29
KD1K062G	6/3	K●B001UL	4/8	K●C003HL	4/3	K●D012GX	4/12	K●E505A	4/2
KD1K063G	6/3	K●B001UX	4/6	K●C003HX	4/3	K●D012N	4/19	K●E505H	4/3
KD2A050G	6/3	K●B001UX	4/8	K●C003N	4/16	K●D012NL	4/19	K●E505N	4/16
KD2C051G	6/3	K●B002A	4/2	K●C003NL	4/16	K●D012NX	4/19	K●E505Q	4/14
KD2D052G	6/3	K●B002AL	4/2	K●C003NX	4/16	K●D012Q	4/18	K●E523W	4/29
KD2D053G	6/3	K●B002AX	4/2	K●C003Q	4/14	K●D012QL	4/18	K●E525H	4/3
KD2E054G	6/3	K●B002G	4/12	K●C003QL	4/14	K●D012QX	4/18	K●F001P	4/31

K●F001PL	4/31	K●F506A	4/2	K●H014QL	4/18	K●K008P	4/32	K●M023L	4/27
K●F001PX	4/31	K●F506H	4/3	K●H014QX	4/18	K●K008PL	4/32	K●M023LL	4/27
K●F002P	4/31	K●F506N	4/16	K●H014U	4/7	K●K010N	4/17	K●M024G	4/13
K●F002PL	4/31	K●F506Q	4/14	K●H014UL	4/7	K●K010NL	4/17	K●M024GL	4/13
K●F002PX	4/31	K●F512L	4/27	K●H014UX	4/7	K●K010NX	4/17	K●M024GX	4/13
K●F003S	4/28	K●F513G	4/12	K●H032N	4/23	K●K010Q	4/15	K●M024N	4/21
K●F003SL	4/28	K●F513N	4/19	K●H032NL	4/23	K●K010QL	4/15	K●M024NL	4/21
K●F003SX	4/28	K●F513Q	4/18	K●H032NX	4/23	K●K010QX	4/15	K●M024NX	4/21
K●F003U	4/6	K●F513U	4/7	K●H032Q	4/22	K●K015N	4/19	K●M024Q	4/20
K●F003UL	4/6	K●F522G	4/13	K●H032QL	4/22	K●K015NL	4/19	K●M024QL	4/20
K●F003UX	4/6	K●F522N	4/21	K●H032QX	4/22	K●K015NX	4/19	K●M024QX	4/20
K●F006A	4/2	K●F522Q	4/20	K●H504P	4/31	K●K015Q	4/18	K●M033N	4/23
K●F006AL	4/2	K●F526H	4/3	K●H504S	4/28	K●K015QL	4/18	K●M033NL	4/23
K●F006AX	4/2	K●G007A	4/2	K●H504U	4/6	K●K015QX	4/18	K●M033Q	4/22
K●F006H	4/3	K●G007AL	4/2	K●H505P	4/32	K●K015U	4/7	K●M033QL	4/22
K●F006HL	4/3	K●G007N	4/16	K●H508A	4/2	K●K015UL	4/7	K●M509P	4/32
K●F006HX	4/3	K●G007NL	4/16	K●H508N	4/16	K●K015UX	4/7	K●M516N	4/19
K●F006N	4/16	K●G007NX	4/16	K●H508Q	4/15	K●K505S	4/28	K●M516Q	4/18
K●F006NL	4/16	K●G007Q	4/14	K●H513L	4/27	K●K505U	4/6	K●M521N	4/17
K●F006NX	4/16	K●G007QL	4/14	K●H514G	4/13	K●K508P	4/32	K●M523L	4/27
K●F006Q	4/14	K●G007QX	4/14	K●H514N	4/19	K●K510N	4/17	K●M524G	4/13
K●F006QL	4/14	K●G507A	4/2	K●H514Q	4/18	K●K510Q	4/15	K●M524N	4/21
K●F006QX	4/14	K●G507N	4/16	K●H514U	4/7	K●K515N	4/19	K●M524Q	4/20
K●F012L	4/27	K●G507Q	4/14	K●H532N	4/23	K●K515Q	4/18	K●M533N	4/23
K●F012LL	4/27	K●H004P	4/31	K●H532Q	4/22	K●K515U	4/7	K●M533Q	4/22
K●F012LX	4/27	K●H004PL	4/31	K●I009N	4/17	K●L010P	4/33	K●P025N	4/21
K●F013G	4/12	K●H004PX	4/31	K●I009NL	4/17	K●L010PL	4/33	K●P025NL	4/21
K●F013GL	4/12	K●H004S	4/28	K●I009NX	4/17	K●L011N	4/17	K●P025NX	4/21
K●F013GX	4/12	K●H004SL	4/28	K●I009Q	4/15	K●L011NL	4/17	K●P025Q	4/20
K●F013N	4/19	K●H004U	4/6	K●I009QL	4/15	K●L011NX	4/17	K●P025QL	4/20
K●F013NL	4/19	K●H004UL	4/6	K●I009QX	4/15	K●L011P	4/33	K●P025QX	4/20
K●F013NX	4/19	K●H004UX	4/6	K●I022L	4/27	K●L011PL	4/33	K●P525N	4/21
K●F013Q	4/18	K●H005P	4/32	K●I022LL	4/27	K●L011Q	4/15	K●P525Q	4/20
K●F013QL	4/18	K●H005PL	4/32	K●I023G	4/13	K●L011QL	4/15	K●Q034N	4/23
K●F013QX	4/18	K●H005PX	4/32	K●I023GL	4/13	K●L011QX	4/15	K●Q034NL	4/23
K●F013U	4/7	K●H008A	4/2	K●I023GX	4/13	K●L012P	4/33	K●Q034Q	4/22
K●F013UL	4/7	K●H008AL	4/2	K●I023N	4/21	K●L012PL	4/33	K●Q034QL	4/22
K●F013UX	4/7	K●H008N	4/16	K●I023NL	4/21	K●L510P	4/33	K●Q534N	4/23
K●F022G	4/13	K●H008NL	4/16	K●I023NX	4/21	K●L511N	4/17	K●Q534Q	4/22
K●F022GL	4/13	K●H008NX	4/16	K●I023Q	4/20	K●L511P	4/33	K●S026N	4/21
K●F022GX	4/13	K●H008Q	4/15	K●I023QL	4/20	K●L511Q	4/15	K●S026NL	4/21
K●F022N	4/21	K●H008QL	4/15	K●I023QX	4/20	K●L512P	4/33	K●S026NX	4/21
K●F022NL	4/21	K●H008QX	4/15	K●I509N	4/17	K●M009P	4/32	K●S026Q	4/20
K●F022NX	4/21	K●H013L	4/27	K●I509Q	4/15	K●M009PL	4/32	K●S026QL	4/20
K●F022Q	4/20	K●H013LL	4/27	K●I522L	4/27	K●M016N	4/19	K●S026QX	4/20
K●F022QL	4/20	K●H013LX	4/27	K●I523G	4/13	K●M016NL	4/19	K●S526N	4/21
K●F022QX	4/20	K●H014G	4/13	K●I523N	4/21	K●M016NX	4/19	K●S526Q	4/20
K●F026H	4/3	K●H014GL	4/13	K●I523Q	4/20	K●M016Q	4/18	K●U035N	4/23
K●F026HL	4/3	K●H014GX	4/13	K●K005S	4/28	K●M016QL	4/18	K●U035NL	4/23
K●F501P	4/31	K●H014N	4/19	K●K005SL	4/28	K●M016QX	4/18	K●U035Q	4/22
K●F502P	4/31	K●H014NL	4/19	K●K005U	4/6	K●M021N	4/17	K●U035QL	4/22
K●F503S	4/28	K●H014NX	4/19	K●K005UL	4/6	K●M021NL	4/17	K●U535N	4/23
K●F503U	4/6	K●H014Q	4/18	K●K005UX	4/6	K●M021NX	4/17	K●U535Q	4/22

KZ1	4/39	KZ18042	4/37	KZ18630L	4/36	XBCY7224	4/38
KZ01R	4/39	KZ18042L	4/36	KZ18631	4/37	XBCY7225	4/38
KZ2	4/39	KZ18043	4/37	KZ18631L	4/36	XBCY7226	4/38
KZ13	4/39	KZ18043L	4/36	KZ18632	4/37	XBCY7227	4/38
KZ14	4/39	KZ18044	4/37	KZ18632L	4/36	XBCY7228	4/38
KZ15	4/39	KZ18044L	4/36	KZ18634	4/37	XBCY7229	4/38
KZ16	4/39	KZ18045	4/37	KZ18634L	4/36	XBCY7230	4/38
KZ17	4/37	KZ18045L	4/36	KZ18635	4/37	XBCY7231	4/38
KZ17L	4/36	KZ18046	4/37	KZ18635L	4/36	XBCY7232	4/38
KZ17X	4/38	KZ18046L	4/36	KZ18637	4/37	XBCY7233	4/38
KZ18	4/37	KZ18047	4/37	KZ18637L	4/36	XBCY7234	4/38
KZ18L	4/36	KZ18047L	4/36	KZ18913	4/37	XBCY7235	4/38
KZ19	4/37	KZ18048	4/37	KZ18913L	4/36	XBCY7236	4/38
KZ19L	4/36	KZ18048L	4/36	KZ18931F	4/37	XBCY7238	4/38
KZ19X	4/38	KZ18061	4/37	KZ18931FL	4/36	XBCY7239	4/38
KZ20	4/37	KZ18061L	4/36	KZ19041	4/37	XBCY7240	4/38
KZ21	4/37	KZ18068	4/37	KZ19041L	4/36	XBCY7241	4/38
KZ22	4/37	KZ18068L	4/36	KZ19093	4/37	XBCY7242	4/38
KZ27	4/40	KZ18091	4/37	KZ19093L	4/36	XBCY7243	4/38
KZ27H	4/40	KZ18091L	4/36	KZ19098F	4/37	XBCY7251	4/38
KZ28	4/40	KZ18093	4/37	KZ19098FL	4/36	XBCY7268	4/38
KZ28H	4/40	KZ18093L	4/36	KZ19910	4/37		
KZ30	4/41	KZ18312	4/37	KZ19910L	4/36	Z	
KZ31	4/41	KZ18312L	4/36	KZ21041	4/37	Z01	4/41
KZ32	4/40	KZ18412	4/37	KZ21048	4/37	Z18	4/41
KZ35	4/41	KZ18412L	4/36	KZ21093	4/37	Z18R	4/41
KZ36	4/41	KZ18413	4/37	KZ21412	4/37	Z18R1	4/41
KZ37	4/41	KZ18413L	4/36	KZ21451	4/37	Z18R15	4/41
KZ38	4/41	KZ18415	4/37	KZ21635	4/37		
KZ39	4/41	KZ18415L	4/36	KZ21637	4/37		
KZ41H	4/40	KZ18416	4/37	KZ21910	4/37		
KZ42H	4/40	KZ18416L	4/36	KZN15	7/7		
KZ50	4/41	KZ18417	4/37	KZN21	7/7		
KZ52	4/41	KZ18417L	4/36	KZN24	7/7		
KZ65	4/41	KZ18418	4/37	KZN103	7/7		
KZ66	4/41	KZ18418L	4/36				
KZ73	4/41	KZ18419	4/37	X			
KZ76	4/39	KZ18419L	4/36	XBCY2211	4/38		
KZ77	4/39	KZ18420	4/37	XBCY2213	4/38		
KZ77N	7/7	KZ18420L	4/36	XBCY2214	4/38		
KZ83	4/40	KZ18421	4/37	XBCY2215	4/38		
KZ91H	4/41	KZ18421L	4/36	XBCY2216	4/38		
KZ93	4/41	KZ18422F	4/37	XBCY2218	4/38		
KZ95	4/41	KZ18422FL	4/36	XBCY2219	4/38		
KZ100N	7/7	KZ18423F	4/37	XBCY2250	4/38		
KZ127	4/40	KZ18423FL	4/36	XBCY7064	4/38		
KZ140	4/40	KZ18434	4/37	XBCY7168	4/38		
KZ141	4/40	KZ18434L	4/36	XBCY7212	4/38		
KZ18032	4/37	KZ18436F	4/37	XBCY7217	4/38		
KZ18032L	4/36	KZ18436FL	4/36	XBCY7220	4/38		
KZ18033L	4/36	KZ18451	4/37	XBCY7221	4/38		
KZ18041	4/37	KZ18451L	4/36	XBCY7222	4/38		
KZ18041L	4/36	KZ18630	4/37	XBCY7223	4/38		

Harmony Innovation



Schneider Electric Industries SAS

Head Office
35, rue Joseph Monier
F-92500 Reuil-Malmaison
France

www.schneider-electric.com/control

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Design: Schneider Electric
Photos: Schneider Electric

DIA5ED2130604EN