

MLFB-Ordering data

6SL3210-5BE23-0UV0



Figure similar

Client order no. :

Order no. :

Offer no. :

Remarks :

Item no. :

Consignment no. :

Project :

Rated data	General tech. specifications																														
Input <table> <tr> <td>Number of phases</td><td>3 AC</td></tr> <tr> <td>Line voltage</td><td>380 ... 480 V -15 % +10 %</td></tr> <tr> <td>Line frequency</td><td>47 ... 63 Hz</td></tr> </table>	Number of phases	3 AC	Line voltage	380 ... 480 V -15 % +10 %	Line frequency	47 ... 63 Hz	<table> <tr> <td>Power factor λ</td><td>0.72</td></tr> <tr> <td>Offset factor $\cos \varphi$</td><td>0.95</td></tr> <tr> <td>Efficiency η</td><td>0.98</td></tr> <tr> <td>Filter class (integrated)</td><td>Unfiltered</td></tr> </table>	Power factor λ	0.72	Offset factor $\cos \varphi$	0.95	Efficiency η	0.98	Filter class (integrated)	Unfiltered																
Number of phases	3 AC																														
Line voltage	380 ... 480 V -15 % +10 %																														
Line frequency	47 ... 63 Hz																														
Power factor λ	0.72																														
Offset factor $\cos \varphi$	0.95																														
Efficiency η	0.98																														
Filter class (integrated)	Unfiltered																														
Output <table> <tr> <td>Number of phases</td><td>3 AC</td></tr> <tr> <td>Rated voltage</td><td>400 V</td></tr> <tr> <td>Rated power (HO)</td><td>3.00 kW / 4.00 hp</td></tr> <tr> <td>Rated power (LO)</td><td>3.00 kW / 4.00 hp</td></tr> <tr> <td>Rated current (HO)</td><td>7.30 A</td></tr> <tr> <td>Rated current (LO)</td><td>7.30 A</td></tr> <tr> <td>Rated current (HO) at 480V</td><td>7.30 A</td></tr> <tr> <td>Rated current (LO) at 480V</td><td>7.30 A</td></tr> <tr> <td>Pulse frequency</td><td>4.00 kHz</td></tr> <tr> <td>Output frequency</td><td>0 ... 550 Hz</td></tr> </table>	Number of phases	3 AC	Rated voltage	400 V	Rated power (HO)	3.00 kW / 4.00 hp	Rated power (LO)	3.00 kW / 4.00 hp	Rated current (HO)	7.30 A	Rated current (LO)	7.30 A	Rated current (HO) at 480V	7.30 A	Rated current (LO) at 480V	7.30 A	Pulse frequency	4.00 kHz	Output frequency	0 ... 550 Hz	Ambient conditions <table> <tr> <td>Cooling</td><td>External fan</td></tr> <tr> <td>Installation altitude</td><td>1000 m (3281 ft)</td></tr> </table> Ambient temperature <table> <tr> <td>Operation</td><td>-10 ... 60 °C (14 ... 140 °F)</td></tr> <tr> <td>Storage</td><td>-40 ... 70 °C (-40 ... 158 °F)</td></tr> </table> Relative humidity <table> <tr> <td>Max. operation</td><td>95 %</td></tr> </table>	Cooling	External fan	Installation altitude	1000 m (3281 ft)	Operation	-10 ... 60 °C (14 ... 140 °F)	Storage	-40 ... 70 °C (-40 ... 158 °F)	Max. operation	95 %
Number of phases	3 AC																														
Rated voltage	400 V																														
Rated power (HO)	3.00 kW / 4.00 hp																														
Rated power (LO)	3.00 kW / 4.00 hp																														
Rated current (HO)	7.30 A																														
Rated current (LO)	7.30 A																														
Rated current (HO) at 480V	7.30 A																														
Rated current (LO) at 480V	7.30 A																														
Pulse frequency	4.00 kHz																														
Output frequency	0 ... 550 Hz																														
Cooling	External fan																														
Installation altitude	1000 m (3281 ft)																														
Operation	-10 ... 60 °C (14 ... 140 °F)																														
Storage	-40 ... 70 °C (-40 ... 158 °F)																														
Max. operation	95 %																														
	Communication <table> <tr> <td>Communication</td><td>USS, Modbus RTU</td></tr> </table>	Communication	USS, Modbus RTU																												
Communication	USS, Modbus RTU																														
	Standards <table> <tr> <td>Compliance with standards</td><td>CE, cULus, C-Tick (RCM), KC</td></tr> <tr> <td>CE marking</td><td>EN 61800-5-1 /EN 60204-1 and EN 61800-3</td></tr> </table>	Compliance with standards	CE, cULus, C-Tick (RCM), KC	CE marking	EN 61800-5-1 /EN 60204-1 and EN 61800-3																										
Compliance with standards	CE, cULus, C-Tick (RCM), KC																														
CE marking	EN 61800-5-1 /EN 60204-1 and EN 61800-3																														

Overload capability

Low Overload (LO)

110 % rated output current for 60 s, cycle time 300 s

High Overload (HO)

150 % rated output current for 60 s, cycle time 300 s



Figure similar

Mechanical data	
Mounting position	Through-hole mounting / wall mounting / side-by-side mounting
Degree of protection	IP20 / UL open type
Size	FSB
Net weight	1.60 kg (3.53 lb)
Width	140.0 mm (5.51 in)
Height	160.0 mm (6.30 in)
Depth	164.5 mm (6.48 in)
Inputs / outputs	
Standard digital inputs	
Number	4
Digital outputs	
Number as relay changeover contact	1
Number as transistor	1
Analog inputs	
Number	2 (Can be used as additional digital input)
Analog outputs	
Number	1

Connections																	
Max. motor cable length																	
Shielded	25 m (82 ft)																
Unshielded	50 m (164 ft)																
Converter losses to IEC61800-9-2*																	
Efficiency class	IE2																
Comparison with the reference converter (90% / 100%)	33.40 %																
<table><tr><th>Frequency (f)</th><th>100% I</th><th>50% I</th><th>25% I</th></tr><tr><td>0%</td><td>85.0 W (1.70 %)</td><td>68.0 W (1.30 %)</td><td>60.8 W (1.20 %)</td></tr><tr><td>50%</td><td>95.7 W (1.90 %)</td><td>72.3 W (1.40 %)</td><td>63 W (1.20 %)</td></tr><tr><td>90%</td><td>114.0 W (2.20 %)</td><td>78.8 W (1.60 %)</td><td>-</td></tr></table>		Frequency (f)	100% I	50% I	25% I	0%	85.0 W (1.70 %)	68.0 W (1.30 %)	60.8 W (1.20 %)	50%	95.7 W (1.90 %)	72.3 W (1.40 %)	63 W (1.20 %)	90%	114.0 W (2.20 %)	78.8 W (1.60 %)	-
Frequency (f)	100% I	50% I	25% I														
0%	85.0 W (1.70 %)	68.0 W (1.30 %)	60.8 W (1.20 %)														
50%	95.7 W (1.90 %)	72.3 W (1.40 %)	63 W (1.20 %)														
90%	114.0 W (2.20 %)	78.8 W (1.60 %)	-														
The percentage values show the losses in relation to the rated apparent power of the converter.																	
The diagram shows the losses for the points (as per standard IEC61800-9-2) of the relative torque generating current (I) over the relative motor stator frequency(f). The values are valid for the basic version of the converter without options/components.																	
*converted values																	