



TEL (915) 590-8500
FAX (915) 590-8510

6.125"

.125" rcr
X4

SIEMENS

Cat. No. DTF326 Fusible Heavy Duty Double Throw Safety Switch Type VB II
600 Amps Maximum 240 Volts AC (V~) Maximum 250 Volts DC (V~) Maximum
Type 1 Indoor

Horsepower Ratings	240 VAC ¹ 1Ø	240 VAC 3Ø	250 VDC ¹
Std. HP (Std. Fuse) ⁴	15 ⁹	75	50
Max. HP (Time Delay)	15 ⁹	200 ⁷	—

Continuous load current not to exceed 80% of the rating of fuses employed in other than motor circuits.
 Suitable for use as Service Equipment when used with ground bar kit **HG656** on 3 phase, 3 wire systems or when used with **HN678** neutral kit on 1 phase, 3 wire or 3 phase, 4 wire systems.
 Manually-operated switch suitable for use in accordance with Article 702 of the National Electrical Code, ANSI/NFPA 70.

Fuse and Short Circuit Information

When used with Class J fuses with the load base relocated to the "J Fuse" position marked on the enclosure or Class T fuses with the load base relocated to the "T Fuse" position marked on the enclosure, this switch is suitable for use on a circuit capable of delivering not more than 200,000 amperes, RMS symmetrical, 240 volts maximum.

Danger - Unless class J or T fuses are used, this switch may present a risk of fire and injury to persons if installed on circuits capable of delivering more than 10,000 amperes, RMS symmetrical.

When used with fuses marked with DC ratings, this switch is suitable for use on a circuit capable of delivering not more than the DC interrupting rating marked on the fuse, at the DC voltage rating marked on the fuse, up to a maximum of 10,000 amperes, 250 volts DC.

Danger - Unless fuses marked for an interrupting rating of 10,000 amperes at 250 volts DC are used, this switch may present a risk of fire and injury to persons if installed on circuits capable of delivering more than 10,000 amperes."

Renewable link fuses are not recommended.



⚠ DANGER

**Hazardous voltage.
Will cause death or serious injury.**

- Disconnect and lock out power supplying this switch before working on this switch.
- Turn off switch before removing or installing fuses if so equipped.
- Always use a properly rated voltage sensing device on all fuse clips (Fusible) or all load side terminals (Non-Fusible) to confirm switch is off.
- Close or replace cover before turning power on.

11.375"

Torque Fuse Clamp Mounting screws to 50 lb-ins.

Terminal & Wire Information

USE 75° COPPER OR ALUMINUM WIRE

Terminal & Wire Information			
Description	Wire Range	Wire Tightening Torque ⁵	Lug Mounting Torque ⁵
Line, Load & Main Neutral	(2) 1/0 AWG-500 kcmil (4) 1/0 AWG-250 kcmil	500 lb-ins.	80 lb-ins. 240 lb-ins. (Neutral 3/8-16 Bolt)
Ground	(2) 6 AWG-300 kcmil	275 lb-ins.	80 lb-ins.

Inspection record number:

UL Listed Compression Lugs (Refer to manufacturers instructions for proper installation)¹⁰

Wire Size (AWG OR kcmil)	Burndy		Thomas & Betts		IlSCO	
	Cu Only	Cu / Al	Cu Only	Cu / Al	Cu Only	Cu / Al
2/0	YA26-N	YA26A1	54160 54951BE			IACL-2/0 ACN-2/0
3/0	YA27-L Box YA27	YA27A3	54165-TB 54965BE		CRB-3/0 CRB-3/0L	IACL-3/0 ACN-3/0
4/0	YA28-L Box YA28	YA28A3	54170 54970BE	60150	CRB-4/0 CRB-4/0L	IACL-4/0 ACN-4/0
250	YA29-L Box YA29	YA29A1	54113 54913BE	61156 60156	CRA-250 CRA-250L	IACL-250 ACL-250
300	YA30-L YA30	YA30A1	54114 54914BE	61162 60162	CRA-300 CRA-300L	IACL-300 ACL-300
350	YA31-L YA31	YA31A1	54915BE	61165 60165	CRA-350 CRA-350L	IACL-350
400	YA32-N		54116 54916BE			
500	YA34-L6 YA34-N			61171		IACL-500

Accessories

Aux. Switch (1NO - 1NC)	HA165678	Neutral	HN678	Class R Fuse Kit (Rejects Class H & K Fuses)	HR656
Aux. Switch (2NO - 2NC)	HA265678	Ground Lug Kit (Wire Range (2) 14-2/0 AWG)	HG656	Compression Lug Mounting Kit ¹⁰	HCL65678
Low Voltage Aux. Sw. (1NO - 1NC)	HA365678	Isolated Ground Lug Kit	HG2656	Wire Grip Kit (CU)	HLC65678

Replacement Parts

Line Base	HFB66	Wire Grip Kit (Al)	HL65678	Handle / Handle Guard	HHD65678
Load Base	HBB656	Mechanism		Door	DTF326DOOR

Protected by one or more of the following US Patents: 6,388,215.

¹ Use outer two poles.

⁴ The starting current of motors more than the standard horsepower or kilowatt ratings may require the use of fuses with appropriate time delay characteristics.

⁵ When tightening or replacing connectors, refer to lug mounting torque in Terminal & Wire Information Table.

⁷ Not for use as a motor controller over 74.6 kW (100 hp).

⁹ If the fuses of this switch are the sole means of motor protection, fuse per the NEC using UL Listed fuse reducers.

¹⁰ If compression lugs are used, order compression lug mounting kit **HCL65678**.

For questions on this device

please call 1-800-241-4453

Siemens Industry, Inc.

Norcross, GA 30092 USA

<http://www.usa.siemens.com/powerdistribution>

Assembled in Mexico

Pc. No. 508316H05

0704

COMPANY NAME

SIEMENS INDUSTRY, INC.

JOB WILL NOT BE PRINTED UNLESS APPROVED BY CUSTOMER.

THIS DOCUMENT IS THE PROPERTY OF LABELTECH, INC. IT'S USE IS AUTHORIZED ONLY FOR RESPONDING TO A REQUEST FOR QUOTATION OR FOR THE PERFORMANCE OF WORK REQUESTED FROM LABELTECH, INC. ALL QUESTIONS MUST BE REFERRED TO THE LABELTECH, INC. PRODUCTION DEPARTMENT.

MATERIAL

Synthetic Paper Fasson

INK COLORS

BLACK

185 RED

SIZE

WIDTH

6.125"

LENGTH

11.375"

ROUND CORNER RADIUS

.125"

OK TO PRINT AS IS

MAKE CORRECTIONS, RESUBMIT CORRECTED PROOF

OK TO PRINT WITH CORRECTIONS AS MARKED

PART NO.

508316H05

DESCRIPTION:

AUTHORIZED BY

DATE

REVISION LEVEL 38P

DESIGNER

Joel Ortega

CHECKED BY

DATE

08/05/11