

# One-Light Undercabinet

Undercabinet mounted • Damp location listed **PROGRESS LED**

## Description:

Under Cabinet 12" LED 3000K. Antique Bronze finish.

## Specifications:

- Antique Bronze (-20) (painted)
- Aluminum Construction
- Direct wire and linkable with long life LEDs.
- Extruded aluminum frame, polycarbonate end plates.
- Tempered micro-prismatic glass lens.
- Keyhole slots on top for ease of mounting.
- 120V integral electronic driver rated for 35,000 hr. continuous use.
- ON/OFF rocker switch.
- 284 lumens (delivered) Long life LEDs.
- Powered from a single location using the P8740 direct-wire junction box (each fixture can also be direct-wired individually).
- Fixtures can be linked together to form a continuous row of illumination. (5 amps max.)
- Linking cables can be used with or without the use of the P8740 junction box.
- Smooth and continuous dimming on most incandescent or ELV dimmer switches.
- Reference manufacturers' minimum load requirements for dimmer switches.
- Dimmable to 10% brightness (See Dimming Notes)

## Performance:

Number of Modules	6
Input Power	6.5w
Input Voltage	120 V
Input Frequency	60 Hz
Lumens/LPW (Source)	per module
Lumens/LPW (Delivered)	284/44 (LM-79)
CCT	3000 K
CRI	80+
Life (hours)	35,000 (L70/TM-21)
FCC	FCC Title 47, Part 15, Class B
Min. Start Temp	-30 °C
Max. Operating Temp	30 °C
Warranty	5 year warranty
Labels	cCSAus Damp location listed

## P7012-20

## Images:



## Dimensions:

Width: 3-1/2"

Length: 12"

Height: 1"

## One-Light Undercabinet

Undercabinet mounted • Damp location listed



### P7012-20

#### Dimming Notes:

---

P7012 is designed to be compatible with many ELV/Reverse Phase and with some incandescent controls.

The following is a partial list of known compatible dimmer controls.

#### Dimming Controls

---

Lutron Diva DV-600P

Lutron Diva DVELV-300P

Lutron Skylark S-600P

Lutron Ariadni AY-600P

Lutron Ariadni TG-603P

Lutron Maestro MAELV-600

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.