NSYTRV952BB

Linergy passthrough terminal block - 95mm² 232A single-level 1x1 lug to lug





Main

Range	Linergy
Product name	Linergy TR
Product or component type	Terminal block
Device short name	TRV
Terminal block type	Passthrough
Terminal block level	1
Mounting mode	Clip-on
Nominal cross section	95 mm²
Length	110 mm
Colour	Grey
Quantity per set	Set of 10

Complementary

Complementary	
Width	40 mm
Height	56 mm
Connections - terminals	1 x lug : downstream 1 x lug : upstream
Number of connections	2
Connection position	Sideways
Number of measurement input	0
Cable cross section	2595 mm², solid 3595 mm², flexible without
Tightening torque	2530 N.m
Wire stripping length	29 mm
Tool type	Disconnection : screwdriver Connection : screwdriver
[Ue] rated operational voltage	600 V CSA 600 V cURus 1000 V conforming to EN/IEC 60947-7-1
[le] rated operational current	200 A CSA 230 A cURus 232 A conforming to EN/IEC 60947-7-1
Material	Polyamide 6/6 (insulating case)
Dielectric loss	0.01 at 1 MHz conforming to VDE 0303-T4 0.01 at 1 MHz conforming to IEC 60250
Dielectric constant	3.7 at 1 MHz
Resistivity	10000 M Ω .m conforming to VDE 0303-T30 10000 M Ω .m conforming to IEC 60093
Surface resistance	1000 G Ω conforming to VDE 0303-T30 1000 G Ω conforming to IEC 60093
Creep resistance	500 CTI (> 400 kB) conforming to VDE 0303-T30 500 CTI (> 400 kB) conforming to IEC 60093
Flame retardance	V0, thickness0.8 mm conforming to UL 94
Range compatibility	Spacial Prisma - PH Prisma - P Prisma - G
Product compatibility	Spacial enclosures

Environment

Product certifications	CSA CURus GL EAC	
Dielectric strength	1000 V conforming to IEC 60243-1	
Ambient air temperature for operation	-40130 °C conforming to VDE 0304-T21 -40130 °C conforming to IEC 60216-1	

Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 1052 - Schneider Electric declaration of conformity
REACh	Reference not containing SVHC above the threshold
Product environmental profile	Available Download Product Environmental
Product end of life instructions	Need no specific recycling operations

