



Overview

Presentation	NetShelter SX Networking Enclosure expands Schneider Electric's superior IT enclosure line with improved support for high density networking applications. Integrated high density cable managers and improved cable access roof provide support for large cable bundles. When combined with the Side Airflow Duct Kit, the Networking Enclosure ensures complete isolation of cold intake and hot exhaust air for large switches and SAN directors.
Lead time	Usually in Stock

General

Provided equipment	<ul style="list-style-type: none"> Baying hardware Documentation CD Key(S) Keyed-alike doors and side panels Leveling feet Mounting Hardware Pre-installed casters Side Panels User Manual Vertical cable managers
--------------------	--

Physical

Maximum Mounting Depth	32.25 in (81.92 cm)
Number of rack unit	42U
Minimum Mounting Depth	11.00 in (27.94 cm)
Marking	<ul style="list-style-type: none"> 14 gauge EIA mounting rail 16 gauge front door 16 gauge post 16 gauge rear door 18 gauge roof 18 gauge side panels
Color	Gray
Maximum Depth	42.13 in (107 cm)
Rack Width	19"
Maximum Height	78.39 in (199.1 cm)
Net Weight	343.81 lb(US) (155.95 kg)
Permanent permissible load	<ul style="list-style-type: none"> 2250 Lb(US) (1020.58 kg) dynamic 3750 lb(US) (1700.97 kg) static
Maximum Width	29.53 in (75 cm)

Conformance

Standards	<ul style="list-style-type: none"> UL 2416 UL 60950-1 EIA-310E
-----------	---



Ordering and shipping details

Package weight(Lbs)	370.77 lb(US) (168.18 kg)
---------------------	---------------------------

Packing Units

Package 1 Height	83.39 in (211.8 cm)
Package 1 width	33.50 in (85.09 cm)
Package 1 Length	47.99 in (121.9 cm)
Number of Units in Package 3	1

Offer Sustainability

Sustainable offer status	Green Premium product
REACH free of SVHC	Yes
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)  EU RoHS Declaration
Toxic heavy metal free	Yes
Mercury free	Yes
RoHS exemption information	 Yes

Contractual warranty

Warranty	5 year repair or replace
----------	--------------------------