

# 8739SEA51V02S

## REVERSING COMBO STARTER 600VAC 90A NEM

### Main

Product	Combination Starter
Type	S
Control Circuit Type	Separate control circuit
Control Units	No control units
Enclosure Type	NEMA 12 painted sheet steel with external reset
Auxiliary Contacts	Without
Horsepower Rating	20...25 Hp 460 V AC 25...30 hp 575 V AC
Number of Poles	3P
Maximum Voltage Rating	600 V AC
NEMA Size	3
Control Circuit Voltage	110 V AC 50 Hz 120 V AC 60 Hz
Pilot Light	No indicator
Starter Type	Reversing
Overload Type	Melting alloy
Number of Thermal Units Required	3
Disconnect Type	Mag-Gard circuit breaker

### Ordering and shipping details

Category	21293 - 8738,39 SE,SF(NOT S*R,T,W)
Discount Schedule	CP1
Package weight(Lbs)	260 lb(US) (117.93 kg)
Returnability	No
Country of origin	MX

### Offer Sustainability

EU RoHS Directive	Not compliant
-------------------	---------------

### Contractual warranty

Warranty	18 months
----------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.