

Main

| | |
|----------------------|------------------------|
| Product | Combination Starter |
| Type | S |
| Control Circuit Type | Common control circuit |

Complementary

| | |
|-------------------------|-----------------------------------|
| Control Circuit Voltage | 220 V AC 50 Hz 240 V AC 60 Hz |
| Starter Type | Non reversing |
| Number of Poles | 2P |
| Horsepower Rating | 7.5 hp 240 V AC, 1 phase |
| Maximum Voltage Rating | 600 V AC |
| Control Units | No control units |
| Pilot Light | No indicator |
| Auxiliary Contacts | Without |
| Thermal overload type | Melting alloy 1 |
| Disconnect Type | Fusible disconnect switch H, 60 A |
| NEMA size | 2 |

Environment

| | |
|----------------|---|
| Enclosure Type | NEMA 4X glass polyester with external reset |
|----------------|---|

Ordering and shipping details

| | |
|---------------------|------------------------------------|
| Category | 21213 - 8538,39 SC,SD(NOT S*R,T,W) |
| Discount Schedule | CP1 |
| Package weight(Lbs) | 37.53 lb(US) (17.02 kg) |
| Returnability | No |
| Country of origin | MX |

Offer Sustainability

| | |
|-------------------|--|
| EU RoHS Directive | Will be compliant – Date to be confirmed |
|-------------------|--|

Contractual warranty

| | |
|----------|-----------|
| Warranty | 18 months |
|----------|-----------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.