

8738SFG11V08

REVERSING COMBO STARTER 600VAC 135A



Main

Product	Combination Starter
Type	S
Control Circuit Type	Common control circuit
Control Units	No control units
Enclosure Type	NEMA 1 painted sheet steel with external reset
Auxiliary Contacts	Without
Horsepower Rating	40 Hp 200 V AC, 3 phase 50 Hp 230 V AC, 3 phase 100 Hp 460 V AC, 3 phase 100 hp 575 V AC, 3 phase
Number of Poles	3P
Maximum Voltage Rating	600 V AC
NEMA Size	4
Control Circuit Voltage	208 V AC 60 Hz
Pilot Light	No indicator
Starter Type	Reversing
Overload Type	Melting alloy
Number of Thermal Units Required	3
Disconnect Type	Non-fusible disconnect

Ordering and shipping details

Category	21293 - 8738,39 SE,SF(NOT S*R,T,W)
Discount Schedule	CP1
Package weight(Lbs)	245 lb(US) (111.13 kg)
Returnability	No
Country of origin	MX

Offer Sustainability

EU RoHS Directive	Not compliant
-------------------	---------------

Contractual warranty

Warranty	18 months
----------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.