# 8538SBG13V81FF4T STARTER MOTOR CONTROL <1000VAC



#### Main

Product	Combination Starter
Туре	S
Control Circuit Type	Control circuit transformer

## Complementary

- Compression y		
Control Circuit Voltage	120 V AC 60 Hz secondary circuit 480 V AC 60 Hz primary circuit	
Starter Type	Non reversing	
Number of Poles	3P	
Horsepower Rating	5 Hp 460 V AC, 3 phase 5 hp 575 V AC, 3 phase	
Maximum Voltage Rating	600 V AC	
Control Units	No control units	
Pilot Light	No indicator	
Auxiliary Contacts	Without	
Control Circuit Fusing	2 fuses primary circuit 1 fuse secondary circuit	
Thermal overload type	Melting alloy 3	
Disconnect Type	Fusible disconnect switch H, 30 A	
NEMA size	0	

## Environment

Enclosure Type	NEMA 1 painted sheet steel with external reset
----------------	--

### Ordering and shipping details

Category	21212-8538,39SB(NOT S*R,S*T,S*W)	
Discount Schedule	CP1	
GTIN	785901020516	
Package weight(Lbs)	33.54 lb(US) (15.213 kg)	
Returnability	Yes	
Country of origin	MX	

#### Offer Sustainability

California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds which is known to the State of California to cause Carcinogen & Reproductive harm. For more information go to www.p65warnings.ca.gov
EU RoHS Directive	Not compliant
China RoHS Regulation	China RoHS Declaration

Warranty 18 months