8538SFG11V08 COMBO STARTER 600VAC 135A NEMA



Main

| Product | Combination Starter |
|----------------------|------------------------|
| Туре | S |
| Control Circuit Type | Common control circuit |

Complementary

| Control Circuit Voltage | 208 V AC 60 Hz | |
|-------------------------|--|--|
| Starter Type | Non reversing | |
| Number of Poles | 3P | |
| Horsepower Rating | 40 Hp 200 V AC, 3 phase 50 Hp 230 V AC, 3 phase 100 Hp 460 V AC, 3 phase 100 hp 575 V AC, 3 phase | |
| Maximum Voltage Rating | 600 V AC | |
| Control Units | No control units | |
| Pilot Light | No indicator | |
| Auxiliary Contacts | Without | |
| Thermal overload type | Melting alloy 3 | |
| Disconnect Type | Non-fusible disconnect switch | |
| NEMA size | 4 | |

Environment

| Enclosure Type | NEMA 1 painted sheet steel with external reset | |
|----------------|--|--|

Ordering and shipping details

| Category | 21214 - 8538,39 SE,SF(NOT S*R,T,W) |
|-------------------|------------------------------------|
| Discount Schedule | CP1 |
| GTIN | 785901518433 |
| Returnability | Yes |
| Country of origin | MX |

Packing Units

| Unit Type of Package 1 | PCE |
|------------------------------|---------------------------|
| Number of Units in Package 1 | 1 |
| Package 1 Weight | 168.00 lb(US) (76.204 kg) |

Offer Sustainability

| EU RoHS Directive | Not compliant |
|-------------------|---------------|
| | |

Warranty 18 months