Data sheet

6ES7134-6GB00-0BA1



SIMATIC ET 200SP, Analog input module, AI 2xI 2-/4-wire Standard, Pack quantity: 1 unit, suitable for BU type A0, A1, Color code CC05, Module diagnostics, 16 bit

General information	
Product type designation	Al 2xl 2-/4-wire ST
HW functional status	from FS04
Firmware version	
FW update possible	Yes
usable BaseUnits	BU type A0, A1
Color code for module-specific color identification plate	CC05
Product function	
 I&M data 	Yes; I&M0 to I&M3
 Isochronous mode 	No
Measuring range scalable	No
Engineering with	
 STEP 7 TIA Portal configurable/integrated from version 	V13 SP1
 STEP 7 configurable/integrated from version 	V5.5 SP3
 PROFIBUS from GSD version/GSD revision 	One GSD file each, Revision 3 and 5 and higher
 PROFINET from GSD version/GSD revision 	V2.3 / -
Operating mode	
 Oversampling 	No
• MSI	No
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	45 mA; without sensor supply
Encoder supply	
24 V encoder supply	
• 24 V	Yes
 Short-circuit protection 	Yes
Output current, max.	50 mA; Total current for both channels (two-wire)
Additional 24 V encoder supply	
• 24 V	Yes

	V M III '
Short-circuit protection	Yes; Module-wise
Output current, max.	200 mA; Total current for both channels (four-wire)
Power loss	
Power loss, typ.	1.1 W
Address area	
Address space per module	
 Address space per module, max. 	4 byte; + 1 byte for QI information
Hardware configuration	
Automatic encoding	Yes
 Mechanical coding element 	Yes
Type of mechanical coding element	Type A
Selection of BaseUnit for connection variants	
 1-wire connection 	BU type A0, A1
• 2-wire connection	BU type A0, A1
 4-wire connection 	BU type A0, A1
Analog inputs	
Number of analog inputs	2
 For current measurement 	2
permissible input current for current input (destruction limit), max.	50 mA
Cycle time (all channels), min.	500 μs
Input ranges (rated values), currents	
• 0 to 20 mA	Yes; 15 bit
 Input resistance (0 to 20 mA) 	130 Ω; 90 ohms with two wires
• -20 mA to +20 mA	Yes; 16 bit incl. sign
 Input resistance (-20 mA to +20 mA) 	130 Ω
• 4 mA to 20 mA	Yes; 15 bit
 Input resistance (4 mA to 20 mA) 	130 Ω; 90 ohms with two wires
Cable length	
• shielded, max.	1 000 m
	1 000 m
• shielded, max.	1 000 m Sigma Delta
shielded, max. Analog value generation for the inputs	
shielded, max. Analog value generation for the inputs Measurement principle	
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel	Sigma Delta
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max.	Sigma Delta 16 bit
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference	Sigma Delta 16 bit Yes
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel)	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without filter
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without filter
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without filter 4 Yes
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without filter 4 Yes Yes; 1x conversion time
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None Step: low	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without filter 4 Yes Yes; 1x conversion time Yes; 4x conversion time
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None Step: low Step: Medium	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without filter 4 Yes Yes; 1x conversion time Yes; 4x conversion time Yes; 8x conversion time
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None Step: None Step: High	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without filter 4 Yes Yes; 1x conversion time Yes; 4x conversion time Yes; 8x conversion time
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None Step: low Step: Medium Step: High Encoder	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without filter 4 Yes Yes; 1x conversion time Yes; 4x conversion time Yes; 8x conversion time
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None Step: low Step: Medium Step: High Encoder Connection of signal encoders	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without filter 4 Yes Yes; 1x conversion time Yes; 4x conversion time Yes; 8x conversion time Yes; 16x conversion time
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None Step: low Step: low Step: Medium Step: High Encoder Connection of signal encoders for current measurement as 2-wire transducer	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without filter 4 Yes Yes; 1x conversion time Yes; 4x conversion time Yes; 8x conversion time Yes; 16x conversion time Yes; 16x conversion time
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None Step: None Step: High Encoder Connection of signal encoders for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max.	Sigma Delta 16 bit Yes $16.6 / 50 / 60 \text{ Hz} / \text{ off}$ 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without filter 4 Yes Yes; 1x conversion time Yes; 4x conversion time Yes; 8x conversion time Yes; 16x conversion time Yes 16x conversion time
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None Step: low Step: Medium Step: High Encoder Connection of signal encoders for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer	Sigma Delta 16 bit Yes $16.6 / 50 / 60 \text{ Hz} / \text{ off}$ 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 µs without filter 4 Yes Yes; 1x conversion time Yes; 4x conversion time Yes; 8x conversion time Yes; 16x conversion time Yes 16x conversion time
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None Step: None Step: low Step: Medium Step: High Encoder Connection of signal encoders for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 μs without filter 4 Yes Yes; 1x conversion time Yes; 4x conversion time Yes; 8x conversion time Yes; 16x conversion time Yes; 16x conversion time
shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None Step: low Step: Medium Step: High Encoder Connection of signal encoders for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-)	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 μs without filter 4 Yes Yes; 1x conversion time Yes; 4x conversion time Yes; 8x conversion time Yes; 16x conversion time Yes; 16x conversion time Yes 650 Ω Yes
 shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None Step: None Step: Medium Step: High Encoder Connection of signal encoders for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input 	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 μs without filter 4 Yes Yes; 1x conversion time Yes; 4x conversion time Yes; 8x conversion time Yes; 16x conversion time Yes; 16x conversion time Yes 650 Ω Yes 0.01 % 0.005 %/K
 shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) Smoothing of measured values Number of smoothing levels parameterizable Step: None Step: None Step: Medium Step: High Encoder Connection of signal encoders for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to inputs, min. 	Sigma Delta 16 bit Yes 16.6 / 50 / 60 Hz / off 50 ms @ 60 Hz, 60 ms @ 50 Hz, 180 ms @ 16.6 Hz, 500 μs without filter 4 Yes Yes; 1x conversion time Yes; 4x conversion time Yes; 8x conversion time Yes; 16x conversion time Yes; 16x conversion time Yes 650 Ω Yes 0.01 % 0.005 %/K -50 dB

Company relative to input samps (1/)	0.5.0/
• Current, relative to input range, (+/-)	0.5 %
Basic error limit (operational limit at 25 °C)	0.00/
Current, relative to input range, (+/-)	0.3 %
Interference voltage suppression for f = n x (f1 +/- 1 %), f1 =	
 Series mode interference (peak value of interference < rated value of input range), min. 	70 dB
 Common mode voltage, max. 	10 V
Common mode interference, min.	90 dB
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Alarms	
Diagnostic alarm	Yes
Limit value alarm	No
Diagnoses	
Monitoring the supply voltage	Yes
Wire-break	Yes; at 4 to 20 mA
Short-circuit	Yes; Short-circuit of the encoder supply
Group error	Yes
Overflow/underflow	Yes
Diagnostics indication LED	
Monitoring of the supply voltage (PWR-LED)	Yes; green PWR LED
Channel status display	Yes; green LED
• for channel diagnostics	No
for module diagnostics	Yes; green/red DIAG LED
Potential separation	
Potential separation channels • between the channels	No
between the channels and backplane bus	Yes
•	
between the channels and the power supply of the electronics	Yes
Permissible potential difference	
between the inputs (UCM)	10 Vpp
Isolation	
Isolation tested with	707 V DC (type test)
Ambient conditions	
Ambient temperature during operation	
horizontal installation, min.	-30 °C; < 0 °C as of FS04
 horizontal installation, max. 	60 °C
vertical installation, min.	-30 °C; < 0 °C as of FS04
vertical installation, max.	50 °C
Altitude during operation relating to sea level	
Installation altitude above sea level. max.	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	2 300 m, resultations for installation analogs 2 300 m, 600 mariation
Width	15 mm
Height	73 mm
Depth	58 mm
Weights	
Weights Weight, approx.	32 g