

Error: No CAD-Data available for this configuration.

Data sheet for Active Line Modules - Chassis format

Article No.: 6SL3330-7TE32-1AA3

Figure similar

Client order no. : Order no. : Offer no. : Remarks :

tem no. :	
Consignment no.	:
Project :	

Rat	ed data
Line voltage	3 AC 380 480 V
Rated power	
for I _{N DC} (50 Hz 400 V)	132 kW
for I _{H DC} (50 Hz 400 V)	115 kW
for I _{N DC} (60 Hz 460 V)	200 hp
for I _{H DC} (60 Hz 460 V)	150 hp
DC-link current	
Rated current I _{N DC}	235 A
Base-load current I _{H DC} 1)	209 A
Maximum current I _{max DC}	352 A
Infeed/regenerative feedback curren	t
Rated current I _{NE}	210 A
Maximum current I _{max E}	315 A
Current drawn	
24 V DC auxiliary power supply	1.1 A
400 V AC	0.6 A
DC link capacitance	
Active Line Module	4,200 μF
Drive line-up, max.	41,600 μF
Power loss, max. 3)	
at 50 Hz 400 V	2.20 kW
at 60 Hz 460 V	2.30 kW

Conn	ections
Line connection U1, V1, W1	
Design	2 x Flat connector for M10 screw
Conductor cross-section, max. (IEC)	2 x 185 mm²
DC link connection DCP, DCN	
Design	2 x M10 screw
Conductor cross-section, max. (IEC)	2 x 185 mm²
PE connection	
Design	2 x M10 screw
Conductor cross-section, max. (IEC)	2 x 185 mm²
PE2/GND connection	
Design	2 x M10 screw
Conductor cross-section, max. (IEC)	2 x 185 mm²
Mechan	nical data
Degree of protection	IP20
Weight	95 kg (209.44 lb)
Frame size	FX
Dimensions	
Width	326 mm (12.8 in)
Height	1,400 mm (55.12 in)
Depth	356 mm (14.02 in)
Other technica	al specifications
Cooling air requirement	0.17 m³/s (6 ft³/s)
Sound pressure level L_{pA} (1 m) at 50/60 Hz $^{\scriptscriptstyle (4)}$	64 dB / 67 dB
Minimum short-circuit current 5)	6,200 A
Line length, max. ⁶⁾	
Shielded	2,700 m (8,858.27 ft)

¹⁾The base load current IH DC is the basis for a duty cycle of 150% for 60 s or Imax DC for 5 s with a duty cycle duration of 300 s.

³⁾The specified power loss represents the maximum value at 100% utilization. The value is lower under normal operating conditions.

⁴⁾Total sound pressure level of Active Interface Module and Active Line Module.

⁵⁾Current required for reliably triggering protective devices.

⁶⁾ Total of all motor cables and DC link. Longer cable lengths for specific configurations are available on request. For additional information, please refer to the SINAMICS Low Voltage Engineering Manual.