**Data sheet** 

## 3RA2220-1AB23-0AK6



Fuseless motor starter Reversing operation 600VAC Size S0 1.1-1.6A 110/120VAC 50/60HZ screw connection For 35 mm rail-mounting Type of coordination 2 IQ = 150 KA Also full fills type Of coordination 1 1NO+1NC (per contactor)

product brand name	SIRIUS		
product designation	non-fused motor starter 3RA2		
design of the product	reversing starter		
manufacturer's article number			
<ul> <li>of the supplied contactor</li> </ul>	3RT2023-1AK60		
<ul> <li>of the supplied circuit-breakers</li> </ul>	3RV2011-1AA10		
<ul> <li>of the supplied RH assembly kit</li> </ul>	3RA2923-1BB1		
<ul> <li>of the supplied busbar adapter</li> </ul>	3RA2922-1AA00		
<ul> <li>of the supplied link module</li> </ul>	3RA2921-1AA00		
<ul> <li>of the supplied standard mounting rail adapter</li> </ul>	3RA2922-1AA00		
General technical data			
size of the circuit-breaker	S00		
size of load feeder	S0		
product extension auxiliary switch	Yes		
insulation voltage with degree of pollution 3 at AC rated value	690 V		
degree of pollution	3		
surge voltage resistance rated value	6 kV		
shock resistance according to IEC 60068-2-27	6g / 11 ms		
mechanical service life (switching cycles) of contactor typical	10 000 000		
type of assignment	2		
Substance Prohibitance (Date)	03/01/2017		
Ambient conditions			
ambient temperature			
<ul> <li>during operation</li> </ul>	-20 +60 °C		
during storage	-50 +80 °C		
<ul> <li>during transport</li> </ul>	-55 +80 °C		
Main circuit			
number of poles for main current circuit	3		
design of the switching contact	electromechanical		
adjustable current response value current of the current-dependent overload release	1.1 1.6 A		
operating voltage			
rated value	690 V		
at AC-3 rated value maximum	690 V		
operating frequency rated value	50 60 Hz		
operational current at AC-3 at 400 V rated value	1.5 A		
operating power at AC-3			
• at 400 V rated value	550 W		

1500 \( \tau \)	FFO.W		
at 500 V rated value	550 W		
at 690 V rated value	1 100 W		
Control circuit/ Control			
control supply voltage at AC			
at 50 Hz rated value	110 V		
<ul> <li>at 50 Hz rated value</li> </ul>	88 121 V		
<ul> <li>at 60 Hz rated value</li> </ul>	120 V		
at 60 Hz rated value	96 132 V		
apparent holding power of magnet coil at AC	7.2 VA		
inductive power factor with the holding power of the coil	0.28		
Auxiliary circuit			
number of NC contacts for auxiliary contacts	2		
number of NO contacts for auxiliary contacts	2		
Protective and monitoring functions			
trip class	CLASS 10		
design of the overload release	thermal (bimetallic)		
response value current of instantaneous short-circuit trip unit	20.8 A		
UL/CSA ratings			
full-load current (FLA) for 3-phase AC motor  • at 480 V rated value	1.6 A		
• at 600 V rated value	1.3 A		
yielded mechanical performance [hp]			
• for single-phase AC motor	0.4 h		
— at 230 V rated value	0.1 hp		
• for 3-phase AC motor	0.75 h		
— at 460/480 V rated value	0.75 hp		
— at 575/600 V rated value	0.75 hp		
Short-circuit protection			
product function short circuit protection	Yes		
design of the short-circuit trip	Yes magnetic		
design of the short-circuit trip conditional short-circuit current (Iq)	magnetic		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value			
design of the short-circuit trip conditional short-circuit current (Iq)	magnetic		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value	magnetic		
design of the short-circuit trip conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value Installation/ mounting/ dimensions	magnetic 153 000 A		
design of the short-circuit trip conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value Installation/ mounting/ dimensions mounting position	magnetic  153 000 A  vertical		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method height	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm		
design of the short-circuit trip conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value Installation/ mounting/ dimensions mounting position fastening method height width	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position fastening method height width depth	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position fastening method height width depth required spacing	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards	vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm  10 mm 0 mm 30 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail  265 mm  90 mm  120 mm  10 mm  0 mm  30 mm  9 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail  265 mm  90 mm  120 mm  10 mm  0 mm  30 mm  9 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm  10 mm 0 mm 30 mm 9 mm 10 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — backwards  — at the side  — downwards  • for live parts  — forwards  — backwards	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — backwards  — upwards  • for live parts  — forwards  — backwards  — upwards  — upwards	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm  10 mm 0 mm 30 mm 10 mm 10 mm 10 mm 10 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — upwards  — downwards  — torwards  — downwards  — backwards  — backwards  — downwards  — at the side	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm  10 mm 0 mm 30 mm 10 mm 10 mm 10 mm 10 mm 10 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — backwards  — upwards  — at the side  — downwards  — backwards  — backwards  — backwards  — at the side  Connections/ Terminals	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm 10 mm 10 mm 9 mm 10 mm 9 mm 10 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — upwards  — a the side  — downwards  • for live parts  — forwards  — backwards  — upwards  — at the side  Connections/ Terminals  type of electrical connection for main current circuit	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm  10 mm 0 mm 30 mm 10 mm 10 mm 10 mm 10 mm 10 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  • at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — upwards  — a the side  — downwards  — torwards  — backwards  — upwards  — to rowards  — to rowa	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm 30 mm 9 mm 10 mm screw-type terminals		
design of the short-circuit trip  conditional short-circuit current (Iq)  at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position fastening method height width depth  required spacing  for grounded parts  forwards  backwards  upwards  at the side  downwards  for live parts  forwards  upwards  downwards  at the side  downwards  at the side  connections/ Terminals  type of electrical connection for main current circuit  type of connectable conductor cross-sections  for main contacts stranded	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm 30 mm 9 mm 10 mm 50 mm 50 mm 50 mm 50 mm 50 mm 50 mm 70 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position fastening method height width depth  required spacing  for grounded parts  forwards  backwards  upwards  at the side  downwards  for live parts  forwards  upwards  at the side  downwards  at the side  connections/ Terminals  type of electrical connection for main current circuit  type of connectable conductor cross-sections  for main contacts stranded  at AWG cables for main contacts	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm somm 10 mm		
design of the short-circuit trip  conditional short-circuit current (Iq)  at 400 V according to IEC 60947-4-1 rated value  Installation/ mounting/ dimensions  mounting position fastening method height width depth  required spacing  for grounded parts  forwards  backwards  upwards  at the side  downwards  for live parts  forwards  upwards  downwards  at the side  downwards  at the side  connections/ Terminals  type of electrical connection for main current circuit  type of connectable conductor cross-sections  for main contacts stranded	magnetic  153 000 A  vertical snap-on fastening on 35 mm standard rail 265 mm 90 mm 120 mm  10 mm 0 mm 30 mm 10 mm 10 mm 10 mm 0 mm 30 mm 10 mm 50 mm 10 mm 50 mm 10 mm 50 mm 50 mm 50 mm 70 mm		

Safety related data						
B10 value with high demand rate according to SN 31920		1 000 000				
proportion of dangerous failures with high demand rate according to SN 31920			73 %			
protection class IP on the front according to IEC 60529		IP20				
touch protection on the front according to IEC 60529		finger-safe, for vertical contact from the front				
Certificates/ approvals						
Conoral Product Approval	For use in haz	zard-	Declaration of	othor		

Confirmation

**General Product Approval** 





ous locations



Conformity

Confirmation

other

## Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2220-1AB23-0AK6

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2220-1AB23-0AK6

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2220-1AB23-0AK6

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RA2220-1AB23-0AK6&lang=en

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2220-1AB23-0AK6/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2220-1AB23-0AK6&objecttype=14&gridview=view1

last modified: 12/15/2020 🖸