SIEMENS

Data sheet

3RA2125-1EA23-0AP6



Fuseless motor starter Direct start 600VAC Size S0 2.8-4A 220/240VAC 50/60HZ screw connection For screw mounting Or 35 mm rail-mounting Type of coordination 2 IQ = 150 KA Also full fills type Of coordination 1 1NO+1NC (MSP) 1NO+1NC (contactor)

product brand name	SIRIUS				
product designation	non-fused motor starter 3RA2				
design of the product	direct starter				
manufacturer's article number					
 of the supplied contactor 	<u>3RT2023-1AP60</u>				
 of the supplied circuit-breakers 	<u>3RV2011-1EA15</u>				
 of the supplied link module 	<u>3RA2921-1AA00</u>				
General technical data					
size of the circuit-breaker	S00				
size of load feeder	S0				
product extension auxiliary switch	Yes				
insulation voltage with degree of pollution 3 at AC rated value	690 V				
degree of pollution	3				
surge voltage resistance rated value	6 kV				
shock resistance according to IEC 60068-2-27	6g / 11 ms				
mechanical service life (switching cycles) of contactor typical	10 000 000				
type of assignment	2				
Ambient conditions					
ambient temperature					
 during operation 	-20 +60 °C				
 during storage 	-50 +80 °C				
 during transport 	-55 +80 °C				
Main circuit					
number of poles for main current circuit	3				
design of the switching contact	electromechanical				
adjustable current response value current of the current-dependent overload release	2.8 4 A				
operating voltage					
 rated value 	690 V				
 at AC-3 rated value maximum 	690 V				
operating frequency rated value	50 60 Hz				
operational current at AC-3 at 400 V rated value	3.6 A				
operating power at AC-3					
• at 400 V rated value	1 500 W				
• at 500 V rated value	2 200 W				
Control circuit/ Control					
control supply voltage at AC					
 at 50 Hz rated value 	220 V				

a at E0 Ha rated value	176 040.1/		
at 50 Hz rated value	176 242 V 240 V		
• at 60 Hz rated value			
at 60 Hz rated value	192 264 V		
apparent holding power of magnet coil at AC	7.2 VA		
inductive power factor with the holding power of the coil	0.28		
Auxiliary circuit			
number of NC contacts for auxiliary contacts	2		
number of NO contacts for auxiliary contacts	2		
Protective and monitoring functions			
trip class	CLASS 10		
design of the overload release	thermal (bimetallic)		
response value current of instantaneous short-circuit trip	52 A		
UL/CSA ratings			
full-load current (FLA) for 3-phase AC motor	0.0F A		
• at 480 V rated value	3.95 A		
at 600 V rated value	4 A		
 yielded mechanical performance [hp] for single-phase AC motor 			
tor single-phase AC motor at 110/120 V rated value	0.13 hp		
— at 230 V rated value	0.33 hp		
• for 3-phase AC motor	0.00 mp		
— at 200/208 V rated value	0.75 hp		
— at 220/230 V rated value	0.75 hp		
— at 460/480 V rated value	2 hp		
— at 575/600 V rated value	3 hp		
Short-circuit protection			
product function short circuit protection	Yes		
design of the short-circuit trip	magnetic		
conditional short-circuit current (lq)	indgriete		
• at 400 V according to IEC 60947-4-1 rated value	153 000 A		
····· · · · · · · · · · · · · · · · ·			
Installation/ mounting/ dimensions			
Installation/ mounting/ dimensions mounting position	vertical		
Installation/ mounting/ dimensions mounting position fastening method	vertical Snap-mounted to DIN rail or screw-mounted with additional push-in lug		
mounting position fastening method			
mounting position	Snap-mounted to DIN rail or screw-mounted with additional push-in lug		
mounting position fastening method height	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm		
mounting position fastening method height width	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm		
mounting position fastening method height width depth	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm		
mounting position fastening method height width depth required spacing	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm		
mounting position fastening method height width depth required spacing • for grounded parts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — upwards — downwards • for live parts — downwards — upwards — downwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 30 mm 10 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — upwards — at the side — downwards — a the side — upwards — a the side — upwards — at the side	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 30 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — upwards — downwards • for live parts — downwards — upwards — downwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 30 mm 10 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — downwards • for live parts — forwards — at the side — downwards — at the side — ownwards — backwards — upwards — backwards — upwards — downwards — at the side Connections/ Terminals type of electrical connection for main current circuit	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 30 mm 10 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — at the side — downwards — backwards — at the side — downwards — backwards — upwards — other side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 9 mm 10 mm 9 mm 10 mm 9 mm 10 mm 9 mm 10 mm 9 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — ownwards • for live parts — ownwards — at the side — downwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm 30 mm 10 mm 9 mm 10 mm 30 mm 10 mm 2 mm 30 mm 10 mm 10 mm 2 mm 30 mm 10 mm 2 mm 30 mm 10 mm 2 mm 30 m		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — upwards — a the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded • at AWG cables for main contacts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 0 mm 30 mm 9 mm 10 mm 9 mm 10 mm 9 mm 10 mm 9 mm 10 mm 9 mm screw-type terminals 1 10 mm², 2x (2.5 6 mm²) 2x (16 12), 2x (14 8)		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — downwards • for live parts — oforwards — upwards — at the side — downwards — backwards — upwards — backwards — upwards — backwards — upwards — downwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm 30 mm 10 mm 9 mm 10 mm 30 mm 10 mm 2 mm 30 mm 10 mm 10 mm 2 mm 30 mm 10 mm 2 mm 30 mm 10 mm 2 mm 30 m		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — upwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded • at AWG cables for main contacts connectable conductor cross-section for main contacts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 10 mm 0 mm 30 mm 10 mm 9 mm 10 mm 2 mm 10 mm 2 mm 10 mm 10 mm 2 mm 10 mm 2 x (2.5 6 mm ²) 2 x (16 12), 2 x (14 8)		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — ownwards • for live parts — forwards — upwards — downwards — upwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded • at AWG cables for main contacts connectable conductor cross-section for main contacts finely stranded with core end processing	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 10 mm 0 mm 30 mm 10 mm 9 mm 10 mm 2 mm 10 mm 2 mm 10 mm 10 mm 2 mm 10 mm 2 x (2.5 6 mm ²) 2 x (16 12), 2 x (14 8)		

proportion of dangerous failures with high demand rate according to SN 31920		73 %			
protection class IP on the front according to IEC 60529		IP20			
touch protection on the front according to IEC 60529		finger-safe, for vertical contact from the front			
Certificates/ approvals					
General Product Ap	proval	For use in ha ous locations		Declaration of Conformity	other
<u>Confirmation</u>	EAC	(Ex)		CE EG-Konf.	<u>Confirmation</u>

Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2125-1EA23-0AP6

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2125-1EA23-0AP6

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-1EA23-0AP6

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)


http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RA2125-1EA23-0AP6&lang=en

Characteristic: Tripping characteristics, I²t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-1EA23-0AP6/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2125-1EA23-0AP6&objecttype=14&gridview=view1



last modified:

12/15/2020 🖸