SIEMENS

Data sheet

3RA2120-1EA23-0AP6



Fuseless motor starter Direct start 600VAC Size S0 2.8-4A 220/240VAC 50/60HZ screw connection For screw mounting Or 35 mm rail-mounting Type of coordination 2 IQ = 150 KA Also full fills type Of coordination 1 1NO+1NC (contactor)

product brand name	SIRIUS			
product designation	non-fused motor starter 3RA2			
design of the product	direct starter			
manufacturer's article number				
 of the supplied contactor 	<u>3RT2023-1AP60</u>			
 of the supplied circuit-breakers 	<u>3RV2011-1EA10</u>			
 of the supplied link module 	<u>3RA2921-1AA00</u>			
General technical data				
size of the circuit-breaker	S00			
size of load feeder	S0			
product extension auxiliary switch	Yes			
insulation voltage with degree of pollution 3 at AC rated value	690 V			
degree of pollution	3			
surge voltage resistance rated value	6 kV			
shock resistance according to IEC 60068-2-27	6g / 11 ms			
mechanical service life (switching cycles) of contactor typical	10 000 000			
type of assignment	2			
Ambient conditions				
ambient temperature				
 during operation 	-20 +60 °C			
 during storage 	-50 +80 °C			
 during transport 	-55 +80 °C			
Main circuit				
number of poles for main current circuit	3			
design of the switching contact	electromechanical			
adjustable current response value current of the current-dependent overload release	2.8 4 A			
operating voltage				
 rated value 	690 V			
 at AC-3 rated value maximum 	690 V			
operating frequency rated value	50 60 Hz			
operational current at AC-3 at 400 V rated value	3.6 A			
operating power at AC-3				
• at 400 V rated value	1 500 W			
• at 500 V rated value	2 200 W			
Control circuit/ Control				
control supply voltage at AC				
 at 50 Hz rated value 	220 V			

a at E0. Ha rated value	176 040 1/		
at 50 Hz rated value	176 242 V		
• at 60 Hz rated value	240 V		
at 60 Hz rated value	192 264 V 7.2 VA		
apparent holding power of magnet coil at AC			
inductive power factor with the holding power of the coil	0.28		
Auxiliary circuit			
number of NC contacts for auxiliary contacts	1		
number of NO contacts for auxiliary contacts	1		
Protective and monitoring functions			
trip class	CLASS 10		
design of the overload release	thermal (bimetallic)		
response value current of instantaneous short-circuit trip	52 A		
unit			
UL/CSA ratings			
full-load current (FLA) for 3-phase AC motor			
at 480 V rated value	3.95 A		
at 600 V rated value	4 A		
yielded mechanical performance [hp]			
for single-phase AC motor at 110/120 V rated value	0.12 hp		
— at 110/120 V rated value	0.13 hp		
— at 230 V rated value	0.33 hp		
 for 3-phase AC motor — at 200/208 V rated value 	0.75 hz		
— at 220/208 V rated value	0.75 hp 0.75 hp		
— at 460/480 V rated value	2 hp		
— at 575/600 V rated value	3 hp		
Short-circuit protection	5 hp		
product function short circuit protection	Yes		
design of the short-circuit trip	magnetic		
conditional short-circuit current (lq)	magnetic		
• at 400 V according to IEC 60947-4-1 rated value	153 000 A		
	100 000 //		
Installation/mounting/dimensions			
Installation/ mounting/ dimensions	vertical		
mounting position	vertical Snap-mounted to DIN rail or screw-mounted with additional push-in lug		
mounting position fastening method	Snap-mounted to DIN rail or screw-mounted with additional push-in lug		
mounting position			
mounting position fastening method height	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm		
mounting position fastening method height width	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm		
mounting position fastening method height width depth	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm		
mounting position fastening method height width depth required spacing	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm		
mounting position fastening method height width depth required spacing • for grounded parts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards • for live parts — backwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — upwards • for live parts — upwards — upwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 30 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — upwards — downwards • for live parts — downwards — upwards — downwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 30 mm 10 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — upwards — at the side — downwards — at the side	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 30 mm 10 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — at the side — downwards — backwards — at the side — downwards — backwards — upwards — other side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 10 mm 10 mm 10 mm 9 mm 10 mm 9 mm 30 mm 9 mm 10 mm 9 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — ownwards • for live parts — ownwards — at the side — downwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm 30 mm 10 mm 9 mm 10 mm 30 mm 10 mm 9 mm 10 mm 2 x (2.5 6 mm ²)		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — upwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded • at AWG cables for main contacts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 10 mm 0 mm 30 mm 10 mm 9 mm 10 mm 2 mm 10 mm ² , 2x (2.5 6 mm ²) 2x (16 12), 2x (14 8)		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — ownwards • for live parts — ownwards — at the side — downwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm 30 mm 10 mm 9 mm 10 mm 30 mm 10 mm 2 mm 30 mm 10 mm 10 mm 2 mm 30 mm 10 mm 10 mm 2 mm 30 mm 10 mm 10 mm 2 mm 30 mm 10 mm 10 mm 2 mm 30 mm		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — upwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded • at AWG cables for main contacts connectable conductor cross-section for main contacts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 10 mm 0 mm 30 mm 10 mm 9 mm 10 mm 2 mm 10 mm 2 mm 10 mm 2 mm 10 mm 2 mm 10 mm 2 x (2.5 6 mm ²) 2 x (16 12), 2 x (14 8)		
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — ownwards • for live parts — forwards — upwards — downwards — upwards — at the side Connections/ Terminals type of electrical connection for main current circuit type of connectable conductor cross-sections • for main contacts stranded • at AWG cables for main contacts connectable conductor cross-section for main contacts finely stranded with core end processing	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 10 mm 0 mm 30 mm 10 mm 9 mm 10 mm 2 mm 10 mm 2 mm 10 mm 2 mm 10 mm 2 mm 10 mm 2 x (2.5 6 mm ²) 2 x (16 12), 2 x (14 8)		

proportion of dangerous failures with high demand rate according to SN 31920		73 %	73 %		
protection class IP on the front according to IEC 60529		IP20			
touch protection on the front according to IEC 60529		finger-safe, for vertical contact from the front			
Certificates/ approvals					
General Product Approval	For use in ha		Declaration of Conformity	other	
<u>Confirmation</u>	(Ex)	•	CE EG-Konf.	Confirmation	

Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2120-1EA23-0AP6

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2120-1EA23-0AP6

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2120-1EA23-0AP6

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RA2120-1EA23-0AP6&lang=en

Characteristic: Tripping characteristics, I²t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2120-1EA23-0AP6/char

Further characteristics (e.g. electrical endurance, switching frequency) http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2120-1EA23-0AP6&objecttype=14&gridview=view1

last modified:

12/15/2020