

## E26 6" Trim Series


## DESCRIPTION

Full cone baffle trim with self-flange in the 6" trim family for use in recessed downlighting. Compatible for use in Halo and other housings.

|             |  |      |
|-------------|--|------|
| Catalog #   |  | Type |
| Project     |  |      |
| Comments    |  | Date |
| Prepared by |  |      |

## SPECIFICATION FEATURES

- Full cone baffle for BR30, BR40, A19, PAR30 and PAR38 lamps
- Torsion spring retention
- Socket supporting baffle
- Self-flanged trim ring sized to hide gaps caused by construction tolerances
- Makes installation Air-Tite, with any compatible housing



## Dimensions:

A: 5-7/16" [138mm]

H: 5-3/8" [137mm]


OD: 7-3/4" [197mm]

| Housings |         | Max Lamp Compatibility                                                                                                                                                     |
|----------|---------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| H7ICT    | H7RICT  | <b>6125WB:</b> 43W A19, 75W PAR30S, 75W PAR30L, 65W PAR38, 65W BR30, 90W BR40                                                                                              |
| H7ICAT   | H7RICAT | <b>6125BB, 6125BKBB:</b> 43W A19, 75W PAR30S, 75W PAR30L, 65W PAR38, 65W BR30, 85W BR40                                                                                    |
| E7ICAT   | E7RICAT |                                                                                                                                                                            |
| H7ICTNB  |         | <b>6125WB:</b> 43W A19, 75W PAR30S, 75W PAR30L, 65W PAR38, 65W BR30, 90W BR40                                                                                              |
| H7ICATNB |         | <b>6125BB, 6125BKBB:</b> 43W A19, 75W PAR30S, 75W PAR30L, 65W PAR38, 65W BR30, 85W BR40                                                                                    |
| E7ICATNB |         |                                                                                                                                                                            |
| H7T      | E7TAT   | 100W A19, 150W A21, 75W PAR30S, 75W PAR30L, 150W PAR38, 85W BR30, 120W BR40                                                                                                |
| H7RT     | E7RTAT  | 100W A19, 150W A21, 75W PAR30S, 75W PAR30L, 100W PAR38, 85W BR30, 120W BR40                                                                                                |
| H7TCP    |         | <b>6125WB:</b> 75W A19, 150W A21, 75W PAR30S, 75W PAR30L, 120W PAR38, 65W BR30<br><b>6125BB, 6125BKBB:</b> 75W A19, 150W A21, 75W PAR30S, 75W PAR30L, 100W PAR38, 65W BR30 |
| H7TNB    | E7TATNB | 100W A19, 150W A21, 75W PAR30S, 75W PAR30L, 150W PAR38, 85W BR30, 120W BR40                                                                                                |


Compatible with Halogen, Incandescent, LED\* or CFL\* lamps.



**6125WB**  
White Baffle,  
White Trim



**6125BB**  
Black Baffle,  
White Trim



**6125BKBB**  
Black Baffle,  
Black Trim

**6125**

6-Inch Full Cone Baffle,  
Self-flange

## ORDERING INFORMATION

SAMPLE NUMBER: 6125WB

| Trim                                   | Finish                                                                                                        |
|----------------------------------------|---------------------------------------------------------------------------------------------------------------|
| 6125= 6" Full Cone Baffle, Self-flange | <b>WB</b> =White baffle and trim<br><b>BB</b> =Black baffle, White trim<br><b>BKBB</b> =Black baffle and trim |

## HALO HOUSING COMPATIBILITY

| Trim # | Style  | H7ICT    | H7ICAT   | H7RICT  | H7RICAT  | E7ICAT  | E7RICAT  | H7UICAT | H7ICTNB |
|--------|--------|----------|----------|---------|----------|---------|----------|---------|---------|
| 6125   | Baffle | •        | •        | •       | •        | •       | •        | —       | •       |
|        |        | H7ICATNB | E7ICATNB | H27ICAT | H27RICAT | E27ICAT | E27RICAT |         |         |
|        |        | •        | •        | —       | —        | —       | —        |         |         |
|        |        | H7T      | H7TCP    | H7RT    | E7TAT    | E7RTAT  | H7TNB    | E7TATNB | H27T    |
|        |        | •        | —        | •       | •        | •       | •        | •       | —       |
|        |        | H27RT    | E27TAT   | E27RTAT |          |         |          |         |         |
|        |        | —        | —        | —       |          |         |          |         |         |

For use in select other's housings, refer to U.L. classification list at [www.cooperlighting.com](http://www.cooperlighting.com).

\*UL1993 listed LED &amp; CFL equivalent lamps permitted. Consult lamp manufacturer for conditions of use. Cooper Lighting Solutions does not warranty the lamp.



For use in Halo listed housings.



Select trims are classified for use in  
others housings.  
See [www.cooperlighting.com](http://www.cooperlighting.com).