Product data sheet

Specifications

NEMA Motor Starter, Type S, replacement coil, 208VAC 60Hz, NEMA Size 00, 0 and 1 starters and 8903SM lighting

3104140048

Product availability: Stock - Normally stocked in distribution facility

Main

Product or Component Type	Coil
Accessory / separate part destination	Class 8502 type SA (series A)/SB/SC contactor Class 8536 type SA (series A)/SB/SC starter Class 8903 type SM lighting contactor

Complementary

NEMA size	0 00 1
[Ue] rated operational voltage	208 V AC 60 Hz
Inrush power in VA	245 VA
Average consumption	27 VA
Height	2.2 in (54.7 mm)
Width	3.2 in (81.5 mm)
Depth	1.9 in (48.3 mm)

Ordering and shipping details

Category	US1CP1018079
Discount Schedule	CP10
GTIN	785901107378
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.10 in (5.334 cm)
Package 1 Width	2.80 in (7.112 cm)
Package 1 Length	3.30 in (8.382 cm)
Package weight(Lbs)	7.040 oz (199.580 g)

Contractual warranty

Warranty	18 months

Price is “List Price” and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

Environmental Data explained

How we assess product sustainability

Use Better

Materials and Substances

Packaging made with recycled cardboard	**No**
Packaging without single use plastic	**No**
EU RoHS Directive	**Not applicable, out of EU RoHS legal scope**

Use Again

Repack and remanufacture

Take-back	**No**