Product data sheet

Specifications

NEMA Motor Starter, Type S, replacement coil, Series A, 110/120VAC 50/60Hz, NEMA size 5 starter and 8903SX lighting

3109640009

Product availability: Stock - Normally stocked in distribution facility

Main

Product or Component Type	Coil
Accessory / separate part destination	Class 8502 type SG contactor Class 8903 type SY/SX lighting contactor Class 8910 type SYD368 (series A) contactor

Complementary

NEMA size	5
[Ue] rated operational voltage	120 V AC 60 Hz 110 V AC 50 Hz
Inrush power in VA	2970 VA
Average consumption	212 VA 250 VA
Height	5.5 in (140.5 mm)
Width	4.0 in (101.2 mm)
Depth	1.8 in (45.3 mm)

Ordering and shipping details

Category	US1CP1018079
Discount Schedule	CP10
GTIN	785901326892
Returnability	Yes
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.10 in (10.414 cm)
Package 1 Width	5.70 in (14.478 cm)
Package 1 Length	6.20 in (15.748 cm)
Package 1 Weight	2.630 lb(US) (1.193 kg)
Unit Type of Package 2	PAL
Number of Units in Package 2	25
Package 2 Height	40.00 in (101.6 cm)

Price is “List Price” and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Package 2 Width	40.00 in (101.6 cm)
Package 2 Length	48.00 in (121.92 cm)
Package 2 Weight	66.000 lb(US) (29.937 kg)

Contractual warranty

Warranty	18 months

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

Environmental Data explained

How we assess product sustainability

Use Better

Materials and Substances

Packaging made with recycled cardboard	**No**
Packaging without single use plastic	**No**

Use Again

Repack and remanufacture

Take-back	**No**