Product data sheet

Specifications

Panelboard accessory, NQ/NF, neutral terminal kit, 200A, AWG 4-300

NQ200AN

Product availability: Stock - Normally stocked in distribution facility

Main

Range of Product	Square D
Product	Terminal kit
Provided equipment	Lug 1 Screw 2

Complementary

Device Application	neutral bar
Current Rating	200 A
Short-circuit withstand	22 kA
Wire Gauge	AWG 4...300 kcmil aluminium/copper
Tightening torque	274.4 lbf.in (31 N.m) 0.03…0.2 in² (21.2…152 mm²) (AWG 4...300 kcmil)

Ordering and shipping details

Category	US1DE3A00102
Discount Schedule	DE3A
GTIN	3606486139660
Returnability	No
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	3.03 in (7.7 cm)
Package 1 Width	7.48 in (19.0 cm)
Package 1 Length	7.48 in (19.0 cm)
Package weight(Lbs)	0.2 oz (4.6 g)

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Price is “List Price” and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

Environmental footprint

Environmental Disclosure	**Product Environmental Profile**

Use Better

Materials and Substances

Packaging made with recycled cardboard	**No**
Packaging without single use plastic	**No**
EU RoHS Directive	**Compliant**
REACh Regulation	**REACh Declaration**
California proposition 65	**WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov**

Use Again

Repack and remanufacture

Circularity Profile	**No need of specific recycling operations**
Take-back	**No**