Product data sheet

Specifications

Panelboard accessory, NF, condo riser neutral kit, 100%

NFN6CR

Product availability: Stock - Normally stocked in distribution facility

Main

Product	Neutral bar
Provided equipment	Neutral bar 2 Jumper bar 1 Screws 12

Complementary

Number of circuits	72
Device Application	NF panelboard
Enclosure Width	26 in (660.4 mm) 26 in (660.4 mm)
Enclosure Depth	6 in (152.4 mm) 9 in (228.6 mm)
Short-circuit withstand	200 kA
Wire Gauge	AWG 3/0...750 kcmil

Ordering and shipping details

Category	US1PE1A08338
Discount Schedule	PE1A
GTIN	3606486139455
Returnability	No
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	14.50 in (36.83 cm)
Package 1 Width	6.50 in (16.51 cm)
Package 1 Length	31.250 in (79.375 cm)
Package weight(Lbs)	20.9 lb(US) (9.5 kg)

Contractual warranty

Warranty (in months)	18

Price is “List Price” and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

Environmental Data explained

How we assess product sustainability

Use Better

Materials and Substances

Packaging made with recycled cardboard	**No**
Packaging without single use plastic	**No**
EU RoHS Directive	**Compliant**
REACh Regulation	**REACh Declaration**
California proposition 65	**WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov**

Use Again

Repack and remanufacture

Take-back	**No**