Product data sheet

Specifications

Load center interior, QO, mounting base, 1 phase, 12 spaces, 125A main lugs, PoN, OEM, neutral busbar

QON112L125PI

Product availability: Stock - Normally stocked in distribution facility

Main

Product Type	Mounting base
Marketing Trade Name	QO
Load Center Type	PoN Convertible Mains (lugs)
Rated Current	125 A
Number of Spaces	12
Max Short Circuit Current Rating	10 kA
Number of Phases	1 phase 3 wires
Voltage Rating	120/240 V AC

Complementary

Wire Size	AWG 6...AWG 2/0 aluminium/copper
Height	8.6 in (218 mm)
Width	10.6 in (270 mm)
Depth	2.3 in (58 mm)
Net Weight	1.499 lb(US) (0.680 kg)

Environment

Ambient Air Temperature for Operation	23 °F (-5 °C) 104 °F (40 °C)

Ordering and shipping details

Category	US1DE3A00909
Discount Schedule	DE3A
GTIN	785901453529
Returnability	Yes
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	8.6 in (21.8 cm)
Package 1 Width	10.6 in (27.0 cm)

Price is “List Price” and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Package 1 Length	2.4 in (6.0 cm)
Package weight(Lbs)	1.968 oz (55.792 g)

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

Environmental footprint

Environmental Disclosure	Product Environmental Profile

Use Better

Materials and Substances

Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant
REACh Regulation	REACh Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

Repack and remanufacture

Circularity Profile	No need of specific recycling operations
Take-back	No