

BALANCE

Wall or ceiling mounted • Damp location listed

Specifications:

Description:

Create harmony in a variety of environments with Balance's clean design and environmentally friendly architectural styling. Soft acrylic lens and a brushed nickel finish are highlights of the two-light Energy Star LED fixture. Fixtures can be wall or ceiling mounted. Can be installed vertically or horizontally. 3000K, 90+ CRI, 623 lumens per module.

Construction:

Brushed Nickel (-09) (plated)
 Steel construction
 Glass: White acrylic diffuser
 LED Module is replaceable (part # 93054049)
 Flicker-free dimming to 10% brightness with most ELV type dimmers
 (See Dimming Notes)
 Title 24 compliant
 Back plate covers a standard 4" hexagonal recessed outlet box
 10-7/16" W., 4-13/16"ht., 13/16"depth
 Mounting plate for outlet box included
 6" of wire supplied

Performance:

Number of Modules	2
Input Power	9W
Input Voltage	120V
Input Frequency	60Hz
Lumens/LPW	623/69.2 (LM-79) per module
CCT	3000K
CRI	90
Life	60,000 (L70/TM-21)
EMI/RFI	FCC Title 47, Part 15, Class B
Min. Start Temp	-30° C
Max. Operating Temp	30° C
Warranty	5 year warranty
Labels	cCSAus Damp location listed
	ENERGY STAR® qualified

P2092-0930K9

Images:



Dimensions:

Width: 11-1/2"
 Height: 5"
 Depth: 3"
 H/CTR: 2-1/2"

Glass: 2-1/8"
 Length: 10-7/16"
 Height: 5"

Catalog number:

Base	Finish	Color Temp	CRI
P2092	09 - Brushed Nickel	30K - 3000K	9 - 90 CRI

P2092-0930K9

Dimming Notes:

P2092 is designed to be compatible with many Electronic Low Voltage (ELV-Reverse Phase) controls.

The following is a partial list of known compatible dimmer controls:

Electronic Low Voltage ELV Reverse Phase Controls

Lutron	Diva Series	(Part Number DVELV-300P)
Lutron	Nova T Series	(Part Number NTELV-300)
Lutron	Vierti Series	(Part Number VTELV-600)
Lutron		(Part Number MAELV-600)
Lutron		(Part Number SPELV-600)
Leviton		(Part Number AWRMG-EAW)
Leviton		(Part Number 6615-P)

Digital type dimmers are not recommended.

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation.

Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.