



## COUNTERBRITE®

The Hide-a-Lite CounterBrite combines a halogen lamp with a unique reflector design to provide a wide distribution of bright white light.

HIDE a LITE

- When mounted 18" above work surface, one unit will light approximately three feet of counter. Multiple units can be used to provide lighting throughout the kitchen.
- The Hide-a-Lite CounterBrite is 120v. No transformer is required.
- Multiple units can be direct wired from one outlet box. The unit comes complete with a two-level hi-lo switch and 50w E-11 mini-can halogen lamp.
- UL and CUL listed.

### FINISHES

- White - 30
- Black - 31

**P7533-30WB** White  
**P7533-31WB** Black  
 One-light direct wire halogen undercabinet.  
 4" W., 9-1/4" L.  
 Extends 1-1/2".  
 One 50w halogen lamp, E-11 mini-can base (included).



P7533-30WB



P7533-31WB

## 12-VOLT TRANSFORMERS

These magnetic transformers (except 60w) have a special feature to provide either 12 volts or greater output to compensate for loading and to maximize lamp life.

- All units are UL listed for dry locations.
- All but the P8604-31 unit can be mounted vertically or horizontally, and feature in-line secondary magnetic breakers to protect against short circuit.
- The P8655-31 Unit has two 300 watt circuits on the secondary and requires balanced loads on each for optimum operation.
- Switches and dimmers (induction type only) must be installed on the primary (input) side only of the low voltage transformers.
- Transformers can be loaded up to the maximum rating.
- All units feature overload protection.



P8604-31



P8655-31



P8652-31

PRODUCT NO.	FINISH	SIZE	CAPACITY	WATTAGE
<b>P8604-31</b>	Black	3-1/2" W. 3-1/2" d.	5-1/4" ht.	60w
<b>P8652-31</b>	Black	3-1/2" W. 3-1/4" d.	8-1/2" ht.	100w
<b>P8653-31</b>	Black	4-1/8" W. 3-3/4" d.	8-1/2" ht.	150w
<b>P8654-31</b>	Black	4-1/8" W. 4-3/4" d.	8-1/2" ht.	300w
<b>P8655-31</b>	Black	5-1/8" W. 5-1/16" d.	11-1/2" ht.	600w (2-300w)