

Electronic/Glass Fuses

MIDGET, PC MOUNT & MINIATURE FUSES

GSA/GSA-V

- Ceramic body
- Time-delay
- 1/4" x 1-1/4"
- 1-1/2" Axial leads optional

1/16A through 8A, 250VAC, UL Listed

10, 12, 15A, 250V UL Recognized

1/16A through 8A, 250VAC, CSA Certified

10, 12, 15A, 250V CSA Recognized

20A, 250VAC, 25 & 30A, 125VAC



STANDARD FUSE AMPERE RATINGS

| Catalog Number | Axial Lead Cat. No | Ampere Rating | Volts | I.R. |
|----------------|--------------------|---------------|-------|------|
| GSA1/16 | GSA-V1/16 | 1/16A | 250V | 1 |
| GSA1/10 | GSA-V1/10 | 1/10A | 250V | 1 |
| GSA1/8 | GSA-V1/8 | 1/8A | 250V | 1 |
| GSA15/100 | GSA-V15/100 | 15/100A | 250V | 1 |
| GSA175/1000 | GSA-V175/1000 | 175/1000A | 250V | 1 |
| GSA3/16 | GSA-V3/16 | 3/16A | 250V | 1 |
| GSA2/10 | GSA-V2/10 | 2/10A | 250V | 1 |
| GSA1/4 | GSA-V1/4 | 1/4A | 250V | 1 |
| GSA3/10 | GSA-V3/10 | 3/10A | 250V | 1 |
| GSA3/8 | GSA-V3/8 | 3/8A | 250V | 1 |
| GSA4/10 | GSA-V4/10 | 4/10A | 250V | 1 |
| GSA1/2 | GSA-V1/2 | 1/2A | 250V | 1 |
| GSA6/10 | GSA-V6/10 | 6/10A | 250V | 1 |
| GSA7/10 | GSA-V7/10 | 7/10A | 250V | 1 |
| GSA3/4 | GSA-V3/4 | 3/4A | 250V | 1 |
| GSA8/10 | GSA-V8/10 | 8/10A | 250V | 1 |
| GSA1 | GSA-V1 | 1A | 250V | 1 |
| GSA1-1/4 | GSA-V1-1/4 | 1-1/4A | 250V | 2 |
| GSA1-1/2 | GSA-V1-1/2 | 1-1/2A | 250V | 2 |
| GSA1-6/10 | GSA-V1-6/10 | 1-6/10A | 250V | 2 |
| GSA2 | GSA-V2 | 2A | 250V | 2 |
| GSA2-1/4 | GSA-V2-1/4 | 2-1/4A | 250V | 2 |
| GSA2-1/2 | GSA-V2-1/2 | 2-1/2A | 250V | 2 |
| GSA2-8/10 | GSA-V2-8/10 | 2-8/10A | 250V | 2 |
| GSA3 | GSA-V3 | 3A | 250V | 2 |
| GSA3-2/10 | GSA-V3-2/10 | 3-2/10A | 250V | 2 |
| GSA3-1/2 | GSA-V3-1/2 | 3-1/2A | 250V | 2 |
| GSA4 | GSA-V4 | 4A | 250V | 3 |
| GSA5 | GSA-V5 | 5A | 250V | 3 |
| GSA6 | GSA-V6 | 6A | 250V | 3 |
| GSA6-1/4 | GSA-V6-1/4 | 6-1/4A | 250V | 3 |
| GSA7 | GSA-V7 | 7A | 250V | 3 |
| GSA8 | GSA-V8 | 8A | 250V | 3 |
| GSA10 | GSA-V10 | 10A | 250V | 4 |
| GSA12 | GSA-V12 | 12A | 250V | 4 |
| GSA15 | GSA-V15 | 15A | 250V | 4 |
| GSA20 | GSA-V20 | 20A | 250V | 5 |
| GSA25 | GSA-V25 | 25A | 125V | 6 |
| GSA30 | GSA-V30 | 30A | 125V | 6 |

1. 250VAC @ 35A I.R./125VAC @ 10kA I.R.
 2. 250VAC @ 100A I.R./125VAC @ 10kA I.R.
 3. 250VAC @ 200A I.R./125VAC @ 10kA I.R.
 4. 250VAC @ 750A I.R./125VAC @ 10kA I.R.
 5. 250VAC @ 400A I.R./125VAC @ 10kA I.R.
 6. 125VAC @ 400A I.R.