

Product data sheet

Characteristics

8538SFA23V06

COMBO STARTER 600VAC 135A NEMA

Product availability : Non-Stock - Not normally stocked in distribution facility



Price* : 8991.00 USD



Main

Product or component type	Combination Starter
Range of product	S
Control circuit	Common control circuit

Complementary

[Uc] control circuit voltage	440 V AC 50 Hz 480 V AC 60 Hz
Motor starter type	Non reversing
Poles description	3P
Motor power hp	100 hp 460 V AC 3 phases 100 hp 575 V AC 3 phases
System Voltage	600 V AC
Control type	No control units
Local signalling	No indicator
Auxiliary contact composition	Without
Thermal overload type	Melting alloy 3 Thermal Units
Disconnecter device type	Fusible disconnect switch, Type H Fuse, 200 A
NEMA size	4

Environment

NEMA degree of protection	NEMA 12 painted sheet steel and with external reset
---------------------------	---

Ordering and shipping details

Category	21214 - 8538,39 SE,SF(NOT S*R,T,W)
Discount Schedule	CP1
GTIN	00785901762607
Nbr. of units in pkg.	1

Package weight(Lbs)	170
Returnability	Y
Country of origin	MX

Offer Sustainability

RoHS (date code: YYWW)	Will not be compliant Will not be compliant
REACH	Reference not containing SVHC above the threshold Reference not containing SVHC above the threshold

Contractual warranty

Warranty period	18 months
-----------------	-----------