LA1LC072F

TeSys Integral - undervoltage trip - 110 V AC 50 Hz - without time delay



Main	
Range	TeSys
Device short name	LA1LC
Product or component type	Undervoltage trip
Product compatibility	LD5 LD4
Range compatibility	TeSys Integral contactor breaker

Complementary

[Uc] control circuit voltage	110 V AC 50 Hz	
	110120 V AC 60 Hz	
Time delay	Without time delay	
Voltage release type	Undervoltage release	
	Instantaneous	
Control circuit voltage limits	0.81.1 Uc	
Threshold tripping voltage	0.350.7 Uc	
Inrush power in VA	8 VA AC	
Hold-in power consumption in VA	4 VA AC	
Quantity per set	Set of 10	
Net Weight	0.33 lb(US) (0.15 kg)	

Ordering and shipping details

Packing Units

Unit Type of Package 1	PCE	
Package 1 Height	1.73 in (4.4 cm)	
Package 1 width	2.48 in (6.3 cm)	
Package 1 Length	4.53 in (11.5 cm)	

Offer Sustainability

California proposition 65	WARNING: This product can expose you to chemicals including: Styrene which is known to the State of California to cause Carcinogen harm. For more information go to www.p65warnings.ca.gov
REACh free of SVHC	Yes
EU RoHS Directive	Compliant
Toxic heavy metal free	Yes
Mercury free	Yes
RoHS exemption information	₫Yes
China RoHS Regulation	China RoHS Declaration
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.

Contractual warranty

	· · · · · · · · · · · · · · · · · · ·
Warranty	40
VVarrantv	18 months
	The state of the s