



### Main

Range	TeSys
Product or component type	Coil
Range compatibility	TeSys Integral contactor breaker
Device short name	LX1
Control circuit type	AC 60 Hz
[Uc] control circuit voltage	110 V AC 60 Hz
Average resistance	4.88 Ohm 68 °F (20 °C)
Inductance of closed circuit	1 H

### Complementary

Control circuit voltage limits	Operational 0.85...1.1 Uc 131 °F (55 °C)) Drop-out 0.25...0.7 Uc 131 °F (55 °C))
Inrush power in VA	420...500 VA 60 Hz 0.55
Hold-in power consumption in VA	24...36 VA 60 Hz 0.28

### Environment

Net Weight	0.66 lb(US) (0.3 kg)
------------	----------------------

### Ordering and shipping details

Category	22384 - STARTERS,INTEGRAL,ACCESS
Discount Schedule	I11
GTIN	03389110246476
Nbr. of units in pkg.	1
Package weight(Lbs)	0.66 lb(US) (0.30 kg)
Returnability	No
Country of origin	FR

### Packing Units

Package 1 Height	0.750 dm
Package 1 width	0.750 dm
Package 1 Length	1.000 dm

### Offer Sustainability

California proposition 65	WARNING: This product can expose you to chemicals including: Antimony oxide & Antimony trioxide which is known to the State of California to cause Carcinogen harm. For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>
---------------------------	---

### Contractual warranty

Warranty	18 months
----------	-----------