



Main

Product	Starter
Range of product	TeSys N
Current Rating	135 A
Certifications	UL Listed CSA CE
Control Circuit Type	Common control circuit
Enclosure Type	Not rated (open device)
Auxiliary Contacts	1 NO
Horsepower Rating	40 HP 200 V AC 50 HP 230 V AC 100 HP 460 V AC 100 HP 575 V AC
Number of Poles	3P
Phase	3 phase
Maximum Voltage Rating	600 V AC
NEMA Size	4
Control Circuit Voltage	240 V AC
Starter Type	Reversing
Electrical Connection	Lugs ordered separately
Overload Type	Solid state Motor Logic class 10/20

Ordering and shipping details

Category	21199 - TESYS N STARTERS SIZES 3 - 7
Discount Schedule	CP1
Package weight(Lbs)	28.6 lb(US) (12.97 kg)
Returnability	No
Country of origin	CZ

Offer Sustainability

EU RoHS Directive	Under investigation
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.

The information provided in this documentation contains general descriptions and/or technical characteristics of the products of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.