

8539SHG5V08

NEMA Combination Starter, Type S, 800A MJL thermal magnetic circuit breaker, Size 6, 540A, 3 phase, 208 VAC coil, NEMA 1



Main

Product	Combination Starter
Type	S
Control Circuit Type	Common control circuit

Complementary

Control Circuit Voltage	208 V AC 60 Hz
Starter Type	Non reversing
Number of Poles	3P
Horsepower Rating	400 Hp 575 V AC, 3 phase 150 Hp 200 V AC, 3 phase 150...200 Hp 230 V AC, 3 phase 300...400 hp 460 V AC, 3 phase
Maximum Voltage Rating	600 V AC
Control Units	No control units
Pilot Light	No indicator
Auxiliary Contacts	Without
Thermal overload type	Melting alloy 3
Disconnect Type	Thermal magnetic circuit breaker, 600 A

Environment

Enclosure Type	NEMA 1 painted sheet steel with external reset
NEMA size	6

Ordering and shipping details

Category	21216 - 8538,39 SH,SJ(NOT S*R,T,W)
Discount Schedule	CP1
Nbr. of units in pkg.	1
Package weight(Lbs)	420 lb(US) (190.51 kg)
Returnability	Yes
Country of origin	MX

Offer Sustainability

EU RoHS Directive	Not compliant
-------------------	---------------

Contractual warranty

Warranty	18 months
----------	-----------