Product data sheet Characteristics

6210AXXTZS-DC3

Relay, Legacy, solid state, SPST NO, 10A, 24...280 VAC, 3...32 VDC Uc, triac AC zero cross, screw terminal



Main Range Legacy Product Type Solid state relay Nominal Output Current 10 A for AC Network Number of Phases Mounting Support Panel Output Voltage 24...280 V AC

3...32 V DC

Complementary

| 15 mA |
|--|
| 10 mA 12 V DC typical |
| SPST |
| NO |
| Current limiter |
| 10 lb.in input 20 lb.in output |
| Input screw clamp terminal, 1 Output screw clamp terminals, 1 |
| M3.5 M4 |
| Input status 1 LED green) |
| Triac output Zero voltage switching |
| 100 A 16.6 ms |
| 1 V |
| <1.6 V on-state for AC |
| With maximum load |
| 1 GΩ |
| 1.48 °C/W |
| 60 A².s |
| 1 mA at off-state |
| 500 V/µs off-state at maximum rated voltage |
| 8.33 ms turn-on, turn-off) |
| 4000 V between input and ground 4000 V between output and ground 4000 V between input and output |
| 1.39 in (35.3 mm) |
| 1.85 in (47.1 mm) |
| 2.30 in (58.4 mm) |
| 3.05 oz (86.5 g) |
| |

Control Circuit Voltage

Environment

| UL CSA CE | | |
|-----------------------|--|--|
| IP20 | | |
| -40176 °F (-4080 °C) | | |
| -40257 °F (-40125 °C) | | |
| | | |

Ordering and shipping details

| GTIN | 03606480277276 |
|------|----------------|
| OTIN | 03000400211210 |

| Offer Sustainability | |
|----------------------------|---|
| California proposition 65 | WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov |
| REACh Regulation | REACh Declaration |
| EU RoHS Directive | Pro-active compliance (Product out of EU RoHS legal scope) EU RoHS Declaration |
| Mercury free | Yes |
| RoHS exemption information | ₫Yes |
| China RoHS Regulation | China RoHS Declaration |
| WEEE | The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins. |
| | |

Connections and Wiring Diagrams

