8538SBG62V02

NEMA Combination Starter, Type S, 30A fusible disconnect, Size 0, 18A, 1 HP at 120 VAC single phase, 120VAC coil, NEMA 1



Main

Product	Combination Starter	
Туре	S	
Control Circuit Type	Common control circuit	

Complementary

Complementary		
Control Circuit Voltage	110 V AC 50 Hz	
	120 V AC 60 Hz	
Starter Type	Non reversing	
Number of Poles	2P	
Horsepower Rating	1 hp 120 V AC, 1 phase	
Maximum Voltage Rating	600 V AC	
Control Units	No control units	
Pilot Light	No indicator	
Auxiliary Contacts	Without	
Thermal overload type	Melting alloy 1	
Disconnect Type	Fusible disconnect switch H, 30 A	
NEMA size	0	

Environment

Enclosure Type	NEMA 1 painted sheet steel with external reset

Ordering and shipping details

Category	21212 - 8538,39SB(NOT S*R,S*T,S*W)	
Discount Schedule	CP1	
GTIN	785901784722	
Nbr. of units in pkg.	1	
Package weight(Lbs)	29.81 lb(US) (13.52 kg)	
Returnability	Yes	
Country of origin	MX	

Offer Sustainability

California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov
REACh Regulation	☑ REACh Declaration
EU RoHS Directive	Not compliant
China RoHS Regulation	China RoHS Declaration

Warranty 18 months