# 8538SBG12V01S

NEMA Combination Starter, Type S, 30A fusible disconnect, Size 0, 18A, 3 HP at 240 VAC polyphase, 24 VAC coil, NEMA 1



### Main

Product	Combination Starter
Туре	S
Control Circuit Type	Separate control circuit

### Complementary

Complementary	
Control Circuit Voltage	24 V AC 60 Hz
Starter Type	Non reversing
Number of Poles	3P
Horsepower Rating	3 Hp 200 V AC, 3 phase 3 hp 230 V AC, 3 phase
Maximum Voltage Rating	600 V AC
Control Units	No control units
Pilot Light	No indicator
Auxiliary Contacts	Without
Thermal overload type	Melting alloy 3
Disconnect Type	Fusible disconnect switch H, 30 A
NEMA size	0

#### Environment

Enclosure Type	NEMA 1 painted sheet steel with external reset

### Ordering and shipping details

Category	21212 - 8538,39SB(NOT S*R,S*T,S*W)
Discount Schedule	CP1
GTIN	785901019763
Returnability	Yes
Country of origin	MX

## **Packing Units**

PCE	
1	
10.50 in (26.67 cm)	
13.00 in (33.02 cm)	
29.00 in (73.66 cm)	
34.42 lb(US) (15.613 kg)	
	1 10.50 in (26.67 cm) 13.00 in (33.02 cm) 29.00 in (73.66 cm)

# Offer Sustainability

California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov
REACh Regulation	☑ REACh Declaration
EU RoHS Directive	Not compliant
China RoHS Regulation	China RoHS Declaration

### Contractual warranty

Warranty	18 months
----------	-----------