

Product data sheet

Characteristics

8538SBW63V02

NEMA Combination Starter, Type S, 30A
fusible disconnect, Size 0, 18A, 1 HP at
120VAC single phase, 120VAC coil, NEMA 4X



Main

Product	Combination Starter
Type	S
Control Circuit Type	Common control circuit

Complementary

Control Circuit Voltage	110 V AC 50 Hz 120 V AC 60 Hz
Starter Type	Non reversing
Number of Poles	2P
Horsepower Rating	1 hp 120 V AC, 1 phase
Maximum Voltage Rating	600 V AC
Control Units	No control units
Pilot Light	No indicator
Auxiliary Contacts	Without
Thermal overload type	Melting alloy 1
Disconnect Type	Fusible disconnect switch R, 30 A
NEMA size	0

Environment

Enclosure Type	NEMA 4/4X Stainless Steel with external reset
----------------	---

Ordering and shipping details

Category	21212 - 8538,39SB(NOT S*R,S*T,S*W)
Discount Schedule	CP1
GTIN	785901928485
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Weight	35.32 lb(US) (16.023 kg)

Offer Sustainability

EU RoHS Directive	Not compliant
-------------------	---------------

Contractual warranty

Warranty	18 months
----------	-----------