T36BN13G7

Motor Starter, TeSys NEMA, nonreversing, Size 0, 18A, 3 pole, HP rated, Motor Logic SSOLR, 120 VAC 60 Hz coil, open



Main

Product	Starter
Range of Product	TeSys N
Current Rating	18 A
Certifications	UL Listed[RETURN]CSA
Control Circuit Type	Common control circuit
Enclosure Type	Not rated (open device)
Auxiliary Contacts	1 NO + 1 NC
Horsepower Rating	3 HP 200 V AC 3 HP 230 V AC 5 HP 460 V AC 5 HP 575 V AC
Number of Poles	3P
Phase	3 phase
Maximum Voltage Rating	600 V AC
NEMA Size	0
Control Circuit Voltage	120 V AC
Starter Type	Non reversing
Electrical Connection	Screw clamp terminals
Overload Type	Solid state Motor Logic class 10/20 618 A

Ordering and shipping details

are arrived arrived arrived and arrived arrive		
Category	21198-TESYS N STARTERS SIZES 00 - 2	
Discount Schedule	CP1	
GTIN	785901990284	
Returnability	No	
Country of origin	US	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Weight	5.92 lb(US) (2.685 kg)

Offer Sustainability

California proposition 65	WARNING: Cancer and Reproductive Harm - www.P65Warnings.ca.gov
REACh Regulation	[™] REACh Declaration
REACh free of SVHC	Yes
EU RoHS Directive	Compliant with Exemptions
Mercury free	Yes
China RoHS Regulation	China RoHS Declaration
RoHS exemption information	₽¥Yes

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the releva Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.