SIEMENS

Data sheet

3RT2017-4AB02



power contactor, AC-3 12 A, 5.5 kW / 400 V 1 NC, 24 V AC, 50 / 60 Hz 3-pole, Size S00 ring cable lug connection


product brand name	SIRIUS
product designation	Power contactor
product type designation	3RT2
General technical data	0.112
size of contactor	S00
product extension	
function module for communication	No
auxiliary switch	Yes
power loss [W] for rated value of the current	
at AC in hot operating state	1.5 W
 at AC in hot operating state per pole 	0.5 W
without load current share typical	5.7 W
insulation voltage	
 of main circuit with degree of pollution 3 rated value 	690 V
 of auxiliary circuit with degree of pollution 3 rated 	690 V
value	
surge voltage resistance	
 of main circuit rated value 	6 kV
 of auxiliary circuit rated value 	6 kV
maximum permissible voltage for safe isolation between coil and main contacts according to EN 60947-1	400 V
shock resistance at rectangular impulse	
• at AC	7,3g / 5 ms, 4,7g / 10 ms
shock resistance with sine pulse	
• at AC	11,4g / 5 ms, 7,3g / 10 ms
mechanical service life (switching cycles)	
 of contactor typical 	30 000 000
 of the contactor with added electronically optimized auxiliary switch block typical 	5 000 000
 of the contactor with added auxiliary switch block typical 	10 000 000
reference code according to IEC 81346-2	Q
Substance Prohibitance (Date)	10/01/2009
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
 during operation 	-25 +60 °C
during storage	-55 +80 °C
relative humidity minimum	10 %
relative humidity at 55 °C according to IEC 60068-2-30 maximum	95 %


Main circuit	
number of poles for main current circuit	3
number of NO contacts for main contacts	3
operating voltage	
 at AC-3 rated value maximum 	690 V
 at AC-3e rated value maximum 	690 V
operational current	
 at AC-1 at 400 V at ambient temperature 40 °C rated value 	22 A
• at AC-1	
— up to 690 V at ambient temperature 40 °C rated value	22 A
— up to 690 V at ambient temperature 60 °C rated value	20 A
• at AC-3	
— at 400 V rated value	12 A
— at 500 V rated value	9.2 A
— at 690 V rated value	6.7 A
• at AC-3e	
— at 400 V rated value	12 A
— at 500 V rated value	9.2 A
— at 690 V rated value	6.7 A
• at AC-4 at 400 V rated value	8.5 A
 at AC-5a up to 690 V rated value 	19.4 A
• at AC-5b up to 400 V rated value	9.9 A
• at AC-6a	
 up to 230 V for current peak value n=20 rated value 	7.2 A
 up to 400 V for current peak value n=20 rated value 	7.2 A
— up to 500 V for current peak value n=20 rated value	7.2 A
 up to 690 V for current peak value n=20 rated value 	6.7 A
 at AC-6a up to 230 V for current peak value n=30 rated value 	4.8 A
 up to 400 V for current peak value n=30 rated value 	4.8 A
 up to 500 V for current peak value n=30 rated value 	4.8 A
— up to 690 V for current peak value n=30 rated value	4.8 A
minimum cross-section in main circuit at maximum AC-1 rated value operational current for approx. 200000 operating	4 mm ²
cycles at AC-4	
• at 400 V rated value	4.1 A
• at 690 V rated value	3.3 A
operational current	
at 1 current path at DC-1	
— at 24 V rated value	20 A
— at 110 V rated value	2.1 A
— at 220 V rated value	0.8 A
— at 440 V rated value	0.6 A
— at 600 V rated value	0.6 A
 with 2 current paths in series at DC-1 	
- at 24 V rated value	20 A
— at 110 V rated value	12 A
	1.6 A
— at 220 V rated value	
— at 440 V rated value	0.8 A
— at 600 V rated value	0.7 A
 with 3 current paths in series at DC-1 	


	20.4
— at 24 V rated value	20 A
— at 110 V rated value	20 A
— at 220 V rated value	20 A
— at 440 V rated value	1.3 A
— at 600 V rated value	1 A
 at 1 current path at DC-3 at DC-5 	
— at 24 V rated value	20 A
— at 110 V rated value	0.1 A
 with 2 current paths in series at DC-3 at DC-5 	
— at 24 V rated value	20 A
— at 110 V rated value	0.35 A
 with 3 current paths in series at DC-3 at DC-5 	
— at 24 V rated value	20 A
— at 110 V rated value	20 A
— at 220 V rated value	1.5 A
— at 440 V rated value	0.2 A
— at 600 V rated value	0.2 A
operating power	
at AC-2 at 400 V rated value	5.5 kW
• at AC-3	
— at 230 V rated value	3 kW
— at 400 V rated value	5.5 kW
— at 500 V rated value	5.5 kW
— at 690 V rated value	5.5 kW
• at AC-3e	
— at 230 V rated value	3 kW
— at 400 V rated value	5.5 kW
— at 500 V rated value	5.5 kW
— at 690 V rated value	5.5 kW
operating power for approx. 200000 operating cycles	0.0 kW
at AC-4	
 at 400 V rated value 	2 kW
 at 690 V rated value 	2.5 kW
operating apparent power at AC-6a	
 up to 230 V for current peak value n=20 rated value 	2.8 kVA
 up to 400 V for current peak value n=20 rated value 	4.9 kVA
 up to 500 V for current peak value n=20 rated value 	6.2 kVA
 up to 690 V for current peak value n=20 rated value 	8 kVA
operating apparent power at AC-6a	
 up to 230 V for current peak value n=30 rated value 	1.9 kVA
• up to 400 V for current peak value n=30 rated value	3.3 kVA
• up to 500 V for current peak value n=30 rated value	4.1 kVA
• up to 690 V for current peak value n=30 rated value	5.7 kVA
short-time withstand current in cold operating state	
up to 40 °C	
 limited to 1 s switching at zero current maximum 	200 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 5 s switching at zero current maximum 	123 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 10 s switching at zero current maximum 	96 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 30 s switching at zero current maximum 	74 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 60 s switching at zero current maximum 	61 A; Use minimum cross-section acc. to AC-1 rated value
no-load switching frequency	
• at AC	10 000 1/h
operating frequency	
• at AC-1 maximum	1 000 1/h
• at AC-2 maximum	750 1/h
• at AC-3 maximum	750 1/h
• at AC-3e maximum	750 1/h
• at AC-4 maximum	250 1/h
Control circuit/ Control	
type of voltage of the control supply voltage	AC

	_
control supply voltage at AC	
• at 50 Hz rated value	24 V
at 60 Hz rated value	24 V
operating range factor control supply voltage rated value of magnet coil at AC	
• at 50 Hz	0.8 1.1
• at 60 Hz	0.85 1.1
apparent pick-up power of magnet coil at AC	
• at 50 Hz	37 VA
• at 60 Hz	33 VA
inductive power factor with closing power of the coil	
• at 50 Hz	0.8
• at 60 Hz	0.75
apparent holding power of magnet coil at AC	
● at 50 Hz	5.7 VA
• at 60 Hz	4.4 VA
inductive power factor with the holding power of the coil	
• at 50 Hz	0.25
• at 60 Hz	0.25
closing delay	
• at AC	9 35 ms
opening delay	
• at AC	7 13 ms
arcing time	10 15 ms
control version of the switch operating mechanism	Standard A1 - A2
Auxiliary circuit	
number of NC contacts for auxiliary contacts	1
instantaneous contact	
operational current at AC-12 maximum	10 A
operational current at AC-15	
at 230 V rated value	10 A
at 400 V rated value	3 A
at 500 V rated value	2 A
at 690 V rated value	1 A
operational current at DC-12	
• at 24 V rated value	10 A
at 48 V rated value	6 A
at 60 V rated value	6 A
• at 110 V rated value	3 A
• at 125 V rated value	2 A
• at 220 V rated value	1 A
at 600 V rated value	0.15 A
operational current at DC-13	
• at 24 V rated value	10 A
at 48 V rated value	2 A
• at 60 V rated value	2 A
at 110 V rated value	1A
at 125 V rated value	0.9 A
at 220 V rated value	0.3 A
at 600 V rated value	0.1 A
contact reliability of auxiliary contacts	1 faulty switching per 100 million (17 V, 1 mA)
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	44.0
at 480 V rated value	11 A
at 600 V rated value	11 A
yielded mechanical performance [hp]	
for single-phase AC motor	
— at 110/120 V rated value	0.5 hp
 — at 230 V rated value for 3-phase AC motor 	2 hp

at 200/208 V rated value	2 hn
- at 200/208 V rated value	3 hp
— at 220/230 V rated value — at 460/480 V rated value	3 hp
— at 575/600 V rated value	7.5 hp 10 hp
contact rating of auxiliary contacts according to UL	
Short-circuit protection	
design of the fuse link	
 for short-circuit protection of the main circuit 	
 with type of coordination 1 required 	gG: 50A (690V,100kA), aM: 20A (690V,100kA), BS88: 35A (415V,80kA)
— with type of assignment 2 required	gG: 20A (690V,100kA), aM: 16A (690V, 100kA), BS88: 20A (415V, 80kA)
 for short-circuit protection of the auxiliary switch required 	gG: 10 A (500 V, 1 kA)
Installation/ mounting/ dimensions	
mounting position	+/-180° rotation possible on vertical mounting surface; can be tilted
	forward and backward by +/- 22.5° on vertical mounting surface
fastening method	screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 60715
side-by-side mounting	Yes
height	58 mm
width	45 mm
depth	73 mm
required spacing	
with side-by-side mounting forwards	10 mm
— forwards	
— upwards	10 mm
— downwards — at the side	10 mm 0 mm
	0 mm
 for grounded parts forwards 	10 mm
— upwards	10 mm
— at the side	6 mm
— downwards	10 mm
• for live parts	10 1111
— forwards	10 mm
— upwards	10 mm
— downwards	10 mm
— at the side	6 mm
Connections/ Terminals	
type of electrical connection	
for main current circuit	Ring cable lug connection
 for auxiliary and control circuit 	ring terminal lug connection
 at contactor for auxiliary contacts 	Ring cable lug connection
 of magnet coil 	Ring cable lug connection
Safety related data	
product function	
 mirror contact according to IEC 60947-4-1 	Yes
B10 value with high demand rate according to SN 31920	1 000 000
proportion of dangerous failures	
 with low demand rate according to SN 31920 	40 %
 with high demand rate according to SN 31920 	73 %
failure rate [FIT] with low demand rate according to SN 31920	100 FIT
T1 value for proof test interval or service life according to IEC 61508	20 у
protection class IP on the front according to IEC 60529	IP00
suitability for use	
 safety-related switching OFF 	Yes
Certificates/ approvals	
General Product Approval	







last modified:

6/2/2022 🖸