

Multi-Gang Switch Boxes

2-1/2" Deep

Features

- 2-1/2" deep
- Welded
- Available with 1/2" and 3/4" Concentric KO's
- Available in 2 thru 6 gangs

Applications

- Use when more than two devices or outlets are required in one box
- Multi-Gang Switch boxes can be installed in walls or ceilings for lighting fixtures, switches, receptacles or other outlet devices
- Use to bring power to a number of electrical devices where multiple conductor runs are split in two or more directions




E195124
NEMA: OS-1




Standard Material


- Galvanized steel




MSB32
Concentric KO




MSB33
Concentric KO



MSB34
Concentric KO



MSB35
Concentric KO



MSB36
Concentric KO

Catalog Number	UPC	Description	Knockouts		Cubic Inches	Ship Case	Weight/Case
			Sides	Bottom			
MSB32	03148	2-1/2" deep, 2 gang	(12) - 1/2" & 3/4" CON	(4) - 1/2" & (2) - 3/4"	71	25	42
MSB33	03150	2-1/2" deep, 3 gang	(6) - 1/2" & 3/4" & (8) - 3/4" & 1" CON	(6) - 1/2" & (4) - 3/4"	90.50	20	40
MSB34	03151	2-1/2" deep, 4 gang	(6) - 1/2" & 3/4" & (10) - 3/4" & 1" CON	(6) - 1/2" & (4) - 3/4"	111.80	20	47
MSB35	03152	2-1/2" deep, 5 gang	(6) - 1/2" & 3/4" & (12) - 3/4" & 1" CON	(6) - 1/2" & (4) - 3/4"	128.50	10	27
MSB36	03153	2-1/2" deep, 6 gang	(6) - 1/2" & 3/4" & (14) - 3/4" & 1" CON	(6) - 1/2" & (4) - 3/4"	148	5	15