

4" Octagon Drawn Boxes and Extensions

1-1/2" deep

Features

- Drawn
- 1-1/2" deep
- 15.8 cu. in.
- Available in multiple KO sizes, with or without Concentric KOs and raised ground emboss with installed 10/32 ground screw where noted

Application

- 4" octagon junction boxes are used to install ceiling and wall lighting fixtures, fans or convenience outlets and devices
- Octagon boxes are used to bring power to an electrical device where multiple conductor runs are split in two or more directions

Standard Material

- Galvanized steel




LISTED
E195124

NEMA: OS-1



G4451


Raised ground emboss



G4452




G4453



G4454

Raised ground emboss &
10/32 Ground screw




G4455

Concentric KO with
Raised ground emboss
& 10/32 Ground screw



G2450

NM Clamp




G2451

MC Clamp




G2453

NM Clamp & Adj. Plaster Ears



EG411



EG412

Catalog Number	UPC	Description	Knockouts		Cubic Inches	Ship Case	Weight/Case
			Sides	Bottom			
G4451	86710	1-1/2" deep 1/2" KO	(4) - 1/2"	(4) - 1/2"	15.8	50	24
G4452	86711	1-1/2" deep 3/4" KO	(4) - 3/4"	(3) - 1/2" & (2) - 3/4"	15.8	50	26
G4453	86712	1-1/2" deep 1/2" & 3/4" KO	(2) - 1/2" & (2) - 3/4"	(5) - 1/2"	15.8	50	26
G4454	86713	1-1/2" deep 1/2" & 3/4" KO with raised ground emboss & 10/32 ground screw	(2) - 1/2" & (2) - 3/4"	(2) - 1/2" & (2) - 3/4"	15.8	50	28
G4455	86714	1-1/2" deep 1/2" & 3/4" Concentric KO with raised ground emboss & 10/32 ground screw	(4) - 1/2" & 3/4" CON	(2) - 1/2" & 3/4" CON (2) - 1/2"	15.8	50	28
G2450	87263	1-1/2" deep 1/2" KO with NM Clamp	(2) - 1/2" & 4 pryouts	(1) - 1/2"	15.8	50	26
G2451	01010	1-1/2" deep 1/2" KO with MC Clamp	(2) - 1/2" & 4 pryouts	(1) - 1/2"	15.8	50	27
G2453	01745	1-1/2" deep 1/2" KO with NM Clamp & adj. plaster ears	(2) - 1/2" & 4 pryouts	(1) - 1/2"	15.8	50	28
EXTENSIONS							
EG411	86715	1-1/2" deep 1/2" KO	(4) - 1/2"	---	15.8	50	19
EG412	86716	1-1/2" deep 1/2" & 3/4" KO	(2) - 1/2" & (2) - 3/4"	---	15.8	50	19